

# Unterschiede beim Kernel von CentOS und CentOSplus

Beim CentOS-Projekt hat man die Möglichkeit durch aktivieren des CentOSplus-Repos einen erweiterten Kernel zu installieren. Dieser beinhaltet mehr Treiber für verschiedene Erweiterungskarten und Spezialitäten wie Firewire- oder DVB(TV)-Unterstützung. Hier ein Diff der aktuellen CentOS-Kernel- und CentOSplus-Kernel-Config:

```
# #
# Automatically generated make config: don't edit # Automatically generated make config: don't
# Linux kernel version: 2.6.18-8.1.15.el5 | # Linux kernel version: 2.6.18-8.1.15.el5.cent
# Mon Oct 22 08:26:05 2007 | # Thu Oct 25 06:43:44 2007
# #
CONFIG_X86_32=y CONFIG_X86_32=y
CONFIG_GENERIC_TIME=y CONFIG_GENERIC_TIME=y
CONFIG_LOCKDEP_SUPPORT=y CONFIG_LOCKDEP_SUPPORT=y
CONFIG_STACKTRACE_SUPPORT=y CONFIG_STACKTRACE_SUPPORT=y
CONFIG_SEMAPHORE_SLEEPERS=y CONFIG_SEMAPHORE_SLEEPERS=y
CONFIG_X86=y CONFIG_X86=y
CONFIG_MMU=y CONFIG_MMU=y
CONFIG_GENERIC_ISA_DMA=y CONFIG_GENERIC_ISA_DMA=y
CONFIG_GENERIC_IOMAP=y CONFIG_GENERIC_IOMAP=y
CONFIG_GENERIC_HWEIGHT=y CONFIG_GENERIC_HWEIGHT=y
CONFIG_ARCH_MAY_HAVE_PC_FDC=y CONFIG_ARCH_MAY_HAVE_PC_FDC=y
CONFIG_DMI=y CONFIG_DMI=y
CONFIG_DEFCONFIG_LIST="/lib/modules/$UNAME_RELEASE/.config" CONFIG_DEFCONFIG_LIST="/lib/modules/

# #
# Code maturity level options # Code maturity level options
# #
CONFIG_EXPERIMENTAL=y CONFIG_EXPERIMENTAL=y
CONFIG_LOCK_KERNEL=y CONFIG_LOCK_KERNEL=y
CONFIG_INIT_ENV_ARG_LIMIT=32 CONFIG_INIT_ENV_ARG_LIMIT=32

# #
# General setup # General setup
# #
CONFIG_LOCALVERSION="" CONFIG_LOCALVERSION=""
# CONFIG_LOCALVERSION_AUTO is not set # CONFIG_LOCALVERSION_AUTO is not set
CONFIG_SWAP=y CONFIG_SWAP=y
CONFIG_SYSVIPC=y CONFIG_SYSVIPC=y
CONFIG_POSIX_MQUEUE=y CONFIG_POSIX_MQUEUE=y
CONFIG_BSD_PROCESS_ACCT=y CONFIG_BSD_PROCESS_ACCT=y
# CONFIG_BSD_PROCESS_ACCT_V3 is not set # CONFIG_BSD_PROCESS_ACCT_V3 is not set
CONFIG_TASKSTATS=y CONFIG_TASKSTATS=y
CONFIG_TASK_DELAY_ACCT=y CONFIG_TASK_DELAY_ACCT=y
CONFIG_AUDIT=y CONFIG_AUDIT=y
CONFIG_AUDITSYSCALL=y CONFIG_AUDITSYSCALL=y
# CONFIG_IKCONFIG is not set # CONFIG_IKCONFIG is not set
CONFIG_CPUSETS=y CONFIG_CPUSETS=y
CONFIG_RELAY=y CONFIG_RELAY=y
CONFIG_INITRAMFS_SOURCE="" CONFIG_INITRAMFS_SOURCE=""
CONFIG_CC_OPTIMIZE_FOR_SIZE=y CONFIG_CC_OPTIMIZE_FOR_SIZE=y
# CONFIG_EMBEDDED is not set # CONFIG_EMBEDDED is not set
CONFIG_UID16=y CONFIG_UID16=y
CONFIG_SYSCTL=y CONFIG_SYSCTL=y
CONFIG_KALLSYMS=y CONFIG_KALLSYMS=y
# CONFIG_KALLSYMS_ALL is not set # CONFIG_KALLSYMS_ALL is not set
CONFIG_KALLSYMS_EXTRA_PASS=y CONFIG_KALLSYMS_EXTRA_PASS=y
CONFIG_HOTPLUG=y CONFIG_HOTPLUG=y
CONFIG_PRINTK=y CONFIG_PRINTK=y
CONFIG_BUG=y CONFIG_BUG=y
CONFIG_ELF_CORE=y CONFIG_ELF_CORE=y
CONFIG_BASE_FULL=y CONFIG_BASE_FULL=y
CONFIG_FUTEX=y CONFIG_FUTEX=y
CONFIG_EPOLL=y CONFIG_EPOLL=y
CONFIG_SHMEM=y CONFIG_SHMEM=y
CONFIG_SLAB=y CONFIG_SLAB=y
```

```

CONFIG_VM_EVENT_COUNTERS=y      CONFIG_VM_EVENT_COUNTERS=y
CONFIG_RT_MUTEXES=y            CONFIG_RT_MUTEXES=y
# CONFIG_TINY_SHMEM is not set  # CONFIG_TINY_SHMEM is not set
CONFIG_BASE_SMALL=0           CONFIG_BASE_SMALL=0
# CONFIG_SLOB is not set      # CONFIG_SLOB is not set

#
# Loadable module support      # Loadable module support
#
CONFIG_MODULES=y              CONFIG_MODULES=y
CONFIG_MODULE_UNLOAD=y        CONFIG_MODULE_UNLOAD=y
# CONFIG_MODULE_FORCE_UNLOAD is not set # CONFIG_MODULE_FORCE_UNLOAD is not set
CONFIG_MODVERSIONS=y         CONFIG_MODVERSIONS=y
CONFIG_MODULE_SRCVERSION_ALL=y CONFIG_MODULE_SRCVERSION_ALL=y
CONFIG_MODULE_SIG=y           CONFIG_MODULE_SIG=y
# CONFIG_MODULE_SIG_FORCE is not set # CONFIG_MODULE_SIG_FORCE is not set
CONFIG_KMOD=y                  CONFIG_KMOD=y
CONFIG_STOP_MACHINE=y         CONFIG_STOP_MACHINE=y

#
# Process debugging support      # Process debugging support
#
CONFIG_UTRACE=y                CONFIG_UTRACE=y
CONFIG_PTRACE=y                CONFIG_PTRACE=y

#
# Block layer                    # Block layer
#
CONFIG_LBD=y                    CONFIG_LBD=y
CONFIG_BLK_DEV_IO_TRACE=y     CONFIG_BLK_DEV_IO_TRACE=y
CONFIG_LSF=y                    CONFIG_LSF=y

#
# IO Schedulers                    # IO Schedulers
#
CONFIG_IOSCHED_NOOP=y         CONFIG_IOSCHED_NOOP=y
CONFIG_IOSCHED_AS=y           CONFIG_IOSCHED_AS=y
CONFIG_IOSCHED_DEADLINE=y     CONFIG_IOSCHED_DEADLINE=y
CONFIG_IOSCHED_CFQ=y          CONFIG_IOSCHED_CFQ=y
# CONFIG_DEFAULT_AS is not set # CONFIG_DEFAULT_AS is not set
# CONFIG_DEFAULT_DEADLINE is not set # CONFIG_DEFAULT_DEADLINE is not set
CONFIG_DEFAULT_CFQ=y           CONFIG_DEFAULT_CFQ=y
# CONFIG_DEFAULT_NOOP is not set # CONFIG_DEFAULT_NOOP is not set
CONFIG_DEFAULT_IOSCHED="cfq"  CONFIG_DEFAULT_IOSCHED="cfq"

#
# Processor type and features      # Processor type and features
#
CONFIG_SMP=y                    CONFIG_SMP=y
# CONFIG_X86_PC is not set      # CONFIG_X86_PC is not set
# CONFIG_X86_XEN is not set     # CONFIG_X86_XEN is not set
# CONFIG_X86_ELAN is not set    # CONFIG_X86_ELAN is not set
# CONFIG_X86_VOYAGER is not set # CONFIG_X86_VOYAGER is not set
# CONFIG_X86_NUMAQ is not set   # CONFIG_X86_NUMAQ is not set
# CONFIG_X86_SUMMIT is not set   # CONFIG_X86_SUMMIT is not set
# CONFIG_X86_BIGSMP is not set  # CONFIG_X86_BIGSMP is not set
# CONFIG_X86_VISWS is not set   # CONFIG_X86_VISWS is not set
CONFIG_X86_GENERICARCH=y      CONFIG_X86_GENERICARCH=y
# CONFIG_X86_ES7000 is not set  # CONFIG_X86_ES7000 is not set
CONFIG_X86_CYCLONE_TIMER=y    CONFIG_X86_CYCLONE_TIMER=y
# CONFIG_M386 is not set        # CONFIG_M386 is not set
# CONFIG_M486 is not set        # CONFIG_M486 is not set
# CONFIG_M586 is not set        # CONFIG_M586 is not set
# CONFIG_M586TSC is not set     # CONFIG_M586TSC is not set
# CONFIG_M586MMX is not set     # CONFIG_M586MMX is not set
CONFIG_M686=y                  CONFIG_M686=y
# CONFIG_MPENTIUMII is not set  # CONFIG_MPENTIUMII is not set
# CONFIG_MPENTIUMIII is not set # CONFIG_MPENTIUMIII is not set
# CONFIG_MPENTIUMM is not set   # CONFIG_MPENTIUMM is not set
# CONFIG_MPENTIUM4 is not set   # CONFIG_MPENTIUM4 is not set
# CONFIG_MK6 is not set         # CONFIG_MK6 is not set
# CONFIG_MK7 is not set         # CONFIG_MK7 is not set
# CONFIG_MK8 is not set         # CONFIG_MK8 is not set
# CONFIG_MCRUSOE is not set     # CONFIG_MCRUSOE is not set
# CONFIG_MEFFICEON is not set   # CONFIG_MEFFICEON is not set
# CONFIG_MWINCHIP6 is not set   # CONFIG_MWINCHIP6 is not set
# CONFIG_MWINCHIP2 is not set   # CONFIG_MWINCHIP2 is not set
# CONFIG_MWINCHIP3D is not set  # CONFIG_MWINCHIP3D is not set
# CONFIG_MGEODEGX1 is not set   # CONFIG_MGEODEGX1 is not set

```

```

# CONFIG_MGEODE_LX is not set      # CONFIG_MGEODE_LX is not set
# CONFIG_MCYRIXIII is not set      # CONFIG_MCYRIXIII is not set
# CONFIG_MVIAC3_2 is not set      # CONFIG_MVIAC3_2 is not set
CONFIG_X86_GENERIC=y              CONFIG_X86_GENERIC=y
CONFIG_X86_CMPXCHG=y              CONFIG_X86_CMPXCHG=y
CONFIG_X86_XADD=y                  CONFIG_X86_XADD=y
CONFIG_X86_L1_CACHE_SHIFT=7       CONFIG_X86_L1_CACHE_SHIFT=7
CONFIG_RWSEM_XCHGADD_ALGORITHM=y   CONFIG_RWSEM_XCHGADD_ALGORITHM=y
CONFIG_GENERIC_CALIBRATE_DELAY=y   CONFIG_GENERIC_CALIBRATE_DELAY=y
CONFIG_X86_PPRO_FENCE=y            CONFIG_X86_PPRO_FENCE=y
CONFIG_X86_WP_WORKS_OK=y           CONFIG_X86_WP_WORKS_OK=y
CONFIG_X86_INVLPG=y                CONFIG_X86_INVLPG=y
CONFIG_X86_BSWAP=y                 CONFIG_X86_BSWAP=y
CONFIG_X86_POPAD_OK=y              CONFIG_X86_POPAD_OK=y
CONFIG_X86_CMPXCHG64=y             CONFIG_X86_CMPXCHG64=y
CONFIG_X86_GOOD_APIC=y            CONFIG_X86_GOOD_APIC=y
CONFIG_X86_INTEL_USERCOPY=y        CONFIG_X86_INTEL_USERCOPY=y
CONFIG_X86_USE_PPRO_CHECKSUM=y     CONFIG_X86_USE_PPRO_CHECKSUM=y
CONFIG_X86_TSC=y                    CONFIG_X86_TSC=y
CONFIG_HPET_TIMER=y                 CONFIG_HPET_TIMER=y
CONFIG_HPET_EMULATE_RTC=y          CONFIG_HPET_EMULATE_RTC=y
CONFIG_NR_CPUS=32                   CONFIG_NR_CPUS=32
CONFIG_SCHED_SMT=y                  CONFIG_SCHED_SMT=y
CONFIG_SCHED_MC=y                   CONFIG_SCHED_MC=y
# CONFIG_PREEMPT_NONE is not set    # CONFIG_PREEMPT_NONE is not set
CONFIG_PREEMPT_VOLUNTARY=y          CONFIG_PREEMPT_VOLUNTARY=y
# CONFIG_PREEMPT is not set         # CONFIG_PREEMPT is not set
CONFIG_PREEMPT_BKL=y                CONFIG_PREEMPT_BKL=y
CONFIG_X86_LOCAL_APIC=y             CONFIG_X86_LOCAL_APIC=y
CONFIG_X86_IO_APIC=y                CONFIG_X86_IO_APIC=y
CONFIG_X86_MCE=y                     CONFIG_X86_MCE=y
# CONFIG_X86_MCE_NONFATAL is not set # CONFIG_X86_MCE_NONFATAL is not set
CONFIG_X86_MCE_P4THERMAL=y          CONFIG_X86_MCE_P4THERMAL=y
CONFIG_VM86=y                         CONFIG_VM86=y
CONFIG_TOSHIBA=m                     CONFIG_TOSHIBA=m
CONFIG_I8K=m                           CONFIG_I8K=m
# CONFIG_X86_REBOOTFIXUPS is not set # CONFIG_X86_REBOOTFIXUPS is not set
CONFIG_MICROCODE=m                   CONFIG_MICROCODE=m
CONFIG_X86_MSR=m                       CONFIG_X86_MSR=m
CONFIG_X86_CPUID=m                     CONFIG_X86_CPUID=m
# CONFIG_SWIOTLB is not set         # CONFIG_SWIOTLB is not set

#                                     #
# Firmware Drivers                     # Firmware Drivers
#                                     #
CONFIG_EDD=m                           CONFIG_EDD=m
CONFIG_EFI_VARS=y                       CONFIG_EFI_VARS=y
CONFIG_DELL_RBU=m                       CONFIG_DELL_RBU=m
CONFIG_DCDBAS=m                         CONFIG_DCDBAS=m
# CONFIG_NOHIGHMEM is not set        # CONFIG_NOHIGHMEM is not set
CONFIG_HIGHMEM4G=y                       CONFIG_HIGHMEM4G=y
# CONFIG_HIGHMEM64G is not set        # CONFIG_HIGHMEM64G is not set
CONFIG_PAGE_OFFSET=0xc0000000           CONFIG_PAGE_OFFSET=0xc0000000
CONFIG_HIGHMEM=y                         CONFIG_HIGHMEM=y
CONFIG_SELECT_MEMORY_MODEL=y             CONFIG_SELECT_MEMORY_MODEL=y
CONFIG_FLATMEM_MANUAL=y                   CONFIG_FLATMEM_MANUAL=y
# CONFIG_DISCONTIGMEM_MANUAL is not set # CONFIG_DISCONTIGMEM_MANUAL is not set
# CONFIG_SPARSEMEM_MANUAL is not set    # CONFIG_SPARSEMEM_MANUAL is not set
CONFIG_FLATMEM=y                         CONFIG_FLATMEM=y
CONFIG_FLAT_NODE_MEM_MAP=y               CONFIG_FLAT_NODE_MEM_MAP=y
# CONFIG_SPARSEMEM_STATIC is not set    # CONFIG_SPARSEMEM_STATIC is not set
CONFIG_SPLIT_PTLOCK_CPUS=4096           CONFIG_SPLIT_PTLOCK_CPUS=4096
CONFIG_RESOURCES_64BIT=y                 CONFIG_RESOURCES_64BIT=y
CONFIG_HIGHPTES=y                       CONFIG_HIGHPTES=y
# CONFIG_MATH_EMULATION is not set     # CONFIG_MATH_EMULATION is not set
CONFIG_MTRR=y                             CONFIG_MTRR=y
CONFIG_EFI=y                             CONFIG_EFI=y
# CONFIG_IRQBALANCE is not set        # CONFIG_IRQBALANCE is not set
CONFIG_BOOT_IOREMAP=y                   CONFIG_BOOT_IOREMAP=y
CONFIG_REGPARM=y                         CONFIG_REGPARM=y
# CONFIG_SECCOMP is not set           # CONFIG_SECCOMP is not set
# CONFIG_VGA_NOPROBE is not set       # CONFIG_VGA_NOPROBE is not set
# CONFIG_HZ_100 is not set            # CONFIG_HZ_100 is not set
# CONFIG_HZ_250 is not set            # CONFIG_HZ_250 is not set
CONFIG_HZ_1000=y                         CONFIG_HZ_1000=y
CONFIG_HZ=1000                           CONFIG_HZ=1000
CONFIG_KEXEC=y                           CONFIG_KEXEC=y
CONFIG_CRASH_DUMP=y                       CONFIG_CRASH_DUMP=y
CONFIG_RELOCATABLE=y                     CONFIG_RELOCATABLE=y

```

```
CONFIG_PHYSICAL_ALIGN=0x400000    CONFIG_PHYSICAL_ALIGN=0x400000
CONFIG_HOTPLUG_CPU=y              CONFIG_HOTPLUG_CPU=y
# CONFIG_COMPAT_VDSO is not set    # CONFIG_COMPAT_VDSO is not set
CONFIG_ARCH_ENABLE_MEMORY_HOTPLUG=y  CONFIG_ARCH_ENABLE_MEMORY_HOTPLUG=y

#
#
# Power management options (ACPI, APM) # Power management options (ACPI, APM)
#
CONFIG_PM=y                        CONFIG_PM=y
CONFIG_PM_LEGACY=y                 CONFIG_PM_LEGACY=y
# CONFIG_PM_DEBUG is not set      # CONFIG_PM_DEBUG is not set
CONFIG_SOFTWARE_SUSPEND=y         CONFIG_SOFTWARE_SUSPEND=y
CONFIG_PM_STD_PARTITION=""        CONFIG_PM_STD_PARTITION=""
CONFIG_SUSPEND_SMP=y              CONFIG_SUSPEND_SMP=y

#
#
# ACPI (Advanced Configuration and Power Interface) Support # ACPI (Advanced Configuration and P
#
CONFIG_ACPI=y                      CONFIG_ACPI=y
CONFIG_ACPI_SLEEP=y               CONFIG_ACPI_SLEEP=y
CONFIG_ACPI_SLEEP_PROC_FS=y       CONFIG_ACPI_SLEEP_PROC_FS=y
# CONFIG_ACPI_SLEEP_PROC_SLEEP is not set # CONFIG_ACPI_SLEEP_PROC_SLEEP is not set
CONFIG_ACPI_AC=m                  CONFIG_ACPI_AC=m
CONFIG_ACPI_BATTERY=m             CONFIG_ACPI_BATTERY=m
CONFIG_ACPI_BUTTON=m              CONFIG_ACPI_BUTTON=m
CONFIG_ACPI_VIDEO=m               CONFIG_ACPI_VIDEO=m
# CONFIG_ACPI_HOTKEY is not set    # CONFIG_ACPI_HOTKEY is not set
CONFIG_ACPI_FAN=y                 CONFIG_ACPI_FAN=y
CONFIG_ACPI_DOCK=y                CONFIG_ACPI_DOCK=y
CONFIG_ACPI_PROCESSOR=y           CONFIG_ACPI_PROCESSOR=y
CONFIG_ACPI_HOTPLUG_CPU=y         CONFIG_ACPI_HOTPLUG_CPU=y
CONFIG_ACPI_THERMAL=y             CONFIG_ACPI_THERMAL=y
CONFIG_ACPI_ASUS=m                CONFIG_ACPI_ASUS=m
CONFIG_ACPI_IBM=m                 CONFIG_ACPI_IBM=m
CONFIG_ACPI_TOSHIBA=m             CONFIG_ACPI_TOSHIBA=m
CONFIG_ACPI_BLACKLIST_YEAR=1999   CONFIG_ACPI_BLACKLIST_YEAR=1999
# CONFIG_ACPI_DEBUG is not set     # CONFIG_ACPI_DEBUG is not set
CONFIG_ACPI_EC=y                  CONFIG_ACPI_EC=y
CONFIG_ACPI_POWER=y               CONFIG_ACPI_POWER=y
CONFIG_ACPI_SYSTEM=y              CONFIG_ACPI_SYSTEM=y
CONFIG_X86_PM_TIMER=y             CONFIG_X86_PM_TIMER=y
CONFIG_ACPI_CONTAINER=y           CONFIG_ACPI_CONTAINER=y
CONFIG_ACPI_SBS=m                 CONFIG_ACPI_SBS=m

#
#
# APM (Advanced Power Management) BIOS Support # APM (Advanced Power Management) BIOS Support
#
CONFIG_APM=y                       CONFIG_APM=y
# CONFIG_APM_IGNORE_USER_SUSPEND is not set # CONFIG_APM_IGNORE_USER_SUSPEND is not set
# CONFIG_APM_DO_ENABLE is not set # CONFIG_APM_DO_ENABLE is not set
CONFIG_APM_CPU_IDLE=y             CONFIG_APM_CPU_IDLE=y
# CONFIG_APM_DISPLAY_BLANK is not set # CONFIG_APM_DISPLAY_BLANK is not set
CONFIG_APM_RTC_IS_GMT=y           CONFIG_APM_RTC_IS_GMT=y
# CONFIG_APM_ALLOW_INTS is not set # CONFIG_APM_ALLOW_INTS is not set
# CONFIG_APM_REAL_MODE_POWER_OFF is not set # CONFIG_APM_REAL_MODE_POWER_OFF is not set

#
#
# CPU Frequency scaling # CPU Frequency scaling
#
CONFIG_CPU_FREQ=y                  CONFIG_CPU_FREQ=y
CONFIG_CPU_FREQ_TABLE=y           CONFIG_CPU_FREQ_TABLE=y
CONFIG_CPU_FREQ_DEBUG=y           CONFIG_CPU_FREQ_DEBUG=y
CONFIG_CPU_FREQ_STAT=m            CONFIG_CPU_FREQ_STAT=m
CONFIG_CPU_FREQ_STAT_DETAILS=y    CONFIG_CPU_FREQ_STAT_DETAILS=y
# CONFIG_CPU_FREQ_DEFAULT_GOV_PERFORMANCE is not set # CONFIG_CPU_FREQ_DEFAULT_GOV_PERFORMANCE
CONFIG_CPU_FREQ_DEFAULT_GOV_USERSPACE=y CONFIG_CPU_FREQ_DEFAULT_GOV_USERSPACE=y
CONFIG_CPU_FREQ_GOV_PERFORMANCE=y CONFIG_CPU_FREQ_GOV_PERFORMANCE=y
CONFIG_CPU_FREQ_GOV_POWERSAVE=m   CONFIG_CPU_FREQ_GOV_POWERSAVE=m
CONFIG_CPU_FREQ_GOV_USERSPACE=y   CONFIG_CPU_FREQ_GOV_USERSPACE=y
CONFIG_CPU_FREQ_GOV_ONDEMAND=m    CONFIG_CPU_FREQ_GOV_ONDEMAND=m
CONFIG_CPU_FREQ_GOV_CONSERVATIVE=m CONFIG_CPU_FREQ_GOV_CONSERVATIVE=m

#
#
# CPUFreq processor drivers # CPUFreq processor drivers
#
CONFIG_X86_ACPI_CPUFREQ=m         CONFIG_X86_ACPI_CPUFREQ=m
# CONFIG_X86_POWERNOW_K6 is not set # CONFIG_X86_POWERNOW_K6 is not set
CONFIG_X86_POWERNOW_K7=y         CONFIG_X86_POWERNOW_K7=y
CONFIG_X86_POWERNOW_K7_ACPI=y    CONFIG_X86_POWERNOW_K7_ACPI=y
```

```

CONFIG_X86_POWERNOW_K8=y      CONFIG_X86_POWERNOW_K8=y
CONFIG_X86_POWERNOW_K8_ACPI=y  CONFIG_X86_POWERNOW_K8_ACPI=y
# CONFIG_X86_GX_SUSPMOD is not set # CONFIG_X86_GX_SUSPMOD is not set
CONFIG_X86_SPEEDSTEP_CENTRINO=y  CONFIG_X86_SPEEDSTEP_CENTRINO=y
CONFIG_X86_SPEEDSTEP_CENTRINO_ACPI=y  CONFIG_X86_SPEEDSTEP_CENTRINO_ACPI=y
CONFIG_X86_SPEEDSTEP_CENTRINO_TABLE=y  CONFIG_X86_SPEEDSTEP_CENTRINO_TABLE=y
CONFIG_X86_SPEEDSTEP_ICH=y  CONFIG_X86_SPEEDSTEP_ICH=y
CONFIG_X86_SPEEDSTEP_SMI=y  CONFIG_X86_SPEEDSTEP_SMI=y
CONFIG_X86_P4_CLOCKMOD=m  CONFIG_X86_P4_CLOCKMOD=m
# CONFIG_X86_CPUFREQ_NFORCE2 is not set # CONFIG_X86_CPUFREQ_NFORCE2 is not set
CONFIG_X86_LONGRUN=y  CONFIG_X86_LONGRUN=y
# CONFIG_X86_LONGHAUL is not set # CONFIG_X86_LONGHAUL is not set

# #
# shared options # shared options
# #
# CONFIG_X86_ACPI_CPUFREQ_PROC_INTF is not set # CONFIG_X86_ACPI_CPUFREQ_PROC_INTF is not set
CONFIG_X86_SPEEDSTEP_LIB=y  CONFIG_X86_SPEEDSTEP_LIB=y
# CONFIG_X86_SPEEDSTEP_RELAXED_CAP_CHECK is not set # CONFIG_X86_SPEEDSTEP_RELAXED_CAP_CHECK is

# #
# Bus options (PCI, PCMCIA, EISA, MCA, ISA) # Bus options (PCI, PCMCIA, EISA, MCA, ISA)
# #
CONFIG_PCI=y  CONFIG_PCI=y
# CONFIG_PCI_GOBIOS is not set # CONFIG_PCI_GOBIOS is not set
# CONFIG_PCI_GOMMCONFIG is not set # CONFIG_PCI_GOMMCONFIG is not set
# CONFIG_PCI_GODIRECT is not set # CONFIG_PCI_GODIRECT is not set
# CONFIG_PCI_GOXEN_FE is not set # CONFIG_PCI_GOXEN_FE is not set
CONFIG_PCI_GOANY=y  CONFIG_PCI_GOANY=y
CONFIG_PCI_BIOS=y  CONFIG_PCI_BIOS=y
CONFIG_PCI_DIRECT=y  CONFIG_PCI_DIRECT=y
CONFIG_PCI_MMCONFIG=y  CONFIG_PCI_MMCONFIG=y
CONFIG_PCIEPORTBUS=y  CONFIG_PCIEPORTBUS=y
CONFIG_HOTPLUG_PCI_PCIE=m  CONFIG_HOTPLUG_PCI_PCIE=m
# CONFIG_HOTPLUG_PCI_PCIE_POLL_EVENT_MODE is not set # CONFIG_HOTPLUG_PCI_PCIE_POLL_EVENT_MODE
CONFIG_PCI_MSI=y  CONFIG_PCI_MSI=y
# CONFIG_PCI_DEBUG is not set # CONFIG_PCI_DEBUG is not set
CONFIG_ISA_DMA_API=y  CONFIG_ISA_DMA_API=y
# CONFIG_ISA is not set # CONFIG_ISA is not set
# CONFIG_MCA is not set # CONFIG_MCA is not set
# CONFIG_SCx200 is not set # CONFIG_SCx200 is not set
CONFIG_K8_NB=y  CONFIG_K8_NB=y

# #
# PCCARD (PCMCIA/CardBus) support # PCCARD (PCMCIA/CardBus) support
# #
CONFIG_PCCARD=y  CONFIG_PCCARD=y
# CONFIG_PCMCIA_DEBUG is not set # CONFIG_PCMCIA_DEBUG is not set
CONFIG_PCMCIA=y  CONFIG_PCMCIA=y
CONFIG_PCMCIA_LOAD_CIS=y  CONFIG_PCMCIA_LOAD_CIS=y
CONFIG_PCMCIA_IOCTL=y  CONFIG_PCMCIA_IOCTL=y
CONFIG_CARDBUS=y  CONFIG_CARDBUS=y

# #
# PC-card bridges # PC-card bridges
# #
CONFIG_YENTA=y  CONFIG_YENTA=y
CONFIG_YENTA_O2=y  CONFIG_YENTA_O2=y
CONFIG_YENTA_RICOH=y  CONFIG_YENTA_RICOH=y
CONFIG_YENTA_TI=y  CONFIG_YENTA_TI=y
CONFIG_YENTA_ENE_TUNE=y  CONFIG_YENTA_ENE_TUNE=y
CONFIG_YENTA_TOSHIBA=y  CONFIG_YENTA_TOSHIBA=y
CONFIG_PD6729=m  CONFIG_PD6729=m
# CONFIG_I82092 is not set # CONFIG_I82092 is not set
CONFIG_PCCARD_NONSTATIC=y  CONFIG_PCCARD_NONSTATIC=y

# #
# PCI Hotplug Support # PCI Hotplug Support
# #
CONFIG_HOTPLUG_PCI=y  CONFIG_HOTPLUG_PCI=y
CONFIG_HOTPLUG_PCI_FAKE=m  CONFIG_HOTPLUG_PCI_FAKE=m
CONFIG_HOTPLUG_PCI_COMPAQ=m  CONFIG_HOTPLUG_PCI_COMPAQ=m
# CONFIG_HOTPLUG_PCI_COMPAQ_NVRAM is not set # CONFIG_HOTPLUG_PCI_COMPAQ_NVRAM is not set
CONFIG_HOTPLUG_PCI_IBM=m  CONFIG_HOTPLUG_PCI_IBM=m
CONFIG_HOTPLUG_PCI_ACPI=m  CONFIG_HOTPLUG_PCI_ACPI=m
CONFIG_HOTPLUG_PCI_ACPI_IBM=m  CONFIG_HOTPLUG_PCI_ACPI_IBM=m
# CONFIG_HOTPLUG_PCI_CPCI is not set # CONFIG_HOTPLUG_PCI_CPCI is not set
# CONFIG_HOTPLUG_PCI_SHPC is not set # CONFIG_HOTPLUG_PCI_SHPC is not set

```

```

#           #
# Executable file formats      # Executable file formats
#           #
CONFIG_BINFMT_ELF=y          CONFIG_BINFMT_ELF=y
# CONFIG_BINFMT_AOUT is not set      # CONFIG_BINFMT_AOUT is not set
CONFIG_BINFMT_MISC=y        CONFIG_BINFMT_MISC=y

#           #
# Networking                   # Networking
#           #
CONFIG_NET=y                CONFIG_NET=y

#           #
# Networking options           # Networking options
#           #
# CONFIG_NETDEBUG is not set      # CONFIG_NETDEBUG is not set
CONFIG_PACKET=y             CONFIG_PACKET=y
CONFIG_PACKET_MMAP=y        CONFIG_PACKET_MMAP=y
CONFIG_UNIX=y               CONFIG_UNIX=y
CONFIG_XFRM=y               CONFIG_XFRM=y
CONFIG_XFRM_USER=y          CONFIG_XFRM_USER=y
CONFIG_NET_KEY=m            CONFIG_NET_KEY=m
CONFIG_INET=y               CONFIG_INET=y
CONFIG_IP_MULTICAST=y       CONFIG_IP_MULTICAST=y
CONFIG_IP_ADVANCED_ROUTER=y  CONFIG_IP_ADVANCED_ROUTER=y
CONFIG_ASK_IP_FIB_HASH=y    CONFIG_ASK_IP_FIB_HASH=y
# CONFIG_IP_FIB_TRIE is not set    # CONFIG_IP_FIB_TRIE is not set
CONFIG_IP_FIB_HASH=y        CONFIG_IP_FIB_HASH=y
CONFIG_IP_MULTIPLE_TABLES=y  CONFIG_IP_MULTIPLE_TABLES=y
CONFIG_IP_ROUTE_FWMARK=y    CONFIG_IP_ROUTE_FWMARK=y
CONFIG_IP_ROUTE_MULTIPATH=y  CONFIG_IP_ROUTE_MULTIPATH=y
# CONFIG_IP_ROUTE_MULTIPATH_CACHED is not set # CONFIG_IP_ROUTE_MULTIPATH_CACHED is not set
CONFIG_IP_ROUTE_VERBOSE=y    CONFIG_IP_ROUTE_VERBOSE=y
# CONFIG_IP_IP_PNP is not set      # CONFIG_IP_PNP is not set
CONFIG_NET_IPIP=m           CONFIG_NET_IPIP=m
CONFIG_NET_IPGRE=m          CONFIG_NET_IPGRE=m
CONFIG_NET_IPGRE_BROADCAST=y CONFIG_NET_IPGRE_BROADCAST=y
CONFIG_IP_MROUTE=y          CONFIG_IP_MROUTE=y
CONFIG_IP_PIMSM_V1=y        CONFIG_IP_PIMSM_V1=y
CONFIG_IP_PIMSM_V2=y        CONFIG_IP_PIMSM_V2=y
# CONFIG_ARPD is not set          # CONFIG_ARPD is not set
CONFIG_SYN_COOKIES=y        CONFIG_SYN_COOKIES=y
CONFIG_INET_AH=m            CONFIG_INET_AH=m
CONFIG_INET_ESP=m           CONFIG_INET_ESP=m
CONFIG_INET_IPCOMP=m        CONFIG_INET_IPCOMP=m
CONFIG_INET_XFRM_TUNNEL=m   CONFIG_INET_XFRM_TUNNEL=m
CONFIG_INET_TUNNEL=m        CONFIG_INET_TUNNEL=m
CONFIG_INET_XFRM_MODE_TRANSPORT=m CONFIG_INET_XFRM_MODE_TRANSPORT=m
CONFIG_INET_XFRM_MODE_TUNNEL=m CONFIG_INET_XFRM_MODE_TUNNEL=m
CONFIG_INET_DIAG=m          CONFIG_INET_DIAG=m
CONFIG_INET_TCP_DIAG=m      CONFIG_INET_TCP_DIAG=m
CONFIG_TCP_CONG_ADVANCED=y   CONFIG_TCP_CONG_ADVANCED=y

#           #
# TCP congestion control         # TCP congestion control
#           #
CONFIG_TCP_CONG_BIC=y        CONFIG_TCP_CONG_BIC=y
CONFIG_TCP_CONG_CUBIC=m      CONFIG_TCP_CONG_CUBIC=m
CONFIG_TCP_CONG_WESTWOOD=m   CONFIG_TCP_CONG_WESTWOOD=m
CONFIG_TCP_CONG_HTCP=m       CONFIG_TCP_CONG_HTCP=m
CONFIG_TCP_CONG_HSTCP=m      CONFIG_TCP_CONG_HSTCP=m
CONFIG_TCP_CONG_HYBLA=m      CONFIG_TCP_CONG_HYBLA=m
CONFIG_TCP_CONG_VEGAS=m      CONFIG_TCP_CONG_VEGAS=m
CONFIG_TCP_CONG_SCALABLE=m   CONFIG_TCP_CONG_SCALABLE=m
CONFIG_TCP_CONG_LP=m         CONFIG_TCP_CONG_LP=m
CONFIG_TCP_CONG_VENO=m       CONFIG_TCP_CONG_VENO=m

#           #
# IP: Virtual Server Configuration # IP: Virtual Server Configuration
#           #
CONFIG_IP_VS=m               CONFIG_IP_VS=m
# CONFIG_IP_VS_DEBUG is not set    # CONFIG_IP_VS_DEBUG is not set
CONFIG_IP_VS_TAB_BITS=12     CONFIG_IP_VS_TAB_BITS=12

#           #
# IPVS transport protocol load balancing support # IPVS transport protocol load balancing support
#           #
CONFIG_IP_VS_PROTO_TCP=y     CONFIG_IP_VS_PROTO_TCP=y
CONFIG_IP_VS_PROTO_UDP=y     CONFIG_IP_VS_PROTO_UDP=y

```

```

CONFIG_IP_VS_PROTO_ESP=y      CONFIG_IP_VS_PROTO_ESP=y
CONFIG_IP_VS_PROTO_AH=y      CONFIG_IP_VS_PROTO_AH=y

#          #
# IPVS scheduler              # IPVS scheduler
#          #
CONFIG_IP_VS_RR=m            CONFIG_IP_VS_RR=m
CONFIG_IP_VS_WRR=m          CONFIG_IP_VS_WRR=m
CONFIG_IP_VS_LC=m           CONFIG_IP_VS_LC=m
CONFIG_IP_VS_WLC=m          CONFIG_IP_VS_WLC=m
CONFIG_IP_VS_LBLC=m         CONFIG_IP_VS_LBLC=m
CONFIG_IP_VS_LBLCR=m        CONFIG_IP_VS_LBLCR=m
CONFIG_IP_VS_DH=m           CONFIG_IP_VS_DH=m
CONFIG_IP_VS_SH=m           CONFIG_IP_VS_SH=m
CONFIG_IP_VS_SED=m          CONFIG_IP_VS_SED=m
CONFIG_IP_VS_NQ=m           CONFIG_IP_VS_NQ=m

#          #
# IPVS application helper    # IPVS application helper
#          #
CONFIG_IP_VS_FTP=m          CONFIG_IP_VS_FTP=m
CONFIG_IPV6=m               CONFIG_IPV6=m
CONFIG_IPV6_PRIVACY=y       CONFIG_IPV6_PRIVACY=y
CONFIG_IPV6_ROUTER_PREF=y   CONFIG_IPV6_ROUTER_PREF=y
CONFIG_IPV6_ROUTE_INFO=y    CONFIG_IPV6_ROUTE_INFO=y
CONFIG_INET6_AH=m           CONFIG_INET6_AH=m
CONFIG_INET6_ESP=m          CONFIG_INET6_ESP=m
CONFIG_INET6_IPCOMP=m       CONFIG_INET6_IPCOMP=m
CONFIG_INET6_XFRM_TUNNEL=m  CONFIG_INET6_XFRM_TUNNEL=m
CONFIG_INET6_TUNNEL=m       CONFIG_INET6_TUNNEL=m
CONFIG_INET6_XFRM_MODE_TRANSPORT=m CONFIG_INET6_XFRM_MODE_TRANSPORT=m
CONFIG_INET6_XFRM_MODE_TUNNEL=m CONFIG_INET6_XFRM_MODE_TUNNEL=m
CONFIG_IPV6_TUNNEL=m        CONFIG_IPV6_TUNNEL=m
# CONFIG_IPV6_SUBTREES is not set # CONFIG_IPV6_SUBTREES is not set
CONFIG_IPV6_MULTIPLE_TABLES=y CONFIG_IPV6_MULTIPLE_TABLES=y
CONFIG_IPV6_ROUTE_FWMARK=y  CONFIG_IPV6_ROUTE_FWMARK=y
CONFIG_NETWORK_SECMARK=y    CONFIG_NETWORK_SECMARK=y
CONFIG_NETFILTER=y          CONFIG_NETFILTER=y
# CONFIG_NETFILTER_DEBUG is not set # CONFIG_NETFILTER_DEBUG is not set
CONFIG_BRIDGE_NETFILTER=y   CONFIG_BRIDGE_NETFILTER=y

#          #
# Core Netfilter Configuration # Core Netfilter Configuration
#          #
CONFIG_NETFILTER_NETLINK=m   CONFIG_NETFILTER_NETLINK=m
CONFIG_NETFILTER_NETLINK_QUEUE=m CONFIG_NETFILTER_NETLINK_QUEUE=m
CONFIG_NETFILTER_NETLINK_LOG=m CONFIG_NETFILTER_NETLINK_LOG=m
CONFIG_NETFILTER_XTABLES=m   CONFIG_NETFILTER_XTABLES=m
CONFIG_NETFILTER_XT_TARGET_CLASSIFY=m CONFIG_NETFILTER_XT_TARGET_CLASSIFY=m
CONFIG_NETFILTER_XT_TARGET_CONNMARK=m CONFIG_NETFILTER_XT_TARGET_CONNMARK=m
CONFIG_NETFILTER_XT_TARGET_MARK=m CONFIG_NETFILTER_XT_TARGET_MARK=m
CONFIG_NETFILTER_XT_TARGET_NFQUEUE=m CONFIG_NETFILTER_XT_TARGET_NFQUEUE=m
CONFIG_NETFILTER_XT_TARGET_NOTRACK=m CONFIG_NETFILTER_XT_TARGET_NOTRACK=m
CONFIG_NETFILTER_XT_TARGET_SECMARK=m CONFIG_NETFILTER_XT_TARGET_SECMARK=m
CONFIG_NETFILTER_XT_TARGET_CONNSECMARK=m CONFIG_NETFILTER_XT_TARGET_CONNSECMARK=m
CONFIG_NETFILTER_XT_MATCH_COMMENT=m CONFIG_NETFILTER_XT_MATCH_COMMENT=m
CONFIG_NETFILTER_XT_MATCH_CONNBYTES=m CONFIG_NETFILTER_XT_MATCH_CONNBYTES=m
CONFIG_NETFILTER_XT_MATCH_CONNMARK=m CONFIG_NETFILTER_XT_MATCH_CONNMARK=m
CONFIG_NETFILTER_XT_MATCH_CONNTRACK=m CONFIG_NETFILTER_XT_MATCH_CONNTRACK=m
CONFIG_NETFILTER_XT_MATCH_DCCP=m CONFIG_NETFILTER_XT_MATCH_DCCP=m
CONFIG_NETFILTER_XT_MATCH_ESP=m CONFIG_NETFILTER_XT_MATCH_ESP=m
CONFIG_NETFILTER_XT_MATCH_HELPER=m CONFIG_NETFILTER_XT_MATCH_HELPER=m
CONFIG_NETFILTER_XT_MATCH_LENGTH=m CONFIG_NETFILTER_XT_MATCH_LENGTH=m
CONFIG_NETFILTER_XT_MATCH_LIMIT=m CONFIG_NETFILTER_XT_MATCH_LIMIT=m
CONFIG_NETFILTER_XT_MATCH_MAC=m CONFIG_NETFILTER_XT_MATCH_MAC=m
CONFIG_NETFILTER_XT_MATCH_MARK=m CONFIG_NETFILTER_XT_MATCH_MARK=m
CONFIG_NETFILTER_XT_MATCH_POLICY=m CONFIG_NETFILTER_XT_MATCH_POLICY=m
CONFIG_NETFILTER_XT_MATCH_MULTIPOINT=m CONFIG_NETFILTER_XT_MATCH_MULTIPOINT=m
CONFIG_NETFILTER_XT_MATCH_PHYSDEV=m CONFIG_NETFILTER_XT_MATCH_PHYSDEV=m
CONFIG_NETFILTER_XT_MATCH_PKTTYPE=m CONFIG_NETFILTER_XT_MATCH_PKTTYPE=m
CONFIG_NETFILTER_XT_MATCH_QUOTA=m CONFIG_NETFILTER_XT_MATCH_QUOTA=m
CONFIG_NETFILTER_XT_MATCH_REALM=m CONFIG_NETFILTER_XT_MATCH_REALM=m
CONFIG_NETFILTER_XT_MATCH_SCTP=m CONFIG_NETFILTER_XT_MATCH_SCTP=m
CONFIG_NETFILTER_XT_MATCH_STATE=m CONFIG_NETFILTER_XT_MATCH_STATE=m
CONFIG_NETFILTER_XT_MATCH_STATISTIC=m CONFIG_NETFILTER_XT_MATCH_STATISTIC=m
CONFIG_NETFILTER_XT_MATCH_STRING=m CONFIG_NETFILTER_XT_MATCH_STRING=m
CONFIG_NETFILTER_XT_MATCH_TCPMSS=m CONFIG_NETFILTER_XT_MATCH_TCPMSS=m

#          #

```

```

# IP: Netfilter Configuration      # IP: Netfilter Configuration
#                                #
CONFIG_IP_NF_CONNTRACK=m          CONFIG_IP_NF_CONNTRACK=m
CONFIG_IP_NF_CT_ACCT=y            CONFIG_IP_NF_CT_ACCT=y
CONFIG_IP_NF_CONNTRACK_MARK=y     CONFIG_IP_NF_CONNTRACK_MARK=y
CONFIG_IP_NF_CONNTRACK_SECMARK=y  CONFIG_IP_NF_CONNTRACK_SECMARK=y
CONFIG_IP_NF_CONNTRACK_EVENTS=y   CONFIG_IP_NF_CONNTRACK_EVENTS=y
CONFIG_IP_NF_CONNTRACK_NETLINK=m  CONFIG_IP_NF_CONNTRACK_NETLINK=m
CONFIG_IP_NF_CT_PROTO_SCTP=m      CONFIG_IP_NF_CT_PROTO_SCTP=m
CONFIG_IP_NF_FTP=m                CONFIG_IP_NF_FTP=m
CONFIG_IP_NF_IRC=m                CONFIG_IP_NF_IRC=m
CONFIG_IP_NF_NETBIOS_NS=m         CONFIG_IP_NF_NETBIOS_NS=m
CONFIG_IP_NF_TFTP=m              CONFIG_IP_NF_TFTP=m
CONFIG_IP_NF_AMANDA=m            CONFIG_IP_NF_AMANDA=m
CONFIG_IP_NF_PPTP=m              CONFIG_IP_NF_PPTP=m
CONFIG_IP_NF_H323=m              CONFIG_IP_NF_H323=m
CONFIG_IP_NF_SIP=m               CONFIG_IP_NF_SIP=m
CONFIG_IP_NF_QUEUE=m             CONFIG_IP_NF_QUEUE=m
CONFIG_IP_NF_IPTABLES=m          CONFIG_IP_NF_IPTABLES=m
CONFIG_IP_NF_MATCH_IPRANGE=m     CONFIG_IP_NF_MATCH_IPRANGE=m
CONFIG_IP_NF_MATCH_TOS=m         CONFIG_IP_NF_MATCH_TOS=m
CONFIG_IP_NF_MATCH_RECENT=m      CONFIG_IP_NF_MATCH_RECENT=m
CONFIG_IP_NF_MATCH_ECN=m         CONFIG_IP_NF_MATCH_ECN=m
CONFIG_IP_NF_MATCH_DSCP=m        CONFIG_IP_NF_MATCH_DSCP=m
CONFIG_IP_NF_MATCH_AH=m          CONFIG_IP_NF_MATCH_AH=m
CONFIG_IP_NF_MATCH_TTL=m         CONFIG_IP_NF_MATCH_TTL=m
CONFIG_IP_NF_MATCH_OWNER=m       CONFIG_IP_NF_MATCH_OWNER=m
CONFIG_IP_NF_MATCH_ADDRTYPE=m    CONFIG_IP_NF_MATCH_ADDRTYPE=m
CONFIG_IP_NF_MATCH_HASHLIMIT=m   CONFIG_IP_NF_MATCH_HASHLIMIT=m
CONFIG_IP_NF_FILTER=m            CONFIG_IP_NF_FILTER=m
CONFIG_IP_NF_TARGET_REJECT=m     CONFIG_IP_NF_TARGET_REJECT=m
CONFIG_IP_NF_TARGET_LOG=m        CONFIG_IP_NF_TARGET_LOG=m
CONFIG_IP_NF_TARGET_ULOG=m       CONFIG_IP_NF_TARGET_ULOG=m
CONFIG_IP_NF_TARGET_TCPMSS=m     CONFIG_IP_NF_TARGET_TCPMSS=m
CONFIG_IP_NF_NAT=m               CONFIG_IP_NF_NAT=m
CONFIG_IP_NF_NAT_NEEDED=y        CONFIG_IP_NF_NAT_NEEDED=y
CONFIG_IP_NF_TARGET_MASQUERADE=m CONFIG_IP_NF_TARGET_MASQUERADE=m
CONFIG_IP_NF_TARGET_REDIRECT=m   CONFIG_IP_NF_TARGET_REDIRECT=m
CONFIG_IP_NF_TARGET_NETMAP=m    CONFIG_IP_NF_TARGET_NETMAP=m
CONFIG_IP_NF_TARGET_SAME=m       CONFIG_IP_NF_TARGET_SAME=m
CONFIG_IP_NF_NAT_SNMP_BASIC=m    CONFIG_IP_NF_NAT_SNMP_BASIC=m
CONFIG_IP_NF_NAT_IRC=m           CONFIG_IP_NF_NAT_IRC=m
CONFIG_IP_NF_NAT_FTP=m           CONFIG_IP_NF_NAT_FTP=m
CONFIG_IP_NF_NAT_TFTP=m          CONFIG_IP_NF_NAT_TFTP=m
CONFIG_IP_NF_NAT_AMANDA=m        CONFIG_IP_NF_NAT_AMANDA=m
CONFIG_IP_NF_NAT_PPTP=m          CONFIG_IP_NF_NAT_PPTP=m
CONFIG_IP_NF_NAT_H323=m          CONFIG_IP_NF_NAT_H323=m
CONFIG_IP_NF_NAT_SIP=m           CONFIG_IP_NF_NAT_SIP=m
CONFIG_IP_NF_MANGLE=m            CONFIG_IP_NF_MANGLE=m
CONFIG_IP_NF_TARGET_TOS=m        CONFIG_IP_NF_TARGET_TOS=m
CONFIG_IP_NF_TARGET_ECN=m        CONFIG_IP_NF_TARGET_ECN=m
CONFIG_IP_NF_TARGET_DSCP=m       CONFIG_IP_NF_TARGET_DSCP=m
CONFIG_IP_NF_TARGET_TTL=m        CONFIG_IP_NF_TARGET_TTL=m
CONFIG_IP_NF_TARGET_CLUSTERIP=m  CONFIG_IP_NF_TARGET_CLUSTERIP=m
CONFIG_IP_NF_RAW=m               CONFIG_IP_NF_RAW=m
CONFIG_IP_NF_ARPTABLES=m         CONFIG_IP_NF_ARPTABLES=m
CONFIG_IP_NF_ARPFILTER=m         CONFIG_IP_NF_ARPFILTER=m
CONFIG_IP_NF_ARP_MANGLE=m        CONFIG_IP_NF_ARP_MANGLE=m

#                                #
# IPv6: Netfilter Configuration (EXPERIMENTAL)  # IPv6: Netfilter Configuration (EXPERIMENTAL)
#                                #
CONFIG_IP6_NF_QUEUE=m            CONFIG_IP6_NF_QUEUE=m
CONFIG_IP6_NF_IPTABLES=m         CONFIG_IP6_NF_IPTABLES=m
CONFIG_IP6_NF_MATCH_RT=m         CONFIG_IP6_NF_MATCH_RT=m
CONFIG_IP6_NF_MATCH_OPTS=m       CONFIG_IP6_NF_MATCH_OPTS=m
CONFIG_IP6_NF_MATCH_FRAG=m       CONFIG_IP6_NF_MATCH_FRAG=m
CONFIG_IP6_NF_MATCH_HL=m         CONFIG_IP6_NF_MATCH_HL=m
CONFIG_IP6_NF_MATCH_OWNER=m      CONFIG_IP6_NF_MATCH_OWNER=m
CONFIG_IP6_NF_MATCH_IPV6HEADER=m CONFIG_IP6_NF_MATCH_IPV6HEADER=m
CONFIG_IP6_NF_MATCH_AH=m         CONFIG_IP6_NF_MATCH_AH=m
CONFIG_IP6_NF_MATCH_EUI64=m      CONFIG_IP6_NF_MATCH_EUI64=m
CONFIG_IP6_NF_FILTER=m           CONFIG_IP6_NF_FILTER=m
CONFIG_IP6_NF_TARGET_LOG=m       CONFIG_IP6_NF_TARGET_LOG=m
CONFIG_IP6_NF_TARGET_REJECT=m    CONFIG_IP6_NF_TARGET_REJECT=m
CONFIG_IP6_NF_MANGLE=m           CONFIG_IP6_NF_MANGLE=m
CONFIG_IP6_NF_TARGET_HL=m        CONFIG_IP6_NF_TARGET_HL=m
CONFIG_IP6_NF_RAW=m              CONFIG_IP6_NF_RAW=m

```

```

# #
# Bridge: Netfilter Configuration # Bridge: Netfilter Configuration
# #
CONFIG_BRIDGE_NF_EBTABLES=m CONFIG_BRIDGE_NF_EBTABLES=m
CONFIG_BRIDGE_EBT_BROUTE=m CONFIG_BRIDGE_EBT_BROUTE=m
CONFIG_BRIDGE_EBT_T_FILTER=m CONFIG_BRIDGE_EBT_T_FILTER=m
CONFIG_BRIDGE_EBT_T_NAT=m CONFIG_BRIDGE_EBT_T_NAT=m
CONFIG_BRIDGE_EBT_802_3=m CONFIG_BRIDGE_EBT_802_3=m
CONFIG_BRIDGE_EBT_AMONG=m CONFIG_BRIDGE_EBT_AMONG=m
CONFIG_BRIDGE_EBT_ARP=m CONFIG_BRIDGE_EBT_ARP=m
CONFIG_BRIDGE_EBT_IP=m CONFIG_BRIDGE_EBT_IP=m
CONFIG_BRIDGE_EBT_LIMIT=m CONFIG_BRIDGE_EBT_LIMIT=m
CONFIG_BRIDGE_EBT_MARK=m CONFIG_BRIDGE_EBT_MARK=m
CONFIG_BRIDGE_EBT_PKTTYPE=m CONFIG_BRIDGE_EBT_PKTTYPE=m
CONFIG_BRIDGE_EBT_STP=m CONFIG_BRIDGE_EBT_STP=m
CONFIG_BRIDGE_EBT_VLAN=m CONFIG_BRIDGE_EBT_VLAN=m
CONFIG_BRIDGE_EBT_ARPREPLY=m CONFIG_BRIDGE_EBT_ARPREPLY=m
CONFIG_BRIDGE_EBT_DNAT=m CONFIG_BRIDGE_EBT_DNAT=m
CONFIG_BRIDGE_EBT_MARK_T=m CONFIG_BRIDGE_EBT_MARK_T=m
CONFIG_BRIDGE_EBT_REDIRECT=m CONFIG_BRIDGE_EBT_REDIRECT=m
CONFIG_BRIDGE_EBT_SNAT=m CONFIG_BRIDGE_EBT_SNAT=m
CONFIG_BRIDGE_EBT_LOG=m CONFIG_BRIDGE_EBT_LOG=m
CONFIG_BRIDGE_EBT_ULOG=m CONFIG_BRIDGE_EBT_ULOG=m

# #
# DCCP Configuration (EXPERIMENTAL) # DCCP Configuration (EXPERIMENTAL)
# #
CONFIG_IP_DCCP=m CONFIG_IP_DCCP=m
CONFIG_INET_DCCP_DIAG=m CONFIG_INET_DCCP_DIAG=m
CONFIG_IP_DCCP_ACKVEC=y CONFIG_IP_DCCP_ACKVEC=y

# #
# DCCP CCIDs Configuration (EXPERIMENTAL) # DCCP CCIDs Configuration (EXPERIMENTAL)
# #
CONFIG_IP_DCCP_CCID2=m CONFIG_IP_DCCP_CCID2=m
CONFIG_IP_DCCP_CCID3=m CONFIG_IP_DCCP_CCID3=m
CONFIG_IP_DCCP_TFRC_LIB=m CONFIG_IP_DCCP_TFRC_LIB=m

# #
# DCCP Kernel Hacking # DCCP Kernel Hacking
# #
# CONFIG_IP_DCCP_DEBUG is not set # CONFIG_IP_DCCP_DEBUG is not set

# #
# SCTP Configuration (EXPERIMENTAL) # SCTP Configuration (EXPERIMENTAL)
# #
CONFIG_IP_SCTP=m CONFIG_IP_SCTP=m
# CONFIG_SCTP_DBG_MSG is not set # CONFIG_SCTP_DBG_MSG is not set
# CONFIG_SCTP_DBG_OBJCNT is not set # CONFIG_SCTP_DBG_OBJCNT is not set
# CONFIG_SCTP_HMAC_NONE is not set # CONFIG_SCTP_HMAC_NONE is not set
# CONFIG_SCTP_HMAC_SHA1 is not set # CONFIG_SCTP_HMAC_SHA1 is not set
CONFIG_SCTP_HMAC_MD5=y CONFIG_SCTP_HMAC_MD5=y

# #
# TIPC Configuration (EXPERIMENTAL) # TIPC Configuration (EXPERIMENTAL)
# #
CONFIG_TIPC=m CONFIG_TIPC=m
# CONFIG_TIPC_ADVANCED is not set # CONFIG_TIPC_ADVANCED is not set
# CONFIG_TIPC_DEBUG is not set # CONFIG_TIPC_DEBUG is not set
CONFIG_ATM=m CONFIG_ATM=m
CONFIG_ATM_CLIP=m CONFIG_ATM_CLIP=m
# CONFIG_ATM_CLIP_NO_ICMP is not set # CONFIG_ATM_CLIP_NO_ICMP is not set
CONFIG_ATM_LANE=m CONFIG_ATM_LANE=m
# CONFIG_ATM_MPOA is not set # CONFIG_ATM_MPOA is not set
CONFIG_ATM_BR2684=m CONFIG_ATM_BR2684=m
# CONFIG_ATM_BR2684_IPFILTER is not set # CONFIG_ATM_BR2684_IPFILTER is not set
CONFIG_BRIDGE=m CONFIG_BRIDGE=m
CONFIG_VLAN_8021Q=m CONFIG_VLAN_8021Q=m
# CONFIG_DECNET is not set # CONFIG_DECNET is not set
CONFIG_LLC=y CONFIG_LLC=y
# CONFIG_LLC2 is not set # CONFIG_LLC2 is not set
# CONFIG_IPX is not set | CONFIG_IPX=m
# CONFIG_ATALK is not set | CONFIG_IPX_INTERN=y
> CONFIG_ATALK=m
> CONFIG_DEV_APPLETALK=m
> CONFIG_IPDDP=m
> CONFIG_IPDDP_ENCAP=y
> CONFIG_IPDDP_DECAP=y
# CONFIG_X25 is not set # CONFIG_X25 is not set

```

```

# CONFIG_LAPB is not set      # CONFIG_LAPB is not set
# CONFIG_ECONET is not set   # CONFIG_ECONET is not set
# CONFIG_WAN_ROUTER is not set # CONFIG_WAN_ROUTER is not set

#
# QoS and/or fair queueing   # QoS and/or fair queueing
#
CONFIG_NET_SCHED=y          CONFIG_NET_SCHED=y
# CONFIG_NET_SCH_CLK_JIFFIES is not set # CONFIG_NET_SCH_CLK_JIFFIES is not set
CONFIG_NET_SCH_CLK_GETTIMEOFDAY=y CONFIG_NET_SCH_CLK_GETTIMEOFDAY=y
# CONFIG_NET_SCH_CLK_CPU is not set # CONFIG_NET_SCH_CLK_CPU is not set

#
# Queueing/Scheduling        # Queueing/Scheduling
#
CONFIG_NET_SCH_CBQ=m        CONFIG_NET_SCH_CBQ=m
CONFIG_NET_SCH_HTB=m        CONFIG_NET_SCH_HTB=m
CONFIG_NET_SCH_HFSC=m       CONFIG_NET_SCH_HFSC=m
CONFIG_NET_SCH_ATM=m        CONFIG_NET_SCH_ATM=m
CONFIG_NET_SCH_PRIO=m       CONFIG_NET_SCH_PRIO=m
CONFIG_NET_SCH_RED=m        CONFIG_NET_SCH_RED=m
CONFIG_NET_SCH_SFQ=m        CONFIG_NET_SCH_SFQ=m
CONFIG_NET_SCH_TEQL=m       CONFIG_NET_SCH_TEQL=m
CONFIG_NET_SCH_TBF=m        CONFIG_NET_SCH_TBF=m
CONFIG_NET_SCH_GRED=m       CONFIG_NET_SCH_GRED=m
CONFIG_NET_SCH_DSMARK=m     CONFIG_NET_SCH_DSMARK=m
CONFIG_NET_SCH_NETEM=m      CONFIG_NET_SCH_NETEM=m
CONFIG_NET_SCH_INGRESS=m    CONFIG_NET_SCH_INGRESS=m

#
# Classification             # Classification
#
CONFIG_NET_CLS=y           CONFIG_NET_CLS=y
CONFIG_NET_CLS_BASIC=m     CONFIG_NET_CLS_BASIC=m
CONFIG_NET_CLS_TCINDEX=m   CONFIG_NET_CLS_TCINDEX=m
CONFIG_NET_CLS_ROUTE4=m    CONFIG_NET_CLS_ROUTE4=m
CONFIG_NET_CLS_ROUTE=y     CONFIG_NET_CLS_ROUTE=y
CONFIG_NET_CLS_FW=m        CONFIG_NET_CLS_FW=m
CONFIG_NET_CLS_U32=m       CONFIG_NET_CLS_U32=m
CONFIG_CLS_U32_PERF=y       CONFIG_CLS_U32_PERF=y
CONFIG_CLS_U32_MARK=y      CONFIG_CLS_U32_MARK=y
CONFIG_NET_CLS_RSVP=m      CONFIG_NET_CLS_RSVP=m
CONFIG_NET_CLS_RSVP6=m     CONFIG_NET_CLS_RSVP6=m
CONFIG_NET_EMATCH=y        CONFIG_NET_EMATCH=y
CONFIG_NET_EMATCH_STACK=32 CONFIG_NET_EMATCH_STACK=32
CONFIG_NET_EMATCH_CMP=m    CONFIG_NET_EMATCH_CMP=m
CONFIG_NET_EMATCH_NBYTE=m  CONFIG_NET_EMATCH_NBYTE=m
CONFIG_NET_EMATCH_U32=m    CONFIG_NET_EMATCH_U32=m
CONFIG_NET_EMATCH_META=m   CONFIG_NET_EMATCH_META=m
CONFIG_NET_EMATCH_TEXT=m   CONFIG_NET_EMATCH_TEXT=m
CONFIG_NET_CLS_ACT=y       CONFIG_NET_CLS_ACT=y
CONFIG_NET_ACT_POLICE=m    CONFIG_NET_ACT_POLICE=m
CONFIG_NET_ACT_GACT=m      CONFIG_NET_ACT_GACT=m
CONFIG_GACT_PROB=y         CONFIG_GACT_PROB=y
CONFIG_NET_ACT_MIRRED=m    CONFIG_NET_ACT_MIRRED=m
CONFIG_NET_ACT_IPT=m       CONFIG_NET_ACT_IPT=m
CONFIG_NET_ACT_PEDIT=m     CONFIG_NET_ACT_PEDIT=m
CONFIG_NET_ACT_SIMP=m      CONFIG_NET_ACT_SIMP=m
CONFIG_NET_CLS_IND=y       CONFIG_NET_CLS_IND=y
CONFIG_NET_ESTIMATOR=y     CONFIG_NET_ESTIMATOR=y

#
# Network testing           # Network testing
#
CONFIG_NET_PKTGEN=m        CONFIG_NET_PKTGEN=m
# CONFIG_NET_TCPPROBE is not set # CONFIG_NET_TCPPROBE is not set
# CONFIG_HAMRADIO is not set # CONFIG_HAMRADIO is not set
# CONFIG_IRDA is not set # CONFIG_IRDA is not set
CONFIG_BT=m                CONFIG_BT=m
CONFIG_BT_L2CAP=m          CONFIG_BT_L2CAP=m
CONFIG_BT_SCO=m            CONFIG_BT_SCO=m
CONFIG_BT_RFCOMM=m        CONFIG_BT_RFCOMM=m
CONFIG_BT_RFCOMM_TTY=y    CONFIG_BT_RFCOMM_TTY=y
CONFIG_BT_BNEP=m          CONFIG_BT_BNEP=m
CONFIG_BT_BNEP_MC_FILTER=y CONFIG_BT_BNEP_MC_FILTER=y
CONFIG_BT_BNEP_PROTO_FILTER=y CONFIG_BT_BNEP_PROTO_FILTER=y
CONFIG_BT_CMTP=m          CONFIG_BT_CMTP=m
CONFIG_BT_HIDP=m          CONFIG_BT_HIDP=m

```

```

# #
# Bluetooth device drivers # Bluetooth device drivers
# #
CONFIG_BT_HCIUSB=m CONFIG_BT_HCIUSB=m
CONFIG_BT_HCIUSB_SCO=y CONFIG_BT_HCIUSB_SCO=y
CONFIG_BT_HCIUART=m CONFIG_BT_HCIUART=m
CONFIG_BT_HCIUART_H4=y CONFIG_BT_HCIUART_H4=y
CONFIG_BT_HCIUART_BCSP=y CONFIG_BT_HCIUART_BCSP=y
CONFIG_BT_HCIBCM203X=m CONFIG_BT_HCIBCM203X=m
CONFIG_BT_HCIBPA10X=m CONFIG_BT_HCIBPA10X=m
CONFIG_BT_HCIBFUSB=m CONFIG_BT_HCIBFUSB=m
CONFIG_BT_HCIDTL1=m CONFIG_BT_HCIDTL1=m
CONFIG_BT_HCIBT3C=m CONFIG_BT_HCIBT3C=m
CONFIG_BT_HCIBLUECARD=m CONFIG_BT_HCIBLUECARD=m
CONFIG_BT_HCIBTUART=m CONFIG_BT_HCIBTUART=m
CONFIG_BT_HCIVHCI=m CONFIG_BT_HCIVHCI=m
CONFIG_IEEE80211=m CONFIG_IEEE80211=m
# CONFIG_IEEE80211_DEBUG is not set # CONFIG_IEEE80211_DEBUG is not set
CONFIG_IEEE80211_CRYPT_WEP=m CONFIG_IEEE80211_CRYPT_WEP=m
CONFIG_IEEE80211_CRYPT_CCMP=m CONFIG_IEEE80211_CRYPT_CCMP=m
CONFIG_IEEE80211_CRYPT_TKIP=m CONFIG_IEEE80211_CRYPT_TKIP=m
CONFIG_IEEE80211_SOFTMAC=m CONFIG_IEEE80211_SOFTMAC=m
CONFIG_IEEE80211_SOFTMAC_DEBUG=y CONFIG_IEEE80211_SOFTMAC_DEBUG=y
CONFIG_TUX=m CONFIG_TUX=m

# #
# TUX options # TUX options
# #
CONFIG_TUX_EXTCGI=y CONFIG_TUX_EXTCGI=y
CONFIG_TUX_EXTENDED_LOG=y CONFIG_TUX_EXTENDED_LOG=y
# CONFIG_TUX_DEBUG is not set # CONFIG_TUX_DEBUG is not set
CONFIG_WIRELESS_EXT=y CONFIG_WIRELESS_EXT=y
CONFIG_NETLABEL=y CONFIG_NETLABEL=y
CONFIG_FIB_RULES=y CONFIG_FIB_RULES=y

# #
# Device Drivers # Device Drivers
# #

# #
# Generic Driver Options # Generic Driver Options
# #
CONFIG_STANDALONE=y CONFIG_STANDALONE=y
CONFIG_PREVENT_FIRMWARE_BUILD=y CONFIG_PREVENT_FIRMWARE_BUILD=y
CONFIG_FW_LOADER=y CONFIG_FW_LOADER=y
# CONFIG_DEBUG_DRIVER is not set # CONFIG_DEBUG_DRIVER is not set
# CONFIG_SYS_HYPERVISOR is not set # CONFIG_SYS_HYPERVISOR is not set

# #
# Connector - unified userspace <-> kernelspace linker # Connector - unified userspace <-> kern
# #
CONFIG_CONNECTOR=y CONFIG_CONNECTOR=y
CONFIG_PROC_EVENTS=y CONFIG_PROC_EVENTS=y

# #
# Memory Technology Devices (MTD) # Memory Technology Devices (MTD)
# #
CONFIG_MTD=m CONFIG_MTD=m
# CONFIG_MTD_DEBUG is not set # CONFIG_MTD_DEBUG is not set
CONFIG_MTD_CONCAT=m CONFIG_MTD_CONCAT=m
CONFIG_MTD_PARTITIONS=y CONFIG_MTD_PARTITIONS=y
CONFIG_MTD_REDBOOT_PARTS=m CONFIG_MTD_REDBOOT_PARTS=m
CONFIG_MTD_REDBOOT_DIRECTORY_BLOCK=-1 CONFIG_MTD_REDBOOT_DIRECTORY_BLOCK=-1
# CONFIG_MTD_REDBOOT_PARTS_UNALLOCATED is not set # CONFIG_MTD_REDBOOT_PARTS_UNALLOCATED is not
# CONFIG_MTD_REDBOOT_PARTS_READONLY is not set # CONFIG_MTD_REDBOOT_PARTS_READONLY is not set
CONFIG_MTD_CMDLINE_PARTS=y CONFIG_MTD_CMDLINE_PARTS=y

# #
# User Modules And Translation Layers # User Modules And Translation Layers
# #
CONFIG_MTD_CHAR=m CONFIG_MTD_CHAR=m
CONFIG_MTD_BLOCK=m CONFIG_MTD_BLOCK=m
CONFIG_MTD_BLOCK_RO=m CONFIG_MTD_BLOCK_RO=m
CONFIG_FTL=m CONFIG_FTL=m
CONFIG_NFTL=m CONFIG_NFTL=m
CONFIG_NFTL_RW=y CONFIG_NFTL_RW=y
# CONFIG_INFTL is not set # CONFIG_INFTL is not set
CONFIG_RFD_FTL=m CONFIG_RFD_FTL=m

```

```

# #
# RAM/ROM/Flash chip drivers # RAM/ROM/Flash chip drivers
# #
CONFIG_MTD_CFI=m CONFIG_MTD_CFI=m
CONFIG_MTD_JEDECPROBE=m CONFIG_MTD_JEDECPROBE=m
CONFIG_MTD_GEN_PROBE=m CONFIG_MTD_GEN_PROBE=m
# CONFIG_MTD_CFI_ADV_OPTIONS is not set # CONFIG_MTD_CFI_ADV_OPTIONS is not set
CONFIG_MTD_MAP_BANK_WIDTH_1=y CONFIG_MTD_MAP_BANK_WIDTH_1=y
CONFIG_MTD_MAP_BANK_WIDTH_2=y CONFIG_MTD_MAP_BANK_WIDTH_2=y
CONFIG_MTD_MAP_BANK_WIDTH_4=y CONFIG_MTD_MAP_BANK_WIDTH_4=y
# CONFIG_MTD_MAP_BANK_WIDTH_8 is not set # CONFIG_MTD_MAP_BANK_WIDTH_8 is not set
# CONFIG_MTD_MAP_BANK_WIDTH_16 is not set # CONFIG_MTD_MAP_BANK_WIDTH_16 is not set
# CONFIG_MTD_MAP_BANK_WIDTH_32 is not set # CONFIG_MTD_MAP_BANK_WIDTH_32 is not set
CONFIG_MTD_CFI_I1=y CONFIG_MTD_CFI_I1=y
CONFIG_MTD_CFI_I2=y CONFIG_MTD_CFI_I2=y
# CONFIG_MTD_CFI_I4 is not set # CONFIG_MTD_CFI_I4 is not set
# CONFIG_MTD_CFI_I8 is not set # CONFIG_MTD_CFI_I8 is not set
CONFIG_MTD_CFI_INTELEXT=m CONFIG_MTD_CFI_INTELEXT=m
CONFIG_MTD_CFI_AMDSTD=m CONFIG_MTD_CFI_AMDSTD=m
CONFIG_MTD_CFI_STAA=m CONFIG_MTD_CFI_STAA=m
CONFIG_MTD_CFI_UTIL=m CONFIG_MTD_CFI_UTIL=m
CONFIG_MTD_RAM=m CONFIG_MTD_RAM=m
CONFIG_MTD_ROM=m CONFIG_MTD_ROM=m
CONFIG_MTD_ABSENT=m CONFIG_MTD_ABSENT=m
# CONFIG_MTD_OBSOLETE_CHIPS is not set # CONFIG_MTD_OBSOLETE_CHIPS is not set

# #
# Mapping drivers for chip access # Mapping drivers for chip access
# #
# CONFIG_MTD_COMPLEX_MAPPINGS is not set # CONFIG_MTD_COMPLEX_MAPPINGS is not set
# CONFIG_MTD_PHYSMAP is not set # CONFIG_MTD_PHYSMAP is not set
# CONFIG_MTD_PNC2000 is not set # CONFIG_MTD_PNC2000 is not set
CONFIG_MTD_SC520CDP=m CONFIG_MTD_SC520CDP=m
CONFIG_MTD_NETSC520=m CONFIG_MTD_NETSC520=m
CONFIG_MTD_TS5500=m CONFIG_MTD_TS5500=m
# CONFIG_MTD_AMD76XROM is not set # CONFIG_MTD_AMD76XROM is not set
# CONFIG_MTD_ICHXROM is not set # CONFIG_MTD_ICHXROM is not set
CONFIG_MTD_SCB2_FLASH=m CONFIG_MTD_SCB2_FLASH=m
# CONFIG_MTD_NETtel is not set # CONFIG_MTD_NETtel is not set
# CONFIG_MTD_DILNETPC is not set # CONFIG_MTD_DILNETPC is not set
# CONFIG_MTD_L440GX is not set # CONFIG_MTD_L440GX is not set
# CONFIG_MTD_PLATRAM is not set # CONFIG_MTD_PLATRAM is not set

# #
# Self-contained MTD device drivers # Self-contained MTD device drivers
# #
# CONFIG_MTD_PMC551 is not set # CONFIG_MTD_PMC551 is not set
# CONFIG_MTD_SLRAM is not set # CONFIG_MTD_SLRAM is not set
# CONFIG_MTD_PHRAM is not set # CONFIG_MTD_PHRAM is not set
CONFIG_MTD_MTDDRAM=m CONFIG_MTD_MTDDRAM=m
CONFIG_MTD_MTDDRAM_TOTAL_SIZE=4096 CONFIG_MTD_MTDDRAM_TOTAL_SIZE=4096
CONFIG_MTD_MTDDRAM_ERASE_SIZE=128 CONFIG_MTD_MTDDRAM_ERASE_SIZE=128
CONFIG_MTD_BLOCK2MTD=m CONFIG_MTD_BLOCK2MTD=m

# #
# Disk-On-Chip Device Drivers # Disk-On-Chip Device Drivers
# #
# CONFIG_MTD_DOC2000 is not set # CONFIG_MTD_DOC2000 is not set
# CONFIG_MTD_DOC2001 is not set # CONFIG_MTD_DOC2001 is not set
# CONFIG_MTD_DOC2001PLUS is not set # CONFIG_MTD_DOC2001PLUS is not set

# #
# NAND Flash Device Drivers # NAND Flash Device Drivers
# #
CONFIG_MTD_NAND=m CONFIG_MTD_NAND=m
# CONFIG_MTD_NAND_VERIFY_WRITE is not set # CONFIG_MTD_NAND_VERIFY_WRITE is not set
CONFIG_MTD_NAND_ECC_SMC=y CONFIG_MTD_NAND_ECC_SMC=y
CONFIG_MTD_NAND_IDS=m CONFIG_MTD_NAND_IDS=m
CONFIG_MTD_NAND_DISKONCHIP=m CONFIG_MTD_NAND_DISKONCHIP=m
# CONFIG_MTD_NAND_DISKONCHIP_PROBE_ADVANCED is not set # CONFIG_MTD_NAND_DISKONCHIP_PROBE_ADVAN
CONFIG_MTD_NAND_DISKONCHIP_PROBE_ADDRESS=0 CONFIG_MTD_NAND_DISKONCHIP_PROBE_ADDRESS=0
# CONFIG_MTD_NAND_DISKONCHIP_BBTWRITE is not set # CONFIG_MTD_NAND_DISKONCHIP_BBTWRITE is not s
CONFIG_MTD_NAND_CS553X=m CONFIG_MTD_NAND_CS553X=m
CONFIG_MTD_NAND_NANDSIM=m CONFIG_MTD_NAND_NANDSIM=m

# #
# OneNAND Flash Device Drivers # OneNAND Flash Device Drivers
# #
# CONFIG_MTD_ONENAND is not set # CONFIG_MTD_ONENAND is not set

```

```

#           #
# Parallel port support           # Parallel port support
#           #
CONFIG_PARPORT=m           CONFIG_PARPORT=m
CONFIG_PARPORT_PC=m       CONFIG_PARPORT_PC=m
CONFIG_PARPORT_SERIAL=m   CONFIG_PARPORT_SERIAL=m
# CONFIG_PARPORT_PC_FIFO is not set # CONFIG_PARPORT_PC_FIFO is not set
# CONFIG_PARPORT_PC_SUPERIO is not set # CONFIG_PARPORT_PC_SUPERIO is not set
CONFIG_PARPORT_PC_PCMCIA=m CONFIG_PARPORT_PC_PCMCIA=m
CONFIG_PARPORT_NOT_PC=y   CONFIG_PARPORT_NOT_PC=y
# CONFIG_PARPORT_GSC is not set # CONFIG_PARPORT_GSC is not set
# CONFIG_PARPORT_AX88796 is not set # CONFIG_PARPORT_AX88796 is not set
CONFIG_PARPORT_1284=y     CONFIG_PARPORT_1284=y

#           #
# Plug and Play support         # Plug and Play support
#           #
CONFIG_PNP=y             CONFIG_PNP=y
# CONFIG_PNP_DEBUG is not set # CONFIG_PNP_DEBUG is not set

#           #
# Protocols                     # Protocols
#           #
CONFIG_PNPACPI=y        CONFIG_PNPACPI=y

#           #
# Block devices                 # Block devices
#           #
CONFIG_BLK_DEV_FD=m     CONFIG_BLK_DEV_FD=m
CONFIG_PARIDE=m         CONFIG_PARIDE=m
CONFIG_PARIDE_PARPORT=m CONFIG_PARIDE_PARPORT=m

#           #
# Parallel IDE high-level drivers # Parallel IDE high-level drivers
#           #
CONFIG_PARIDE_PD=m      CONFIG_PARIDE_PD=m
CONFIG_PARIDE_PCD=m    CONFIG_PARIDE_PCD=m
CONFIG_PARIDE_PF=m     CONFIG_PARIDE_PF=m
CONFIG_PARIDE_PT=m     CONFIG_PARIDE_PT=m
CONFIG_PARIDE_PG=m     CONFIG_PARIDE_PG=m

#           #
# Parallel IDE protocol modules # Parallel IDE protocol modules
#           #
CONFIG_PARIDE_ATEN=m   CONFIG_PARIDE_ATEN=m
CONFIG_PARIDE_BPCK=m   CONFIG_PARIDE_BPCK=m
CONFIG_PARIDE_BPCK6=m  CONFIG_PARIDE_BPCK6=m
CONFIG_PARIDE_COMM=m   CONFIG_PARIDE_COMM=m
CONFIG_PARIDE_DSTR=m   CONFIG_PARIDE_DSTR=m
CONFIG_PARIDE_FIT2=m   CONFIG_PARIDE_FIT2=m
CONFIG_PARIDE_FIT3=m   CONFIG_PARIDE_FIT3=m
CONFIG_PARIDE_EPAT=m   CONFIG_PARIDE_EPAT=m
CONFIG_PARIDE_EPATC8=y CONFIG_PARIDE_EPATC8=y
CONFIG_PARIDE_EPIA=m   CONFIG_PARIDE_EPIA=m
CONFIG_PARIDE_FRIQ=m   CONFIG_PARIDE_FRIQ=m
CONFIG_PARIDE_FRPW=m   CONFIG_PARIDE_FRPW=m
CONFIG_PARIDE_KBIC=m   CONFIG_PARIDE_KBIC=m
CONFIG_PARIDE_KTTI=m   CONFIG_PARIDE_KTTI=m
CONFIG_PARIDE_ON20=m   CONFIG_PARIDE_ON20=m
CONFIG_PARIDE_ON26=m   CONFIG_PARIDE_ON26=m
CONFIG_BLK_CPQ_DA=m    CONFIG_BLK_CPQ_DA=m
CONFIG_BLK_CPQ_CISS_DA=m CONFIG_BLK_CPQ_CISS_DA=m
CONFIG_CISS_SCSI_TAPE=y CONFIG_CISS_SCSI_TAPE=y
CONFIG_BLK_DEV_DAC960=m CONFIG_BLK_DEV_DAC960=m
# CONFIG_BLK_DEV_UMEM is not set # CONFIG_BLK_DEV_UMEM is not set
# CONFIG_BLK_DEV_COW_COMMON is not set # CONFIG_BLK_DEV_COW_COMMON is not set
CONFIG_BLK_DEV_LOOP=m  CONFIG_BLK_DEV_LOOP=m
CONFIG_BLK_DEV_CRYPTOLOOP=m CONFIG_BLK_DEV_CRYPTOLOOP=m
CONFIG_BLK_DEV_NBD=m   CONFIG_BLK_DEV_NBD=m
CONFIG_BLK_DEV_SX8=m   CONFIG_BLK_DEV_SX8=m
# CONFIG_BLK_DEV_UB is not set # CONFIG_BLK_DEV_UB is not set
CONFIG_BLK_DEV_RAM=y   CONFIG_BLK_DEV_RAM=y
CONFIG_BLK_DEV_RAM_COUNT=16 CONFIG_BLK_DEV_RAM_COUNT=16
CONFIG_BLK_DEV_RAM_SIZE=16384 CONFIG_BLK_DEV_RAM_SIZE=16384
CONFIG_BLK_DEV_RAM_BLOCKSIZE=4096 CONFIG_BLK_DEV_RAM_BLOCKSIZE=4096
CONFIG_BLK_DEV_INITRD=y CONFIG_BLK_DEV_INITRD=y
CONFIG_CDROM_PKTCDVD=m CONFIG_CDROM_PKTCDVD=m
CONFIG_CDROM_PKTCDVD_BUFFERS=8 CONFIG_CDROM_PKTCDVD_BUFFERS=8

```

```

# CONFIG_CDROM_PKTCDVD_WCACHE is not set # CONFIG_CDROM_PKTCDVD_WCACHE is not set
CONFIG_ATA_OVER_ETH=m CONFIG_ATA_OVER_ETH=m

# #
# ATA/ATAPI/MFM/RLL support # ATA/ATAPI/MFM/RLL support
# #
CONFIG_IDE=y CONFIG_IDE=y
CONFIG_BLK_DEV_IDE=y CONFIG_BLK_DEV_IDE=y

# #
# Please see Documentation/ide.txt for help/info on IDE drive # Please see Documentation/ide.txt
# #
# CONFIG_BLK_DEV_IDE_SATA is not set # CONFIG_BLK_DEV_IDE_SATA is not set
# CONFIG_BLK_DEV_IDE_HD is not set # CONFIG_BLK_DEV_IDE_HD is not set
CONFIG_BLK_DEV_IDEDISK=y CONFIG_BLK_DEV_IDEDISK=y
CONFIG_IDEDISK_MULTI_MODE=y CONFIG_IDEDISK_MULTI_MODE=y
CONFIG_BLK_DEV_IDECS=m CONFIG_BLK_DEV_IDECS=m
CONFIG_BLK_DEV_IDECD=m CONFIG_BLK_DEV_IDECD=m
# CONFIG_BLK_DEV_IDETAPE is not set # CONFIG_BLK_DEV_IDETAPE is not set
CONFIG_BLK_DEV_IDEFLOPPY=y CONFIG_BLK_DEV_IDEFLOPPY=y
CONFIG_BLK_DEV_IDESCSI=m CONFIG_BLK_DEV_IDESCSI=m
CONFIG_IDE_TASK_IOCTL=y CONFIG_IDE_TASK_IOCTL=y

# #
# IDE chipset support/bugfixes # IDE chipset support/bugfixes
# #
CONFIG_IDE_GENERIC=y CONFIG_IDE_GENERIC=y
CONFIG_BLK_DEV_CMD640=y CONFIG_BLK_DEV_CMD640=y
CONFIG_BLK_DEV_CMD640_ENHANCED=y CONFIG_BLK_DEV_CMD640_ENHANCED=y
CONFIG_BLK_DEV_IDEPNP=y CONFIG_BLK_DEV_IDEPNP=y
CONFIG_BLK_DEV_IDEPCI=y CONFIG_BLK_DEV_IDEPCI=y
CONFIG_IDEPCI_SHARE_IRQ=y CONFIG_IDEPCI_SHARE_IRQ=y
# CONFIG_BLK_DEV_OFFBOARD is not set # CONFIG_BLK_DEV_OFFBOARD is not set
CONFIG_BLK_DEV_GENERIC=y CONFIG_BLK_DEV_GENERIC=y
# CONFIG_BLK_DEV_OPTI621 is not set # CONFIG_BLK_DEV_OPTI621 is not set
CONFIG_BLK_DEV_RZ1000=y CONFIG_BLK_DEV_RZ1000=y
CONFIG_BLK_DEV_IDEDMA_PCI=y CONFIG_BLK_DEV_IDEDMA_PCI=y
# CONFIG_BLK_DEV_IDEDMA_FORCED is not set # CONFIG_BLK_DEV_IDEDMA_FORCED is not set
CONFIG_IDEDMA_PCI_AUTO=y CONFIG_IDEDMA_PCI_AUTO=y
# CONFIG_IDEDMA_ONLYDISK is not set # CONFIG_IDEDMA_ONLYDISK is not set
CONFIG_BLK_DEV_AEC62XX=y CONFIG_BLK_DEV_AEC62XX=y
CONFIG_BLK_DEV_ALI15X3=y CONFIG_BLK_DEV_ALI15X3=y
# CONFIG_WDC_ALI15X3 is not set # CONFIG_WDC_ALI15X3 is not set
CONFIG_BLK_DEV_AMD74XX=y CONFIG_BLK_DEV_AMD74XX=y
CONFIG_BLK_DEV_ATIIXP=y CONFIG_BLK_DEV_ATIIXP=y
CONFIG_BLK_DEV_CMD64X=y CONFIG_BLK_DEV_CMD64X=y
CONFIG_BLK_DEV_TRIFLEX=y CONFIG_BLK_DEV_TRIFLEX=y
# CONFIG_BLK_DEV_CY82C693 is not set # CONFIG_BLK_DEV_CY82C693 is not set
CONFIG_BLK_DEV_CS5520=y CONFIG_BLK_DEV_CS5520=y
CONFIG_BLK_DEV_CS5530=y CONFIG_BLK_DEV_CS5530=y
CONFIG_BLK_DEV_CS5535=y CONFIG_BLK_DEV_CS5535=y
CONFIG_BLK_DEV_HPT34X=y CONFIG_BLK_DEV_HPT34X=y
# CONFIG_HPT34X_AUTODMA is not set # CONFIG_HPT34X_AUTODMA is not set
CONFIG_BLK_DEV_HPT366=y CONFIG_BLK_DEV_HPT366=y
# CONFIG_BLK_DEV_SC1200 is not set # CONFIG_BLK_DEV_SC1200 is not set
CONFIG_BLK_DEV_PIIX=y CONFIG_BLK_DEV_PIIX=y
CONFIG_BLK_DEV_IT821X=y CONFIG_BLK_DEV_IT821X=y
# CONFIG_BLK_DEV_NS87415 is not set # CONFIG_BLK_DEV_NS87415 is not set
CONFIG_BLK_DEV_PDC202XX_OLD=y CONFIG_BLK_DEV_PDC202XX_OLD=y
# CONFIG_PDC202XX_BURST is not set # CONFIG_PDC202XX_BURST is not set
CONFIG_BLK_DEV_PDC202XX_NEW=y CONFIG_BLK_DEV_PDC202XX_NEW=y
CONFIG_BLK_DEV_SVWKS=y CONFIG_BLK_DEV_SVWKS=y
CONFIG_BLK_DEV_SIIMAGE=y CONFIG_BLK_DEV_SIIMAGE=y
CONFIG_BLK_DEV_SIS5513=y CONFIG_BLK_DEV_SIS5513=y
# CONFIG_BLK_DEV_SLC90E66 is not set # CONFIG_BLK_DEV_SLC90E66 is not set
# CONFIG_BLK_DEV_TRM290 is not set # CONFIG_BLK_DEV_TRM290 is not set
CONFIG_BLK_DEV_VIA82CXXX=y CONFIG_BLK_DEV_VIA82CXXX=y
# CONFIG_IDE_ARM is not set # CONFIG_IDE_ARM is not set
CONFIG_BLK_DEV_IDEDMA=y CONFIG_BLK_DEV_IDEDMA=y
# CONFIG_IDEDMA_IVB is not set # CONFIG_IDEDMA_IVB is not set
CONFIG_IDEDMA_AUTO=y CONFIG_IDEDMA_AUTO=y
# CONFIG_BLK_DEV_HD is not set # CONFIG_BLK_DEV_HD is not set

# #
# SCSI device support # SCSI device support
# #
CONFIG_RAID_ATTRS=m CONFIG_RAID_ATTRS=m
CONFIG_SCSI=m CONFIG_SCSI=m
CONFIG_SCSI_NETLINK=y CONFIG_SCSI_NETLINK=y

```

```

CONFIG_SCSI_PROC_FS=y          CONFIG_SCSI_PROC_FS=y

#          #
# SCSI support type (disk, tape, CD-ROM) # SCSI support type (disk, tape, CD-ROM)
#          #
CONFIG_BLK_DEV_SD=m           CONFIG_BLK_DEV_SD=m
CONFIG_CHR_DEV_ST=m           CONFIG_CHR_DEV_ST=m
CONFIG_CHR_DEV_OSST=m         CONFIG_CHR_DEV_OSST=m
CONFIG_BLK_DEV_SR=m           CONFIG_BLK_DEV_SR=m
CONFIG_BLK_DEV_SR_VENDOR=y     CONFIG_BLK_DEV_SR_VENDOR=y
CONFIG_CHR_DEV_SG=m           CONFIG_CHR_DEV_SG=m
CONFIG_CHR_DEV_SCH=m          CONFIG_CHR_DEV_SCH=m

#          #
# Some SCSI devices (e.g. CD jukebox) support multiple LUNs # Some SCSI devices (e.g. CD jukebox)
#          #
CONFIG_SCSI_MULTI_LUN=y        CONFIG_SCSI_MULTI_LUN=y
CONFIG_SCSI_CONSTANTS=y        CONFIG_SCSI_CONSTANTS=y
CONFIG_SCSI_LOGGING=y          CONFIG_SCSI_LOGGING=y

#          #
# SCSI Transport # SCSI Transport
#          #
CONFIG_SCSI_SPI_ATTRS=m        CONFIG_SCSI_SPI_ATTRS=m
CONFIG_SCSI_FC_ATTRS=m         CONFIG_SCSI_FC_ATTRS=m
CONFIG_SCSI_ISCSI_ATTRS=m      CONFIG_SCSI_ISCSI_ATTRS=m
CONFIG_SCSI_SAS_ATTRS=m        CONFIG_SCSI_SAS_ATTRS=m
CONFIG_SCSI_SAS_LIBSAS=m       CONFIG_SCSI_SAS_LIBSAS=m
# CONFIG_SCSI_SAS_LIBSAS_DEBUG is not set # CONFIG_SCSI_SAS_LIBSAS_DEBUG is not set

#          #
# SCSI low-level drivers # SCSI low-level drivers
#          #
CONFIG_ISCSI_TCP=m             CONFIG_ISCSI_TCP=m
CONFIG_BLK_DEV_3W_XXXX_RAID=m  CONFIG_BLK_DEV_3W_XXXX_RAID=m
CONFIG_SCSI_3W_9XXX=m          CONFIG_SCSI_3W_9XXX=m
CONFIG_SCSI_ACARD=m            CONFIG_SCSI_ACARD=m
CONFIG_SCSI_AACRAID=m          CONFIG_SCSI_AACRAID=m
CONFIG_SCSI_AIC7XXX=m          CONFIG_SCSI_AIC7XXX=m
CONFIG_AIC7XXX_CMDS_PER_DEVICE=4 CONFIG_AIC7XXX_CMDS_PER_DEVICE=4
CONFIG_AIC7XXX_RESET_DELAY_MS=15000 CONFIG_AIC7XXX_RESET_DELAY_MS=15000
# CONFIG_AIC7XXX_DEBUG_ENABLE is not set # CONFIG_AIC7XXX_DEBUG_ENABLE is not set
CONFIG_AIC7XXX_DEBUG_MASK=0    CONFIG_AIC7XXX_DEBUG_MASK=0
# CONFIG_AIC7XXX_REG_PRETTY_PRINT is not set # CONFIG_AIC7XXX_REG_PRETTY_PRINT is not set
CONFIG_SCSI_AIC7XXX_OLD=m       CONFIG_SCSI_AIC7XXX_OLD=m
CONFIG_SCSI_AIC79XX=m          CONFIG_SCSI_AIC79XX=m
CONFIG_AIC79XX_CMDS_PER_DEVICE=4 CONFIG_AIC79XX_CMDS_PER_DEVICE=4
CONFIG_AIC79XX_RESET_DELAY_MS=15000 CONFIG_AIC79XX_RESET_DELAY_MS=15000
# CONFIG_AIC79XX_ENABLE_RD_STRM is not set # CONFIG_AIC79XX_ENABLE_RD_STRM is not set
# CONFIG_AIC79XX_DEBUG_ENABLE is not set # CONFIG_AIC79XX_DEBUG_ENABLE is not set
CONFIG_AIC79XX_DEBUG_MASK=0    CONFIG_AIC79XX_DEBUG_MASK=0
# CONFIG_AIC79XX_REG_PRETTY_PRINT is not set # CONFIG_AIC79XX_REG_PRETTY_PRINT is not set
CONFIG_SCSI_AIC94XX=m          CONFIG_SCSI_AIC94XX=m
# CONFIG_AIC94XX_DEBUG is not set # CONFIG_AIC94XX_DEBUG is not set
# CONFIG_SCSI_DPT_I2O is not set # CONFIG_SCSI_DPT_I2O is not set
# CONFIG_SCSI_ADVANSYS is not set # CONFIG_SCSI_ADVANSYS is not set
CONFIG_MEGARAID_NEWGEN=y        CONFIG_MEGARAID_NEWGEN=y
CONFIG_MEGARAID_MM=m           CONFIG_MEGARAID_MM=m
CONFIG_MEGARAID_MAILBOX=m       CONFIG_MEGARAID_MAILBOX=m
CONFIG_MEGARAID_LEGACY=m        CONFIG_MEGARAID_LEGACY=m
CONFIG_MEGARAID_SAS=m          CONFIG_MEGARAID_SAS=m
CONFIG_SCSI_SATA=m             CONFIG_SCSI_SATA=m
CONFIG_SCSI_SATA_AHCI=m         CONFIG_SCSI_SATA_AHCI=m
CONFIG_SCSI_SATA_SVW=m          CONFIG_SCSI_SATA_SVW=m
CONFIG_SCSI_ATA_PIIX=m          CONFIG_SCSI_ATA_PIIX=m
CONFIG_SCSI_SATA_MV=m           CONFIG_SCSI_SATA_MV=m
CONFIG_SCSI_SATA_NV=m           CONFIG_SCSI_SATA_NV=m
CONFIG_SCSI_PDC_ADMA=m          CONFIG_SCSI_PDC_ADMA=m
CONFIG_SCSI_HPTIOP=m           CONFIG_SCSI_HPTIOP=m
CONFIG_SCSI_SATA_QSTOR=m        CONFIG_SCSI_SATA_QSTOR=m
CONFIG_SCSI_SATA_PROMISE=m      CONFIG_SCSI_SATA_PROMISE=m
CONFIG_SCSI_SATA_SX4=m          CONFIG_SCSI_SATA_SX4=m
CONFIG_SCSI_SATA_SIL=m          CONFIG_SCSI_SATA_SIL=m
CONFIG_SCSI_SATA_SIL24=m        CONFIG_SCSI_SATA_SIL24=m
CONFIG_SCSI_SATA_SIS=m          CONFIG_SCSI_SATA_SIS=m
CONFIG_SCSI_SATA_ULI=m          CONFIG_SCSI_SATA_ULI=m
CONFIG_SCSI_SATA_VIA=m          CONFIG_SCSI_SATA_VIA=m
CONFIG_SCSI_SATA_VITESSE=m      CONFIG_SCSI_SATA_VITESSE=m
CONFIG_SCSI_SATA_INTEL_COMBINED=y CONFIG_SCSI_SATA_INTEL_COMBINED=y

```

```

# CONFIG_SCSI_BUSLOGIC is not set      # CONFIG_SCSI_BUSLOGIC is not set
# CONFIG_SCSI_DM3191D is not set      # CONFIG_SCSI_DM3191D is not set
# CONFIG_SCSI_EATA is not set         # CONFIG_SCSI_EATA is not set
# CONFIG_SCSI_FUTURE_DOMAIN is not set # CONFIG_SCSI_FUTURE_DOMAIN is not set
CONFIG_SCSI_GDTH=m                    CONFIG_SCSI_GDTH=m
CONFIG_SCSI_IPS=m                     CONFIG_SCSI_IPS=m
CONFIG_SCSI_INITIO=m                  CONFIG_SCSI_INITIO=m
# CONFIG_SCSI_INIA100 is not set      # CONFIG_SCSI_INIA100 is not set
CONFIG_SCSI_PPA=m                     CONFIG_SCSI_PPA=m
CONFIG_SCSI_IMM=m                     CONFIG_SCSI_IMM=m
# CONFIG_SCSI_IZIP_EPP16 is not set   # CONFIG_SCSI_IZIP_EPP16 is not set
# CONFIG_SCSI_IZIP_SLOW_CTR is not set # CONFIG_SCSI_IZIP_SLOW_CTR is not set
CONFIG_SCSI_STEX=m                    CONFIG_SCSI_STEX=m
CONFIG_SCSI_SYM53C8XX_2=m             CONFIG_SCSI_SYM53C8XX_2=m
CONFIG_SCSI_SYM53C8XX_DMA_ADDRESSING_MODE=1 CONFIG_SCSI_SYM53C8XX_DMA_ADDRESSING_MODE=1
CONFIG_SCSI_SYM53C8XX_DEFAULT_TAGS=16 CONFIG_SCSI_SYM53C8XX_DEFAULT_TAGS=16
CONFIG_SCSI_SYM53C8XX_MAX_TAGS=64    CONFIG_SCSI_SYM53C8XX_MAX_TAGS=64
CONFIG_SCSI_SYM53C8XX_MMIO=y          CONFIG_SCSI_SYM53C8XX_MMIO=y
# CONFIG_SCSI_IPR is not set           # CONFIG_SCSI_IPR is not set
CONFIG_SCSI_QLOGIC_1280=m             CONFIG_SCSI_QLOGIC_1280=m
CONFIG_SCSI_QLA_FC=m                  CONFIG_SCSI_QLA_FC=m
CONFIG_SCSI_QLA_ISCSI=m               CONFIG_SCSI_QLA_ISCSI=m
CONFIG_SCSI_LPFC=m                    CONFIG_SCSI_LPFC=m
CONFIG_SCSI_DC395x=m                  CONFIG_SCSI_DC395x=m
# CONFIG_SCSI_DC390T is not set        # CONFIG_SCSI_DC390T is not set
# CONFIG_SCSI_NS32 is not set          # CONFIG_SCSI_NS32 is not set
# CONFIG_SCSI_DEBUG is not set        # CONFIG_SCSI_DEBUG is not set

#
# PCMCIA SCSI adapter support         # PCMCIA SCSI adapter support
#
# CONFIG_PCMCIA_AHA152X is not set     # CONFIG_PCMCIA_AHA152X is not set
CONFIG_PCMCIA_FDOMAIN=m               CONFIG_PCMCIA_FDOMAIN=m
# CONFIG_PCMCIA_NINJA_SCSI is not set  # CONFIG_PCMCIA_NINJA_SCSI is not set
# CONFIG_PCMCIA_QLOGIC is not set     # CONFIG_PCMCIA_QLOGIC is not set
# CONFIG_PCMCIA_SYM53C500 is not set   # CONFIG_PCMCIA_SYM53C500 is not set

#
# Multi-device support (RAID and LVM) # Multi-device support (RAID and LVM)
#
CONFIG_MD=y                            CONFIG_MD=y
CONFIG_BLK_DEV_MD=y                    CONFIG_BLK_DEV_MD=y
CONFIG_MD_LINEAR=m                     CONFIG_MD_LINEAR=m
CONFIG_MD_RAID0=m                      CONFIG_MD_RAID0=m
CONFIG_MD_RAID1=m                      CONFIG_MD_RAID1=m
CONFIG_MD_RAID10=m                     CONFIG_MD_RAID10=m
CONFIG_MD_RAID456=m                    CONFIG_MD_RAID456=m
CONFIG_MD_RAID5_RESHAPE=y              CONFIG_MD_RAID5_RESHAPE=y
CONFIG_MD_MULTIPATH=m                  CONFIG_MD_MULTIPATH=m
CONFIG_MD_FAULTY=m                     CONFIG_MD_FAULTY=m
CONFIG_BLK_DEV_DM=m                     CONFIG_BLK_DEV_DM=m
CONFIG_DM_CRYPT=m                       CONFIG_DM_CRYPT=m
CONFIG_DM_SNAPSHOT=m                   CONFIG_DM_SNAPSHOT=m
CONFIG_DM_MIRROR=m                     CONFIG_DM_MIRROR=m
CONFIG_DM_ZERO=m                       CONFIG_DM_ZERO=m
CONFIG_DM_MULTIPATH=m                  CONFIG_DM_MULTIPATH=m
CONFIG_DM_MULTIPATH_EMCM=m             CONFIG_DM_MULTIPATH_EMCM=m

#
# Fusion MPT device support           # Fusion MPT device support
#
CONFIG_FUSION=y                         CONFIG_FUSION=y
CONFIG_FUSION_SPI=m                    CONFIG_FUSION_SPI=m
CONFIG_FUSION_FC=m                     CONFIG_FUSION_FC=m
CONFIG_FUSION_SAS=m                     CONFIG_FUSION_SAS=m
CONFIG_FUSION_MAX_SGE=40               CONFIG_FUSION_MAX_SGE=40
CONFIG_FUSION_CTL=m                     CONFIG_FUSION_CTL=m
CONFIG_FUSION_LAN=m                     CONFIG_FUSION_LAN=m

#
# IEEE 1394 (FireWire) support        # IEEE 1394 (FireWire) support
#
# CONFIG_IEEE1394 is not set           | CONFIG_IEEE1394=m
>
> #
> # Subsystem Options
> #
> # CONFIG_IEEE1394_VERBOSEDEBUG is not set
> CONFIG_IEEE1394_OUI_DB=y

```

```

> CONFIG_IEEE1394_EXTRA_CONFIG_ROMS=y
> CONFIG_IEEE1394_CONFIG_ROM_IP1394=y
> CONFIG_IEEE1394_EXPORT_FULL_API=y
>
> #
> # Device Drivers
> #
> CONFIG_IEEE1394_PCILYNX=m
> CONFIG_IEEE1394_OHCI1394=m
>
> #
> # Protocol Drivers
> #
> CONFIG_IEEE1394_VIDEO1394=m
> CONFIG_IEEE1394_SBP2=m
> # CONFIG_IEEE1394_SBP2_PHYS_DMA is not set
> CONFIG_IEEE1394_ETH1394=m
> CONFIG_IEEE1394_DV1394=m
> CONFIG_IEEE1394_RAWIO=m

# #
# I2O device support # I2O device support
# #
CONFIG_I2O=m CONFIG_I2O=m
# CONFIG_I2O_LCT_NOTIFY_ON_CHANGES is not set # CONFIG_I2O_LCT_NOTIFY_ON_CHANGES is not set
CONFIG_I2O_EXT_ADAPTEC=y CONFIG_I2O_EXT_ADAPTEC=y
CONFIG_I2O_CONFIG=m CONFIG_I2O_CONFIG=m
CONFIG_I2O_CONFIG_OLD_IOCTL=y CONFIG_I2O_CONFIG_OLD_IOCTL=y
CONFIG_I2O_BUS=m CONFIG_I2O_BUS=m
CONFIG_I2O_BLOCK=m CONFIG_I2O_BLOCK=m
CONFIG_I2O_SCSI=m CONFIG_I2O_SCSI=m
CONFIG_I2O_PROC=m CONFIG_I2O_PROC=m

# #
# Network device support # Network device support
# #
CONFIG_NETDEVICES=y CONFIG_NETDEVICES=y
CONFIG_IFB=m CONFIG_IFB=m
CONFIG_DUMMY=m CONFIG_DUMMY=m
CONFIG_BONDING=m CONFIG_BONDING=m
# CONFIG_EQUALIZER is not set # CONFIG_EQUALIZER is not set
CONFIG_TUN=m CONFIG_TUN=m
# CONFIG_NET_SB1000 is not set | CONFIG_NET_SB1000=m

# #
# ARCnet devices # ARCnet devices
# #
# CONFIG_ARCNET is not set # CONFIG_ARCNET is not set

# #
# PHY device support # PHY device support
# #
CONFIG_PHYLIB=m CONFIG_PHYLIB=m

# #
# MII PHY device drivers # MII PHY device drivers
# #
CONFIG_MARVELL_PHY=m CONFIG_MARVELL_PHY=m
CONFIG_DAVICOM_PHY=m CONFIG_DAVICOM_PHY=m
CONFIG_QSEMI_PHY=m CONFIG_QSEMI_PHY=m
CONFIG_LXT_PHY=m CONFIG_LXT_PHY=m
CONFIG_CICADA_PHY=m CONFIG_CICADA_PHY=m
CONFIG_VITESSE_PHY=m CONFIG_VITESSE_PHY=m
CONFIG_SMSC_PHY=m CONFIG_SMSC_PHY=m
CONFIG_FIXED_PHY=m CONFIG_FIXED_PHY=m
CONFIG_FIXED_MII_10_FDX=y CONFIG_FIXED_MII_10_FDX=y
CONFIG_FIXED_MII_100_FDX=y CONFIG_FIXED_MII_100_FDX=y

# #
# Ethernet (10 or 100Mbit) # Ethernet (10 or 100Mbit)
# #
CONFIG_NET_ETHERNET=y CONFIG_NET_ETHERNET=y
CONFIG_MII=m CONFIG_MII=m
CONFIG_HAPPYMEAL=m CONFIG_HAPPYMEAL=m
CONFIG_SUNGEM=m CONFIG_SUNGEM=m
CONFIG_CASSINI=m CONFIG_CASSINI=m
CONFIG_NET_VENDOR_3COM=y CONFIG_NET_VENDOR_3COM=y
CONFIG_VORTEX=m CONFIG_VORTEX=m
CONFIG_TYPHOON=m CONFIG_TYPHOON=m

```

```

# #
# Tulip family network device support # Tulip family network device support
# #
CONFIG_NET_TULIP=y CONFIG_NET_TULIP=y
CONFIG_DE2104X=m CONFIG_DE2104X=m
CONFIG_TULIP=m CONFIG_TULIP=m
# CONFIG_TULIP_MWI is not set # CONFIG_TULIP_MWI is not set
CONFIG_TULIP_MMIO=y CONFIG_TULIP_MMIO=y
# CONFIG_TULIP_NAPI is not set # CONFIG_TULIP_NAPI is not set
CONFIG_DE4X5=m CONFIG_DE4X5=m
CONFIG_WINBOND_840=m CONFIG_WINBOND_840=m
CONFIG_DM9102=m CONFIG_DM9102=m
CONFIG_ULI526X=m CONFIG_ULI526X=m
CONFIG_PCPCIA_XIRCOM=m CONFIG_PCPCIA_XIRCOM=m
# CONFIG_HP100 is not set | CONFIG_HP100=m
CONFIG_NET_PCI=y CONFIG_NET_PCI=y
CONFIG_PCNET32=m CONFIG_PCNET32=m
CONFIG_AMD8111_ETH=m CONFIG_AMD8111_ETH=m
CONFIG_AMD8111E_NAPI=y CONFIG_AMD8111E_NAPI=y
CONFIG_ADAPTEC_STARFIRE=m CONFIG_ADAPTEC_STARFIRE=m
CONFIG_ADAPTEC_STARFIRE_NAPI=y CONFIG_ADAPTEC_STARFIRE_NAPI=y
CONFIG_B44=m CONFIG_B44=m
CONFIG_FORCEDETH=m CONFIG_FORCEDETH=m
# CONFIG_DGRS is not set | CONFIG_DGRS=m
# CONFIG_EEPRO100 is not set | CONFIG_EEPRO100=m
CONFIG_E100=m CONFIG_E100=m
CONFIG_FEALNX=m CONFIG_FEALNX=m
CONFIG_NATSEMI=m CONFIG_NATSEMI=m
CONFIG_NE2K_PCI=m CONFIG_NE2K_PCI=m
CONFIG_8139CP=m CONFIG_8139CP=m
CONFIG_8139TOO=m CONFIG_8139TOO=m
# CONFIG_8139TOO_PIO is not set # CONFIG_8139TOO_PIO is not set
# CONFIG_8139TOO_TUNE_TWISTER is not set # CONFIG_8139TOO_TUNE_TWISTER is not set
CONFIG_8139TOO_8129=y CONFIG_8139TOO_8129=y
# CONFIG_8139_OLD_RX_RESET is not set # CONFIG_8139_OLD_RX_RESET is not set
CONFIG_SIS900=m CONFIG_SIS900=m
CONFIG_EPIC100=m CONFIG_EPIC100=m
# CONFIG_SUNDANCE is not set | CONFIG_SUNDANCE=m
> # CONFIG_SUNDANCE_MMIO is not set
CONFIG_TLAN=m CONFIG_TLAN=m
CONFIG_VIA_RHINE=m CONFIG_VIA_RHINE=m
CONFIG_VIA_RHINE_MMIO=y CONFIG_VIA_RHINE_MMIO=y
CONFIG_VIA_RHINE_NAPI=y CONFIG_VIA_RHINE_NAPI=y
CONFIG_NET_POCKET=y CONFIG_NET_POCKET=y
# CONFIG_ATP is not set | CONFIG_ATP=m
# CONFIG_DE600 is not set | CONFIG_DE600=m
# CONFIG_DE620 is not set | CONFIG_DE620=m

# #
# Ethernet (1000 Mbit) # Ethernet (1000 Mbit)
# #
CONFIG_ACENIC=m CONFIG_ACENIC=m
# CONFIG_ACENIC_OMIT_TIGON_I is not set # CONFIG_ACENIC_OMIT_TIGON_I is not set
CONFIG_DL2K=m CONFIG_DL2K=m
CONFIG_E1000=m CONFIG_E1000=m
CONFIG_E1000_NAPI=y CONFIG_E1000_NAPI=y
# CONFIG_E1000_DISABLE_PACKET_SPLIT is not set # CONFIG_E1000_DISABLE_PACKET_SPLIT is not set
CONFIG_NS83820=m CONFIG_NS83820=m
# CONFIG_HAMACHI is not set | CONFIG_HAMACHI=m
# CONFIG_YELLOWFIN is not set | CONFIG_YELLOWFIN=m
CONFIG_R8169=m CONFIG_R8169=m
CONFIG_R8169_NAPI=y CONFIG_R8169_NAPI=y
CONFIG_R8169_VLAN=y CONFIG_R8169_VLAN=y
CONFIG_SIS190=m CONFIG_SIS190=m
CONFIG_SKGE=m CONFIG_SKGE=m
CONFIG_SKY2=m CONFIG_SKY2=m
# CONFIG_SK98LIN is not set | CONFIG_SK98LIN=m
CONFIG_VIA_VELOCITY=m CONFIG_VIA_VELOCITY=m
CONFIG_TIGON3=m CONFIG_TIGON3=m
CONFIG_BNX2=m CONFIG_BNX2=m
# CONFIG_QLA3XXX is not set | CONFIG_QLA3XXX=m

# #
# Ethernet (10000 Mbit) # Ethernet (10000 Mbit)
# #
CONFIG_CHELSIO_T1=m CONFIG_CHELSIO_T1=m
CONFIG_IXGB=m CONFIG_IXGB=m
CONFIG_IXGB_NAPI=y CONFIG_IXGB_NAPI=y

```

```

CONFIG_S2IO=m          CONFIG_S2IO=m
CONFIG_S2IO_NAPI=y     CONFIG_S2IO_NAPI=y
CONFIG_MYRI10GE=m      CONFIG_MYRI10GE=m

#           #
# Token Ring devices   # Token Ring devices
#           #
CONFIG_TR=y           CONFIG_TR=y
CONFIG_IBMOL=m        CONFIG_IBMOL=m
CONFIG_IBMLS=m        CONFIG_IBMLS=m
CONFIG_3C359=m        CONFIG_3C359=m
# CONFIG_TMS380TR is not set # CONFIG_TMS380TR is not set

#           #
# Wireless LAN (non-hamradio) # Wireless LAN (non-hamradio)
#           #
CONFIG_NET_RADIO=y     CONFIG_NET_RADIO=y
CONFIG_NET_WIRELESS_RTNETLINK=y CONFIG_NET_WIRELESS_RTNETLINK=y

#           #
# Obsolete Wireless cards support (pre-802.11) # Obsolete Wireless cards support (pre-802.11)
#           #
# CONFIG_STRIP is not set # CONFIG_STRIP is not set
CONFIG_PCMCIA_WAVELAN=m CONFIG_PCMCIA_WAVELAN=m
CONFIG_PCMCIA_NETWAVE=m CONFIG_PCMCIA_NETWAVE=m

#           #
# Wireless 802.11 Frequency Hopping cards support # Wireless 802.11 Frequency Hopping cards support
#           #
# CONFIG_PCMCIA_RAYCS is not set # CONFIG_PCMCIA_RAYCS is not set

#           #
# Wireless 802.11b ISA/PCI cards support # Wireless 802.11b ISA/PCI cards support
#           #
CONFIG_IPW2100=m        CONFIG_IPW2100=m
CONFIG_IPW2100_MONITOR=y CONFIG_IPW2100_MONITOR=y
# CONFIG_IPW2100_DEBUG is not set # CONFIG_IPW2100_DEBUG is not set
CONFIG_IPW2200=m        CONFIG_IPW2200=m
CONFIG_IPW2200_MONITOR=y CONFIG_IPW2200_MONITOR=y
CONFIG_IPW2200_RADIOTAP=y CONFIG_IPW2200_RADIOTAP=y
CONFIG_IPW2200_PROMISCUOUS=y CONFIG_IPW2200_PROMISCUOUS=y
CONFIG_IPW2200_QOS=y    CONFIG_IPW2200_QOS=y
# CONFIG_IPW2200_DEBUG is not set # CONFIG_IPW2200_DEBUG is not set
CONFIG_AIRO=m          CONFIG_AIRO=m
CONFIG_HERMES=m        CONFIG_HERMES=m
CONFIG_PLX_HERMES=m    CONFIG_PLX_HERMES=m
CONFIG_TMD_HERMES=m    CONFIG_TMD_HERMES=m
CONFIG_NORTEL_HERMES=m CONFIG_NORTEL_HERMES=m
CONFIG_PCI_HERMES=m    CONFIG_PCI_HERMES=m
CONFIG_ATMEL=m         CONFIG_ATMEL=m
CONFIG_PCI_ATMEL=m     CONFIG_PCI_ATMEL=m

#           #
# Wireless 802.11b Pcmcia/Cardbus cards support # Wireless 802.11b Pcmcia/Cardbus cards support
#           #
CONFIG_PCMCIA_HERMES=m CONFIG_PCMCIA_HERMES=m
CONFIG_PCMCIA_SPECTRUM=m CONFIG_PCMCIA_SPECTRUM=m
CONFIG_AIRO_CS=m       CONFIG_AIRO_CS=m
CONFIG_PCMCIA_ATMEL=m  CONFIG_PCMCIA_ATMEL=m
CONFIG_PCMCIA_WL3501=m CONFIG_PCMCIA_WL3501=m

#           #
# Prism GT/Duette 802.11(a/b/g) PCI/Cardbus support # Prism GT/Duette 802.11(a/b/g) PCI/Cardbus support
#           #
CONFIG_PRISM54=m        CONFIG_PRISM54=m
CONFIG_USB_ZD1201=m     CONFIG_USB_ZD1201=m
CONFIG_HOSTAP=m         CONFIG_HOSTAP=m
CONFIG_HOSTAP_FIRMWARE=y CONFIG_HOSTAP_FIRMWARE=y
CONFIG_HOSTAP_FIRMWARE_NVRAM=y CONFIG_HOSTAP_FIRMWARE_NVRAM=y
CONFIG_HOSTAP_PLX=m     CONFIG_HOSTAP_PLX=m
CONFIG_HOSTAP_PCI=m     CONFIG_HOSTAP_PCI=m
CONFIG_HOSTAP_CS=m      CONFIG_HOSTAP_CS=m
CONFIG_BCM43XX=m        CONFIG_BCM43XX=m
CONFIG_BCM43XX_DEBUG=y  CONFIG_BCM43XX_DEBUG=y
CONFIG_BCM43XX_DMA=y    CONFIG_BCM43XX_DMA=y
CONFIG_BCM43XX_PIO=y    CONFIG_BCM43XX_PIO=y
CONFIG_BCM43XX_DMA_AND_PIO_MODE=y CONFIG_BCM43XX_DMA_AND_PIO_MODE=y
# CONFIG_BCM43XX_DMA_MODE is not set # CONFIG_BCM43XX_DMA_MODE is not set
# CONFIG_BCM43XX_PIO_MODE is not set # CONFIG_BCM43XX_PIO_MODE is not set

```

```

CONFIG_ZD1211RW=m          CONFIG_ZD1211RW=m
# CONFIG_ZD1211RW_DEBUG is not set  # CONFIG_ZD1211RW_DEBUG is not set
CONFIG_NET_WIRELESS=y      CONFIG_NET_WIRELESS=y

#          #
# PCMCIA network device support      # PCMCIA network device support
#          #
CONFIG_NET_PCMCIA=y        CONFIG_NET_PCMCIA=y
CONFIG_PCMCIA_3C589=m      CONFIG_PCMCIA_3C589=m
CONFIG_PCMCIA_3C574=m      CONFIG_PCMCIA_3C574=m
CONFIG_PCMCIA_FMVJ18X=m    CONFIG_PCMCIA_FMVJ18X=m
CONFIG_PCMCIA_PCNET=m      CONFIG_PCMCIA_PCNET=m
CONFIG_PCMCIA_NMCLAN=m     CONFIG_PCMCIA_NMCLAN=m
CONFIG_PCMCIA_SMC91C92=m   CONFIG_PCMCIA_SMC91C92=m
CONFIG_PCMCIA_XIRC2PS=m    CONFIG_PCMCIA_XIRC2PS=m
CONFIG_PCMCIA_AXNET=m      CONFIG_PCMCIA_AXNET=m
CONFIG_PCMCIA_IBMTR=m      CONFIG_PCMCIA_IBMTR=m

#          #
# Wan interfaces                # Wan interfaces
#          #
# CONFIG_WAN is not set          # CONFIG_WAN is not set

#          #
# ATM drivers                    # ATM drivers
#          #
# CONFIG_ATM_DUMMY is not set     # CONFIG_ATM_DUMMY is not set
CONFIG_ATM_TCP=m           CONFIG_ATM_TCP=m
CONFIG_ATM_LANAI=m         CONFIG_ATM_LANAI=m
CONFIG_ATM_ENI=m           CONFIG_ATM_ENI=m
# CONFIG_ATM_ENI_DEBUG is not set # CONFIG_ATM_ENI_DEBUG is not set
# CONFIG_ATM_ENI_TUNE_BURST is not set # CONFIG_ATM_ENI_TUNE_BURST is not set
CONFIG_ATM_FIRESTREAM=m    CONFIG_ATM_FIRESTREAM=m
# CONFIG_ATM_ZATM is not set      | CONFIG_ATM_ZATM=m
> # CONFIG_ATM_ZATM_DEBUG is not set
CONFIG_ATM_NICSTAR=m       CONFIG_ATM_NICSTAR=m
# CONFIG_ATM_NICSTAR_USE_SUNI is not set # CONFIG_ATM_NICSTAR_USE_SUNI is not set
# CONFIG_ATM_NICSTAR_USE_IDT77105 is not set # CONFIG_ATM_NICSTAR_USE_IDT77105 is not set
CONFIG_ATM_IDT77252=m      CONFIG_ATM_IDT77252=m
# CONFIG_ATM_IDT77252_DEBUG is not set # CONFIG_ATM_IDT77252_DEBUG is not set
# CONFIG_ATM_IDT77252_RCV_ALL is not set # CONFIG_ATM_IDT77252_RCV_ALL is not set
CONFIG_ATM_IDT77252_USE_SUNI=y CONFIG_ATM_IDT77252_USE_SUNI=y
CONFIG_ATM_AMBASSADOR=m    CONFIG_ATM_AMBASSADOR=m
# CONFIG_ATM_AMBASSADOR_DEBUG is not set # CONFIG_ATM_AMBASSADOR_DEBUG is not set
CONFIG_ATM_HORIZON=m       CONFIG_ATM_HORIZON=m
# CONFIG_ATM_HORIZON_DEBUG is not set # CONFIG_ATM_HORIZON_DEBUG is not set
# CONFIG_ATM_IA is not set        | CONFIG_ATM_IA=m
> # CONFIG_ATM_IA_DEBUG is not set
CONFIG_ATM_FORE200E_MAYBE=m CONFIG_ATM_FORE200E_MAYBE=m
# CONFIG_ATM_FORE200E_PCA is not set # CONFIG_ATM_FORE200E_PCA is not set
CONFIG_ATM_HE=m            CONFIG_ATM_HE=m
# CONFIG_ATM_HE_USE_SUNI is not set # CONFIG_ATM_HE_USE_SUNI is not set
CONFIG_FDDI=y              CONFIG_FDDI=y
# CONFIG_DEFXX is not set         | CONFIG_DEFXX=m
# CONFIG_SKFP is not set          | CONFIG_SKFP=m
# CONFIG_HIPPI is not set         # CONFIG_HIPPI is not set
# CONFIG_PLIP is not set          # CONFIG_PLIP is not set
CONFIG_PPP=m               CONFIG_PPP=m
CONFIG_PPP_MULTILINK=y     CONFIG_PPP_MULTILINK=y
CONFIG_PPP_FILTER=y        CONFIG_PPP_FILTER=y
CONFIG_PPP_ASYNC=m         CONFIG_PPP_ASYNC=m
CONFIG_PPP_SYNC_TTY=m      CONFIG_PPP_SYNC_TTY=m
CONFIG_PPP_DEFLATE=m       CONFIG_PPP_DEFLATE=m
# CONFIG_PPP_BSDCOMP is not set # CONFIG_PPP_BSDCOMP is not set
CONFIG_PPP_MPPE=m          CONFIG_PPP_MPPE=m
CONFIG_PPPOE=m             CONFIG_PPPOE=m
CONFIG_PPPOATM=m           CONFIG_PPPOATM=m
CONFIG_SLIP=m              CONFIG_SLIP=m
CONFIG_SLIP_COMPRESSED=y   CONFIG_SLIP_COMPRESSED=y
CONFIG_SLIP_SMART=y        CONFIG_SLIP_SMART=y
# CONFIG_SLIP_MODE_SLIP6 is not set # CONFIG_SLIP_MODE_SLIP6 is not set
CONFIG_NET_FC=y            CONFIG_NET_FC=y
# CONFIG_SHAPER is not set        | CONFIG_SHAPER=m
CONFIG_NETCONSOLE=m        CONFIG_NETCONSOLE=m
CONFIG_NETPOLL=y           CONFIG_NETPOLL=y
# CONFIG_NETPOLL_RX is not set # CONFIG_NETPOLL_RX is not set
CONFIG_NETPOLL_TRAP=y      CONFIG_NETPOLL_TRAP=y
CONFIG_NET_POLL_CONTROLLER=y CONFIG_NET_POLL_CONTROLLER=y

```

```

# #
# ISDN subsystem # ISDN subsystem
# #
CONFIG_ISDN=m CONFIG_ISDN=m

# #
# Old ISDN4Linux # Old ISDN4Linux
# #
CONFIG_ISDN_I4L=m CONFIG_ISDN_I4L=m
CONFIG_ISDN_PPP=y CONFIG_ISDN_PPP=y
CONFIG_ISDN_PPP_VJ=y CONFIG_ISDN_PPP_VJ=y
CONFIG_ISDN_MPP=y CONFIG_ISDN_MPP=y
CONFIG_IPPP_FILTER=y CONFIG_IPPP_FILTER=y
# CONFIG_ISDN_PPP_BSDCOMP is not set # CONFIG_ISDN_PPP_BSDCOMP is not set
CONFIG_ISDN_AUDIO=y CONFIG_ISDN_AUDIO=y
CONFIG_ISDN_TTY_FAX=y CONFIG_ISDN_TTY_FAX=y

# #
# ISDN feature submodules # ISDN feature submodules
# #
CONFIG_ISDN_DIVERSION=m CONFIG_ISDN_DIVERSION=m

# #
# ISDN4Linux hardware drivers # ISDN4Linux hardware drivers
# #

# #
# Passive cards # Passive cards
# #
CONFIG_ISDN_DRV_HISAX=m CONFIG_ISDN_DRV_HISAX=m

# #
# D-channel protocol features # D-channel protocol features
# #
CONFIG_HISAX_EURO=y CONFIG_HISAX_EURO=y
CONFIG_DE_AOC=y CONFIG_DE_AOC=y
CONFIG_HISAX_NO_SENDCOMPLETE=y CONFIG_HISAX_NO_SENDCOMPLETE=y
CONFIG_HISAX_NO_LLC=y CONFIG_HISAX_NO_LLC=y
CONFIG_HISAX_NO_KEYPAD=y CONFIG_HISAX_NO_KEYPAD=y
CONFIG_HISAX_1TR6=y CONFIG_HISAX_1TR6=y
CONFIG_HISAX_NI1=y CONFIG_HISAX_NI1=y
CONFIG_HISAX_MAX_CARDS=8 CONFIG_HISAX_MAX_CARDS=8

# #
# HiSax supported cards # HiSax supported cards
# #
CONFIG_HISAX_16_3=y CONFIG_HISAX_16_3=y
CONFIG_HISAX_TELESPCI=y CONFIG_HISAX_TELESPCI=y
CONFIG_HISAX_S0BOX=y CONFIG_HISAX_S0BOX=y
CONFIG_HISAX_FRITZPCI=y CONFIG_HISAX_FRITZPCI=y
CONFIG_HISAX_AVM_A1_PCMCIA=y CONFIG_HISAX_AVM_A1_PCMCIA=y
CONFIG_HISAX_ELSA=y CONFIG_HISAX_ELSA=y
CONFIG_HISAX_DIEHLDIVA=y CONFIG_HISAX_DIEHLDIVA=y
CONFIG_HISAX_SEDLBAUER=y CONFIG_HISAX_SEDLBAUER=y
CONFIG_HISAX_NETJET=y CONFIG_HISAX_NETJET=y
CONFIG_HISAX_NETJET_U=y CONFIG_HISAX_NETJET_U=y
CONFIG_HISAX_NICCY=y CONFIG_HISAX_NICCY=y
CONFIG_HISAX_BKM_A4T=y CONFIG_HISAX_BKM_A4T=y
CONFIG_HISAX_SCT_QUADRO=y CONFIG_HISAX_SCT_QUADRO=y
CONFIG_HISAX_GAZEL=y CONFIG_HISAX_GAZEL=y
CONFIG_HISAX_HFC_PCI=y CONFIG_HISAX_HFC_PCI=y
CONFIG_HISAX_W6692=y CONFIG_HISAX_W6692=y
CONFIG_HISAX_HFC_SX=y CONFIG_HISAX_HFC_SX=y
CONFIG_HISAX_ENTERNOW_PCI=y CONFIG_HISAX_ENTERNOW_PCI=y
# CONFIG_HISAX_DEBUG is not set # CONFIG_HISAX_DEBUG is not set

# #
# HiSax PCMCIA card service modules # HiSax PCMCIA card service modules
# #
CONFIG_HISAX_SEDLBAUER_CS=m CONFIG_HISAX_SEDLBAUER_CS=m
CONFIG_HISAX_ELSA_CS=m CONFIG_HISAX_ELSA_CS=m
CONFIG_HISAX_AVM_A1_CS=m CONFIG_HISAX_AVM_A1_CS=m
CONFIG_HISAX_TELES_CS=m CONFIG_HISAX_TELES_CS=m

# #
# HiSax sub driver modules # HiSax sub driver modules
# #
CONFIG_HISAX_ST5481=m CONFIG_HISAX_ST5481=m
# CONFIG_HISAX_HFCUSB is not set # CONFIG_HISAX_HFCUSB is not set

```

```

CONFIG_HISAX_HFC4S8S=m          CONFIG_HISAX_HFC4S8S=m
CONFIG_HISAX_FRITZ_PCIPNP=m     CONFIG_HISAX_FRITZ_PCIPNP=m
CONFIG_HISAX_HDLC=y            CONFIG_HISAX_HDLC=y

# #
# Active cards # Active cards
# #

# #
# Siemens Gigaset # Siemens Gigaset
# #
CONFIG_ISDN_DRV_GIGASET=m      CONFIG_ISDN_DRV_GIGASET=m
CONFIG_GIGASET_BASE=m        CONFIG_GIGASET_BASE=m
CONFIG_GIGASET_M105=m        CONFIG_GIGASET_M105=m
# CONFIG_GIGASET_DEBUG is not set # CONFIG_GIGASET_DEBUG is not set
# CONFIG_GIGASET_UNDOCREQ is not set # CONFIG_GIGASET_UNDOCREQ is not set

# #
# CAPI subsystem # CAPI subsystem
# #
CONFIG_ISDN_CAPI=m           CONFIG_ISDN_CAPI=m
CONFIG_ISDN_DRV_AVMB1_VERBOSE_REASON=y CONFIG_ISDN_DRV_AVMB1_VERBOSE_REASON=y
CONFIG_ISDN_CAPI_MIDDLEWARE=y CONFIG_ISDN_CAPI_MIDDLEWARE=y
CONFIG_ISDN_CAPI_CAPI20=m    CONFIG_ISDN_CAPI_CAPI20=m
CONFIG_ISDN_CAPI_CAPIFS_BOOL=y CONFIG_ISDN_CAPI_CAPIFS_BOOL=y
CONFIG_ISDN_CAPI_CAPIFS=m    CONFIG_ISDN_CAPI_CAPIFS=m
CONFIG_ISDN_CAPI_CAPIDRV=m   CONFIG_ISDN_CAPI_CAPIDRV=m

# #
# CAPI hardware drivers # CAPI hardware drivers
# #

# #
# Active AVM cards # Active AVM cards
# #
CONFIG_CAPI_AVM=y           CONFIG_CAPI_AVM=y
CONFIG_ISDN_DRV_AVMB1_B1PCI=m CONFIG_ISDN_DRV_AVMB1_B1PCI=m
CONFIG_ISDN_DRV_AVMB1_B1PCIV4=y CONFIG_ISDN_DRV_AVMB1_B1PCIV4=y
CONFIG_ISDN_DRV_AVMB1_B1PCMCIAM CONFIG_ISDN_DRV_AVMB1_B1PCMCIAM
CONFIG_ISDN_DRV_AVMB1_AVM_CS=m CONFIG_ISDN_DRV_AVMB1_AVM_CS=m
CONFIG_ISDN_DRV_AVMB1_T1PCI=m CONFIG_ISDN_DRV_AVMB1_T1PCI=m
CONFIG_ISDN_DRV_AVMB1_C4=m   CONFIG_ISDN_DRV_AVMB1_C4=m

# #
# Active Eicon DIVA Server cards # Active Eicon DIVA Server cards
# #
CONFIG_CAPI_EICON=y         CONFIG_CAPI_EICON=y
CONFIG_ISDN_DIVAS=m        CONFIG_ISDN_DIVAS=m
CONFIG_ISDN_DIVAS_BRIPCI=y CONFIG_ISDN_DIVAS_BRIPCI=y
CONFIG_ISDN_DIVAS_PRIIPCI=y CONFIG_ISDN_DIVAS_PRIIPCI=y
CONFIG_ISDN_DIVAS_DIVACAPI=m CONFIG_ISDN_DIVAS_DIVACAPI=m
CONFIG_ISDN_DIVAS_USERIDI=m CONFIG_ISDN_DIVAS_USERIDI=m
CONFIG_ISDN_DIVAS_MAINT=m   CONFIG_ISDN_DIVAS_MAINT=m

# #
# Telephony Support # Telephony Support
# #
# CONFIG_PHONE is not set # CONFIG_PHONE is not set

# #
# Input device support # Input device support
# #
CONFIG_INPUT=y             CONFIG_INPUT=y

# #
# Userland interfaces # Userland interfaces
# #
CONFIG_INPUT_MOUSEDEV=y    CONFIG_INPUT_MOUSEDEV=y
# CONFIG_INPUT_MOUSEDEV_PSAUX is not set # CONFIG_INPUT_MOUSEDEV_PSAUX is not set
CONFIG_INPUT_MOUSEDEV_SCREEN_X=1024 CONFIG_INPUT_MOUSEDEV_SCREEN_X=1024
CONFIG_INPUT_MOUSEDEV_SCREEN_Y=768 CONFIG_INPUT_MOUSEDEV_SCREEN_Y=768
CONFIG_INPUT_JOYDEV=m     CONFIG_INPUT_JOYDEV=m
# CONFIG_INPUT_TSDEV is not set # CONFIG_INPUT_TSDEV is not set
CONFIG_INPUT_EVDEV=y      CONFIG_INPUT_EVDEV=y
# CONFIG_INPUT_EVBUG is not set # CONFIG_INPUT_EVBUG is not set

# #
# Input Device Drivers # Input Device Drivers
# #

```

```

CONFIG_INPUT_KEYBOARD=y          CONFIG_INPUT_KEYBOARD=y
CONFIG_KEYBOARD_ATKBD=y          CONFIG_KEYBOARD_ATKBD=y
# CONFIG_KEYBOARD_SUNKBD is not set # CONFIG_KEYBOARD_SUNKBD is not set
# CONFIG_KEYBOARD_LKKBD is not set # CONFIG_KEYBOARD_LKKBD is not set
# CONFIG_KEYBOARD_XTKBD is not set # CONFIG_KEYBOARD_XTKBD is not set
# CONFIG_KEYBOARD_NEWTON is not set # CONFIG_KEYBOARD_NEWTON is not set
CONFIG_INPUT_MOUSE=y            CONFIG_INPUT_MOUSE=y
CONFIG_MOUSE_PS2=y              CONFIG_MOUSE_PS2=y
CONFIG_MOUSE_SERIAL=m           CONFIG_MOUSE_SERIAL=m
CONFIG_MOUSE_VSXXXAA=m          CONFIG_MOUSE_VSXXXAA=m
CONFIG_INPUT_JOYSTICK=y         CONFIG_INPUT_JOYSTICK=y
# CONFIG_JOYSTICK_ANALOG is not set # CONFIG_JOYSTICK_ANALOG is not set
# CONFIG_JOYSTICK_A3D is not set # CONFIG_JOYSTICK_A3D is not set
# CONFIG_JOYSTICK_ADI is not set # CONFIG_JOYSTICK_ADI is not set
# CONFIG_JOYSTICK_COBRA is not set # CONFIG_JOYSTICK_COBRA is not set
# CONFIG_JOYSTICK_GF2K is not set # CONFIG_JOYSTICK_GF2K is not set
# CONFIG_JOYSTICK_GRIP is not set # CONFIG_JOYSTICK_GRIP is not set
# CONFIG_JOYSTICK_GRIP_MP is not set # CONFIG_JOYSTICK_GRIP_MP is not set
# CONFIG_JOYSTICK_GUILLEMOT is not set # CONFIG_JOYSTICK_GUILLEMOT is not set
# CONFIG_JOYSTICK_INTERACT is not set # CONFIG_JOYSTICK_INTERACT is not set
# CONFIG_JOYSTICK_SIDEWINDER is not set # CONFIG_JOYSTICK_SIDEWINDER is not set
# CONFIG_JOYSTICK_TMDC is not set # CONFIG_JOYSTICK_TMDC is not set
# CONFIG_JOYSTICK_IFORCE is not set # CONFIG_JOYSTICK_IFORCE is not set
# CONFIG_JOYSTICK_WARRIOR is not set # CONFIG_JOYSTICK_WARRIOR is not set
# CONFIG_JOYSTICK_MAGELLAN is not set # CONFIG_JOYSTICK_MAGELLAN is not set
# CONFIG_JOYSTICK_SPACEORB is not set # CONFIG_JOYSTICK_SPACEORB is not set
# CONFIG_JOYSTICK_SPACEBALL is not set # CONFIG_JOYSTICK_SPACEBALL is not set
# CONFIG_JOYSTICK_STINGER is not set # CONFIG_JOYSTICK_STINGER is not set
CONFIG_JOYSTICK_TWIDJOY=m       CONFIG_JOYSTICK_TWIDJOY=m
# CONFIG_JOYSTICK_DB9 is not set # CONFIG_JOYSTICK_DB9 is not set
# CONFIG_JOYSTICK_GAMECON is not set # CONFIG_JOYSTICK_GAMECON is not set
# CONFIG_JOYSTICK_TURBOGRAFX is not set # CONFIG_JOYSTICK_TURBOGRAFX is not set
CONFIG_JOYSTICK_JOYDUMP=m       CONFIG_JOYSTICK_JOYDUMP=m
CONFIG_INPUT_TOUCHSCREEN=y       CONFIG_INPUT_TOUCHSCREEN=y
CONFIG_TOUCHSCREEN_GUNZE=m       CONFIG_TOUCHSCREEN_GUNZE=m
CONFIG_TOUCHSCREEN_ELO=m         CONFIG_TOUCHSCREEN_ELO=m
CONFIG_TOUCHSCREEN_MTOUCH=m      CONFIG_TOUCHSCREEN_MTOUCH=m
CONFIG_TOUCHSCREEN_MK712=m       CONFIG_TOUCHSCREEN_MK712=m
CONFIG_INPUT_MISC=y             CONFIG_INPUT_MISC=y
CONFIG_INPUT_PCSPKR=m           CONFIG_INPUT_PCSPKR=m
CONFIG_INPUT_WISTRON_BTNS=m     CONFIG_INPUT_WISTRON_BTNS=m
CONFIG_INPUT_UINPUT=m           CONFIG_INPUT_UINPUT=m

# #
# Hardware I/O ports # Hardware I/O ports
# #
CONFIG_SERIO=y                  CONFIG_SERIO=y
CONFIG_SERIO_I8042=y            CONFIG_SERIO_I8042=y
CONFIG_SERIO_SERPORT=y         CONFIG_SERIO_SERPORT=y
# CONFIG_SERIO_CT82C710 is not set # CONFIG_SERIO_CT82C710 is not set
# CONFIG_SERIO_PARKBD is not set # CONFIG_SERIO_PARKBD is not set
# CONFIG_SERIO_PCIPS2 is not set # CONFIG_SERIO_PCIPS2 is not set
CONFIG_SERIO_LIBPS2=y          CONFIG_SERIO_LIBPS2=y
CONFIG_SERIO_RAW=m             CONFIG_SERIO_RAW=m
CONFIG_GAMEPORT=m              CONFIG_GAMEPORT=m
CONFIG_GAMEPORT_NS558=m        CONFIG_GAMEPORT_NS558=m
CONFIG_GAMEPORT_L4=m           CONFIG_GAMEPORT_L4=m
CONFIG_GAMEPORT_EMU10K1=m      CONFIG_GAMEPORT_EMU10K1=m
CONFIG_GAMEPORT_FM801=m        CONFIG_GAMEPORT_FM801=m

# #
# Character devices # Character devices
# #
CONFIG_VT=y                     CONFIG_VT=y
CONFIG_VT_CONSOLE=y            CONFIG_VT_CONSOLE=y
CONFIG_HW_CONSOLE=y            CONFIG_HW_CONSOLE=y
CONFIG_VT_HW_CONSOLE_BINDING=y CONFIG_VT_HW_CONSOLE_BINDING=y
CONFIG_SERIAL_NONSTANDARD=y     CONFIG_SERIAL_NONSTANDARD=y
# CONFIG_COMPUTONE is not set # CONFIG_COMPUTONE is not set
# CONFIG_ROCKETPORT is not set # CONFIG_ROCKETPORT is not set
CONFIG_CYCLADES=m              CONFIG_CYCLADES=m
# CONFIG_CYZ_INTR is not set # CONFIG_CYZ_INTR is not set
# CONFIG_DIGIEPCA is not set # CONFIG_DIGIEPCA is not set
# CONFIG_MOXA_INTELLIO is not set # CONFIG_MOXA_INTELLIO is not set
# CONFIG_MOXA_SMARTIO is not set # CONFIG_MOXA_SMARTIO is not set
# CONFIG_ISI is not set # CONFIG_ISI is not set
CONFIG_SYNCLINK=m              CONFIG_SYNCLINK=m
CONFIG_SYNCLINKMP=m            CONFIG_SYNCLINKMP=m
CONFIG_SYNCLINK_GT=m           CONFIG_SYNCLINK_GT=m

```

```

CONFIG_N_HDLC=m          CONFIG_N_HDLC=m
# CONFIG_SPECIALIX is not set      # CONFIG_SPECIALIX is not set
# CONFIG_SX is not set             # CONFIG_SX is not set
# CONFIG_RIO is not set            # CONFIG_RIO is not set
# CONFIG_STALDRV is not set        # CONFIG_STALDRV is not set

#
#
# Serial drivers                # Serial drivers
#
CONFIG_SERIAL_8250=y          CONFIG_SERIAL_8250=y
CONFIG_SERIAL_8250_CONSOLE=y    CONFIG_SERIAL_8250_CONSOLE=y
CONFIG_SERIAL_8250_PCI=y        CONFIG_SERIAL_8250_PCI=y
CONFIG_SERIAL_8250_PNP=y        CONFIG_SERIAL_8250_PNP=y
CONFIG_SERIAL_8250_CS=m         CONFIG_SERIAL_8250_CS=m
CONFIG_SERIAL_8250_NR_UARTS=32  CONFIG_SERIAL_8250_NR_UARTS=32
CONFIG_SERIAL_8250_RUNTIME_UARTS=4  CONFIG_SERIAL_8250_RUNTIME_UARTS=4
CONFIG_SERIAL_8250_EXTENDED=y    CONFIG_SERIAL_8250_EXTENDED=y
CONFIG_SERIAL_8250_MANY_PORTS=y  CONFIG_SERIAL_8250_MANY_PORTS=y
CONFIG_SERIAL_8250_SHARE_IRQ=y    CONFIG_SERIAL_8250_SHARE_IRQ=y
CONFIG_SERIAL_8250_DETECT_IRQ=y   CONFIG_SERIAL_8250_DETECT_IRQ=y
CONFIG_SERIAL_8250_RSA=y         CONFIG_SERIAL_8250_RSA=y

#
#
# Non-8250 serial port support    # Non-8250 serial port support
#
CONFIG_SERIAL_CORE=y          CONFIG_SERIAL_CORE=y
CONFIG_SERIAL_CORE_CONSOLE=y    CONFIG_SERIAL_CORE_CONSOLE=y
CONFIG_SERIAL_JSM=m           CONFIG_SERIAL_JSM=m
CONFIG_UNIX98_PTYS=y          CONFIG_UNIX98_PTYS=y
# CONFIG_LEGACY_PTYS is not set    # CONFIG_LEGACY_PTYS is not set
CONFIG_CRASH=m                CONFIG_CRASH=m
CONFIG_PRINTER=m              CONFIG_PRINTER=m
CONFIG_LP_CONSOLE=y           CONFIG_LP_CONSOLE=y
CONFIG_PPDEV=m                CONFIG_PPDEV=m
# CONFIG_TIPAR is not set          # CONFIG_TIPAR is not set

#
#
# IPMI                            # IPMI
#
CONFIG_IPMI_HANDLER=m          CONFIG_IPMI_HANDLER=m
# CONFIG_IPMI_PANIC_EVENT is not set  # CONFIG_IPMI_PANIC_EVENT is not set
CONFIG_IPMI_DEVICE_INTERFACE=m  CONFIG_IPMI_DEVICE_INTERFACE=m
CONFIG_IPMI_SI=m              CONFIG_IPMI_SI=m
CONFIG_IPMI_WATCHDOG=m         CONFIG_IPMI_WATCHDOG=m
CONFIG_IPMI_POWEROFF=m         CONFIG_IPMI_POWEROFF=m

#
#
# Watchdog Cards                    # Watchdog Cards
#
CONFIG_WATCHDOG=y             CONFIG_WATCHDOG=y
# CONFIG_WATCHDOG_NOWAYOUT is not set  # CONFIG_WATCHDOG_NOWAYOUT is not set

#
#
# Watchdog Device Drivers            # Watchdog Device Drivers
#
CONFIG_SOFT_WATCHDOG=m         CONFIG_SOFT_WATCHDOG=m
# CONFIG_ACQUIRE_WDT is not set      # CONFIG_ACQUIRE_WDT is not set
# CONFIG_ADVANTECH_WDT is not set     # CONFIG_ADVANTECH_WDT is not set
CONFIG_ALIM1535_WDT=m          CONFIG_ALIM1535_WDT=m
CONFIG_ALIM7101_WDT=m          CONFIG_ALIM7101_WDT=m
# CONFIG_SC520_WDT is not set          # CONFIG_SC520_WDT is not set
# CONFIG_EUROTECH_WDT is not set      # CONFIG_EUROTECH_WDT is not set
# CONFIG_IB700_WDT is not set          # CONFIG_IB700_WDT is not set
CONFIG_IBMASR=m                CONFIG_IBMASR=m
# CONFIG_WAFER_WDT is not set          # CONFIG_WAFER_WDT is not set
CONFIG_I6300ESB_WDT=m          CONFIG_I6300ESB_WDT=m
CONFIG_I8XX_TCO=m              CONFIG_I8XX_TCO=m
# CONFIG_SC1200_WDT is not set          # CONFIG_SC1200_WDT is not set
# CONFIG_60XX_WDT is not set           # CONFIG_60XX_WDT is not set
# CONFIG_SBC8360_WDT is not set        # CONFIG_SBC8360_WDT is not set
# CONFIG_CPU5_WDT is not set           # CONFIG_CPU5_WDT is not set
CONFIG_W83627HF_WDT=m          CONFIG_W83627HF_WDT=m
CONFIG_W83877F_WDT=m           CONFIG_W83877F_WDT=m
CONFIG_W83977F_WDT=m           CONFIG_W83977F_WDT=m
CONFIG_MACHZ_WDT=m             CONFIG_MACHZ_WDT=m
# CONFIG_SBC_EPX_C3_WATCHDOG is not set  # CONFIG_SBC_EPX_C3_WATCHDOG is not set

#
#
# PCI-based Watchdog Cards            # PCI-based Watchdog Cards

```

```

# #
CONFIG_PCIPCWATCHDOG=m CONFIG_PCIPCWATCHDOG=m
CONFIG_WDTPCI=m CONFIG_WDTPCI=m
CONFIG_WDT_501_PCI=y CONFIG_WDT_501_PCI=y

# #
# USB-based Watchdog Cards # USB-based Watchdog Cards
# #
CONFIG_USBPCWATCHDOG=m CONFIG_USBPCWATCHDOG=m
CONFIG_HW_RANDOM=y CONFIG_HW_RANDOM=y
CONFIG_HW_RANDOM_INTEL=m CONFIG_HW_RANDOM_INTEL=m
CONFIG_HW_RANDOM_AMD=m CONFIG_HW_RANDOM_AMD=m
CONFIG_HW_RANDOM_GEODE=m CONFIG_HW_RANDOM_GEODE=m
CONFIG_HW_RANDOM_VIA=m CONFIG_HW_RANDOM_VIA=m
CONFIG_NVRAM=y CONFIG_NVRAM=y
CONFIG_RTC=y CONFIG_RTC=y
CONFIG_DTLK=m CONFIG_DTLK=m
# CONFIG_R3964 is not set # CONFIG_R3964 is not set
# CONFIG_APPLICOM is not set # CONFIG_APPLICOM is not set
CONFIG_SONYPI=m CONFIG_SONYPI=m

# #
# Ftape, the floppy tape device driver # Ftape, the floppy tape device driver
# #
CONFIG_AGP=y CONFIG_AGP=y
CONFIG_AGP_ALI=y CONFIG_AGP_ALI=y
CONFIG_AGP_ATI=y CONFIG_AGP_ATI=y
CONFIG_AGP_AMD=y CONFIG_AGP_AMD=y
CONFIG_AGP_AMD64=y CONFIG_AGP_AMD64=y
CONFIG_AGP_INTEL=y CONFIG_AGP_INTEL=y
CONFIG_AGP_NVIDIA=y CONFIG_AGP_NVIDIA=y
CONFIG_AGP_SIS=y CONFIG_AGP_SIS=y
CONFIG_AGP_SWORKS=y CONFIG_AGP_SWORKS=y
CONFIG_AGP_VIA=y CONFIG_AGP_VIA=y
CONFIG_AGP_EFFICEON=y CONFIG_AGP_EFFICEON=y
CONFIG_DRM=m CONFIG_DRM=m
# CONFIG_DRM_TDFX is not set # CONFIG_DRM_TDFX is not set
CONFIG_DRM_R128=m CONFIG_DRM_R128=m
CONFIG_DRM_RADEON=m CONFIG_DRM_RADEON=m
CONFIG_DRM_I810=m CONFIG_DRM_I810=m
CONFIG_DRM_I830=m CONFIG_DRM_I830=m
CONFIG_DRM_I915=m CONFIG_DRM_I915=m
CONFIG_DRM_MGA=m CONFIG_DRM_MGA=m
# CONFIG_DRM_SIS is not set # CONFIG_DRM_SIS is not set
CONFIG_DRM_VIA=m CONFIG_DRM_VIA=m
CONFIG_DRM_SAVAGE=m CONFIG_DRM_SAVAGE=m

# #
# PCMCIA character devices # PCMCIA character devices
# #
# CONFIG_SYNCLINK_CS is not set # CONFIG_SYNCLINK_CS is not set
CONFIG_CARDMAN_4000=m CONFIG_CARDMAN_4000=m
CONFIG_CARDMAN_4040=m CONFIG_CARDMAN_4040=m
# CONFIG_MWAVE is not set # CONFIG_MWAVE is not set
CONFIG_PC8736x_GPIO=m CONFIG_PC8736x_GPIO=m
CONFIG_NSC_GPIO=m CONFIG_NSC_GPIO=m
CONFIG_CS5535_GPIO=m CONFIG_CS5535_GPIO=m
CONFIG_RAW_DRIVER=y CONFIG_RAW_DRIVER=y
CONFIG_MAX_RAW_DEVS=8192 CONFIG_MAX_RAW_DEVS=8192
CONFIG_HPET=y CONFIG_HPET=y
# CONFIG_HPET_RTC_IRQ is not set # CONFIG_HPET_RTC_IRQ is not set
# CONFIG_HPET_MMAP is not set # CONFIG_HPET_MMAP is not set
CONFIG_HANGCHECK_TIMER=m CONFIG_HANGCHECK_TIMER=m

# #
# TPM devices # TPM devices
# #
# CONFIG_TCG_TPM is not set # CONFIG_TCG_TPM is not set
# CONFIG_TELCLOCK is not set # CONFIG_TELCLOCK is not set

# #
# I2C support # I2C support
# #
CONFIG_I2C=m CONFIG_I2C=m
CONFIG_I2C_CHARDEV=m CONFIG_I2C_CHARDEV=m

# #
# I2C Algorithms # I2C Algorithms
# #

```

```

CONFIG_I2C_ALGOBIT=m          CONFIG_I2C_ALGOBIT=m
CONFIG_I2C_ALGOPCF=m         CONFIG_I2C_ALGOPCF=m

CONFIG_I2C_ALGOPCA=m         CONFIG_I2C_ALGOPCA=m

#           #
# I2C Hardware Bus support   # I2C Hardware Bus support
#           #
CONFIG_I2C_ALI1535=m         CONFIG_I2C_ALI1535=m
CONFIG_I2C_ALI1563=m         CONFIG_I2C_ALI1563=m
CONFIG_I2C_ALI15X3=m         CONFIG_I2C_ALI15X3=m
CONFIG_I2C_AMD756=m          CONFIG_I2C_AMD756=m
CONFIG_I2C_AMD756_S4882=m    CONFIG_I2C_AMD756_S4882=m
CONFIG_I2C_AMD8111=m         CONFIG_I2C_AMD8111=m
CONFIG_I2C_I801=m            CONFIG_I2C_I801=m
CONFIG_I2C_I810=m            CONFIG_I2C_I810=m
CONFIG_I2C_PII4=m            CONFIG_I2C_PII4=m
CONFIG_I2C_ISA=m             CONFIG_I2C_ISA=m
CONFIG_I2C_NFORCE2=m         CONFIG_I2C_NFORCE2=m
# CONFIG_I2C_OCORES is not set # CONFIG_I2C_OCORES is not set
CONFIG_I2C_PARPORT=m         CONFIG_I2C_PARPORT=m
CONFIG_I2C_PARPORT_LIGHT=m   CONFIG_I2C_PARPORT_LIGHT=m
CONFIG_I2C_PROSAVAGE=m        CONFIG_I2C_PROSAVAGE=m
CONFIG_I2C_SAVAGE4=m          CONFIG_I2C_SAVAGE4=m
# CONFIG_SCx200_ACB is not set # CONFIG_SCx200_ACB is not set
CONFIG_I2C_SIS5595=m         CONFIG_I2C_SIS5595=m
CONFIG_I2C_SIS630=m          CONFIG_I2C_SIS630=m
CONFIG_I2C_SIS96X=m          CONFIG_I2C_SIS96X=m
CONFIG_I2C_STUB=m            CONFIG_I2C_STUB=m
CONFIG_I2C_VIA=m             CONFIG_I2C_VIA=m
CONFIG_I2C_VIAPRO=m          CONFIG_I2C_VIAPRO=m
CONFIG_I2C_VOODOO3=m         CONFIG_I2C_VOODOO3=m
# CONFIG_I2C_PCA_ISA is not set # CONFIG_I2C_PCA_ISA is not set

#           #
# Miscellaneous I2C Chip support # Miscellaneous I2C Chip support
#           #
CONFIG_SENSORS_DS1337=m       CONFIG_SENSORS_DS1337=m
CONFIG_SENSORS_DS1374=m       CONFIG_SENSORS_DS1374=m
CONFIG_SENSORS_EEPROM=m       CONFIG_SENSORS_EEPROM=m
CONFIG_SENSORS_PCF8574=m      CONFIG_SENSORS_PCF8574=m
CONFIG_SENSORS_PCA9539=m      CONFIG_SENSORS_PCA9539=m
CONFIG_SENSORS_PCF8591=m      CONFIG_SENSORS_PCF8591=m
CONFIG_SENSORS_MAX6875=m      CONFIG_SENSORS_MAX6875=m
# CONFIG_I2C_DEBUG_CORE is not set # CONFIG_I2C_DEBUG_CORE is not set
# CONFIG_I2C_DEBUG_ALGO is not set # CONFIG_I2C_DEBUG_ALGO is not set
# CONFIG_I2C_DEBUG_BUS is not set # CONFIG_I2C_DEBUG_BUS is not set
# CONFIG_I2C_DEBUG_CHIP is not set # CONFIG_I2C_DEBUG_CHIP is not set

#           #
# SPI support                 # SPI support
#           #
# CONFIG_SPI is not set       # CONFIG_SPI is not set
# CONFIG_SPI_MASTER is not set # CONFIG_SPI_MASTER is not set

#           #
# Dallas's 1-wire bus         # Dallas's 1-wire bus
#           #
# CONFIG_W1 is not set        # CONFIG_W1 is not set

#           #
# Hardware Monitoring support  # Hardware Monitoring support
#           #
CONFIG_HWMON=m                CONFIG_HWMON=m
CONFIG_HWMON_VID=m            CONFIG_HWMON_VID=m
CONFIG_SENSORS_ABITUGURU=m    CONFIG_SENSORS_ABITUGURU=m
CONFIG_SENSORS_ADM1021=m       CONFIG_SENSORS_ADM1021=m
CONFIG_SENSORS_ADM1025=m       CONFIG_SENSORS_ADM1025=m
CONFIG_SENSORS_ADM1026=m       CONFIG_SENSORS_ADM1026=m
CONFIG_SENSORS_ADM1031=m       CONFIG_SENSORS_ADM1031=m
CONFIG_SENSORS_ADM9240=m       CONFIG_SENSORS_ADM9240=m
CONFIG_SENSORS_ASB100=m        CONFIG_SENSORS_ASB100=m
CONFIG_SENSORS_ATXP1=m         CONFIG_SENSORS_ATXP1=m
CONFIG_SENSORS_DS1621=m        CONFIG_SENSORS_DS1621=m
CONFIG_SENSORS_F71805F=m       CONFIG_SENSORS_F71805F=m
CONFIG_SENSORS_FSCHER=m        CONFIG_SENSORS_FSCHER=m
CONFIG_SENSORS_FSCPOS=m        CONFIG_SENSORS_FSCPOS=m
CONFIG_SENSORS_GL518SM=m       CONFIG_SENSORS_GL518SM=m
CONFIG_SENSORS_GL520SM=m       CONFIG_SENSORS_GL520SM=m

```

```

CONFIG_SENSORS_IT87=m          CONFIG_SENSORS_IT87=m
CONFIG_SENSORS_LM63=m         CONFIG_SENSORS_LM63=m
CONFIG_SENSORS_LM75=m         CONFIG_SENSORS_LM75=m
CONFIG_SENSORS_LM77=m         CONFIG_SENSORS_LM77=m
CONFIG_SENSORS_LM78=m         CONFIG_SENSORS_LM78=m
CONFIG_SENSORS_LM80=m         CONFIG_SENSORS_LM80=m
CONFIG_SENSORS_LM83=m         CONFIG_SENSORS_LM83=m
CONFIG_SENSORS_LM85=m         CONFIG_SENSORS_LM85=m
CONFIG_SENSORS_LM87=m         CONFIG_SENSORS_LM87=m
CONFIG_SENSORS_LM90=m         CONFIG_SENSORS_LM90=m
CONFIG_SENSORS_LM92=m         CONFIG_SENSORS_LM92=m
CONFIG_SENSORS_MAX1619=m      CONFIG_SENSORS_MAX1619=m
CONFIG_SENSORS_PC87360=m      CONFIG_SENSORS_PC87360=m
CONFIG_SENSORS_SIS5595=m      CONFIG_SENSORS_SIS5595=m
CONFIG_SENSORS_SMSC47M1=m     CONFIG_SENSORS_SMSC47M1=m
CONFIG_SENSORS_SMSC47M192=m   CONFIG_SENSORS_SMSC47M192=m
CONFIG_SENSORS_SMSC47B397=m   CONFIG_SENSORS_SMSC47B397=m
CONFIG_SENSORS_VIA686A=m      CONFIG_SENSORS_VIA686A=m
CONFIG_SENSORS_VT8231=m       CONFIG_SENSORS_VT8231=m
CONFIG_SENSORS_W83781D=m      CONFIG_SENSORS_W83781D=m
CONFIG_SENSORS_W83791D=m      CONFIG_SENSORS_W83791D=m
CONFIG_SENSORS_W83792D=m      CONFIG_SENSORS_W83792D=m
CONFIG_SENSORS_W83L785TS=m    CONFIG_SENSORS_W83L785TS=m
CONFIG_SENSORS_W83627HF=m     CONFIG_SENSORS_W83627HF=m
CONFIG_SENSORS_W83627EHF=m    CONFIG_SENSORS_W83627EHF=m
CONFIG_SENSORS_HDAPS=m        CONFIG_SENSORS_HDAPS=m
# CONFIG_HWMON_DEBUG_CHIP is not set  # CONFIG_HWMON_DEBUG_CHIP is not set

#
# Misc devices                # Misc devices
#
CONFIG_IBM_ASM=m             CONFIG_IBM_ASM=m

#
# Multimedia devices          # Multimedia devices
#
CONFIG_VIDEO_DEV=m          CONFIG_VIDEO_DEV=m
CONFIG_VIDEO_V4L1=y         CONFIG_VIDEO_V4L1=y
CONFIG_VIDEO_V4L1_COMPAT=y  CONFIG_VIDEO_V4L1_COMPAT=y
CONFIG_VIDEO_V4L2=y         CONFIG_VIDEO_V4L2=y

#
# Video Capture Adapters     # Video Capture Adapters
#

#
# Video Capture Adapters     # Video Capture Adapters
#
# CONFIG_VIDEO_ADV_DEBUG is not set  # CONFIG_VIDEO_ADV_DEBUG is not set
# CONFIG_VIDEO_VIVI is not set       | CONFIG_VIDEO_VIVI=m
CONFIG_VIDEO_BT848=m         CONFIG_VIDEO_BT848=m
> # CONFIG_VIDEO_BT848_DVB is not set
CONFIG_VIDEO_SAA6588=m       CONFIG_VIDEO_SAA6588=m
# CONFIG_VIDEO_BWQCAM is not set     | CONFIG_VIDEO_BWQCAM=m
# CONFIG_VIDEO_CQCAM is not set     | CONFIG_VIDEO_CQCAM=m
# CONFIG_VIDEO_W9966 is not set     | CONFIG_VIDEO_W9966=m
# CONFIG_VIDEO_CPIA is not set       | CONFIG_VIDEO_CPIA=m
> CONFIG_VIDEO_CPIA_PP=m
> CONFIG_VIDEO_CPIA_USB=m
CONFIG_VIDEO_CPIA2=m         CONFIG_VIDEO_CPIA2=m
# CONFIG_VIDEO_SAA5246A is not set   | CONFIG_VIDEO_SAA5246A=m
# CONFIG_VIDEO_SAA5249 is not set   | CONFIG_VIDEO_SAA5249=m
# CONFIG_TUNER_3036 is not set       | CONFIG_TUNER_3036=m
# CONFIG_VIDEO_STRADIS is not set   | CONFIG_VIDEO_STRADIS=m
# CONFIG_VIDEO_ZORAN is not set     | CONFIG_VIDEO_ZORAN=m
# CONFIG_VIDEO_MEYE is not set      | CONFIG_VIDEO_ZORAN_BUZ=m
# CONFIG_VIDEO_SAA7134 is not set   | CONFIG_VIDEO_ZORAN_DC10=m
# CONFIG_VIDEO_MXB is not set       | CONFIG_VIDEO_ZORAN_DC30=m
# CONFIG_VIDEO_DPC is not set       | CONFIG_VIDEO_ZORAN_LML33=m
# CONFIG_VIDEO_HEXIUM_ORION is not set | CONFIG_VIDEO_ZORAN_LML33R10=m
# CONFIG_VIDEO_HEXIUM_GEMINI is not set | CONFIG_VIDEO_ZORAN_AV56EYES=m
# CONFIG_VIDEO_CX88 is not set      | CONFIG_VIDEO_MEYE=m
> CONFIG_VIDEO_SAA7134=m
> CONFIG_VIDEO_SAA7134_ALSA=m
> # CONFIG_VIDEO_SAA7134_DVB is not set
> CONFIG_VIDEO_MXB=m
> CONFIG_VIDEO_DPC=m
> CONFIG_VIDEO_HEXIUM_ORION=m
> CONFIG_VIDEO_HEXIUM_GEMINI=m

```

```

> CONFIG_VIDEO_CX88_VP3054=m
> CONFIG_VIDEO_CX88=m
> CONFIG_VIDEO_CX88_ALSA=m
> CONFIG_VIDEO_CX88_BLACKBIRD=m
> CONFIG_VIDEO_CX88_DVB=m
> CONFIG_VIDEO_CX88_DVB_ALL_FRONTENDS=y

# #
# Encoders and Decoders # Encoders and Decoders
# #
CONFIG_VIDEO_MSP3400=m CONFIG_VIDEO_MSP3400=m
CONFIG_VIDEO_CS53L32A=m CONFIG_VIDEO_CS53L32A=m
CONFIG_VIDEO_TLV320AIC23B=m CONFIG_VIDEO_TLV320AIC23B=m
CONFIG_VIDEO_WM8775=m CONFIG_VIDEO_WM8775=m
CONFIG_VIDEO_WM8739=m CONFIG_VIDEO_WM8739=m
CONFIG_VIDEO_CX2341X=m CONFIG_VIDEO_CX2341X=m
CONFIG_VIDEO_CX25840=m CONFIG_VIDEO_CX25840=m
CONFIG_VIDEO_SAA711X=m CONFIG_VIDEO_SAA711X=m
CONFIG_VIDEO_SAA7127=m CONFIG_VIDEO_SAA7127=m
CONFIG_VIDEO_UPD64031A=m CONFIG_VIDEO_UPD64031A=m
CONFIG_VIDEO_UPD64083=m CONFIG_VIDEO_UPD64083=m

# #
# V4L USB devices # V4L USB devices
# #
CONFIG_VIDEO_PVRUSB2=m CONFIG_VIDEO_PVRUSB2=m
CONFIG_VIDEO_PVRUSB2_24XXX=y CONFIG_VIDEO_PVRUSB2_24XXX=y
CONFIG_VIDEO_PVRUSB2_SYSFS=y CONFIG_VIDEO_PVRUSB2_SYSFS=y
# CONFIG_VIDEO_PVRUSB2_DEBUGIFC is not set # CONFIG_VIDEO_PVRUSB2_DEBUGIFC is not set
CONFIG_VIDEO_EM28XX=m CONFIG_VIDEO_EM28XX=m
CONFIG_VIDEO_USBVIDEO=m CONFIG_VIDEO_USBVIDEO=m
CONFIG_USB_VICAM=m CONFIG_USB_VICAM=m
CONFIG_USB_IBMCAM=m CONFIG_USB_IBMCAM=m
CONFIG_USB_KONICAWC=m CONFIG_USB_KONICAWC=m
CONFIG_USB_QUICKCAM_MESSENGER=m CONFIG_USB_QUICKCAM_MESSENGER=m
CONFIG_USB_ET61X251=m CONFIG_USB_ET61X251=m
CONFIG_VIDEO_OVCAMCHIP=m CONFIG_VIDEO_OVCAMCHIP=m
CONFIG_USB_W9968CF=m CONFIG_USB_W9968CF=m
CONFIG_USB_OV511=m CONFIG_USB_OV511=m
CONFIG_USB_SE401=m CONFIG_USB_SE401=m
CONFIG_USB_SN9C102=m CONFIG_USB_SN9C102=m
CONFIG_USB_STV680=m CONFIG_USB_STV680=m
CONFIG_USB_ZC0301=m CONFIG_USB_ZC0301=m
CONFIG_USB_PWC=m CONFIG_USB_PWC=m
# CONFIG_USB_PWC_DEBUG is not set # CONFIG_USB_PWC_DEBUG is not set

# #
# Radio Adapters # Radio Adapters
# #
# CONFIG_RADIO_GEMTEK_PCI is not set | CONFIG_RADIO_GEMTEK_PCI=m
# CONFIG_RADIO_MAXIRADIO is not set | CONFIG_RADIO_MAXIRADIO=m
# CONFIG_RADIO_MAESTRO is not set | CONFIG_RADIO_MAESTRO=m
CONFIG_USB_DSBR=m CONFIG_USB_DSBR=m

# #
# Digital Video Broadcasting Devices # Digital Video Broadcasting Devices
# #
# CONFIG_DVB is not set | CONFIG_DVB=y
> CONFIG_DVB_CORE=m
>
> #
> # Supported SAA7146 based PCI Adapters
> #
> CONFIG_DVB_AV7110=m
> CONFIG_DVB_AV7110_OSD=y
> CONFIG_DVB_BUDGET=m
> CONFIG_DVB_BUDGET_CI=m
> CONFIG_DVB_BUDGET_AV=m
> CONFIG_DVB_BUDGET_PATCH=m
>
> #
> # Supported USB Adapters
> #
> CONFIG_DVB_USB=m
> # CONFIG_DVB_USB_DEBUG is not set
> CONFIG_DVB_USB_A800=m
> CONFIG_DVB_USB_DIBUSB_MB=m
> CONFIG_DVB_USB_DIBUSB_MB_FAULTY=y
> CONFIG_DVB_USB_DIBUSB_MC=m

```

```
> CONFIG_DVB_USB_UMT_010=m
> CONFIG_DVB_USB_CXUSB=m
> CONFIG_DVB_USB_DIGITV=m
> CONFIG_DVB_USB_VP7045=m
> CONFIG_DVB_USB_VP702X=m
> CONFIG_DVB_USB_GP8PSK=m
> CONFIG_DVB_USB_NOVA_T_USB2=m
> CONFIG_DVB_USB_DTT200U=m
> CONFIG_DVB_TTUSB_BUDGET=m
> CONFIG_DVB_TTUSB_DEC=m
> CONFIG_DVB_CINERGYT2=m
> CONFIG_DVB_CINERGYT2_TUNING=y
> CONFIG_DVB_CINERGYT2_STREAM_URB_COUNT=32
> CONFIG_DVB_CINERGYT2_STREAM_BUF_SIZE=512
> CONFIG_DVB_CINERGYT2_QUERY_INTERVAL=250
> CONFIG_DVB_CINERGYT2_ENABLE_RC_INPUT_DEVICE=y
> CONFIG_DVB_CINERGYT2_RC_QUERY_INTERVAL=50
>
> #
> # Supported FlexCopII (B2C2) Adapters
> #
> CONFIG_DVB_B2C2_FLEXCOP=m
> CONFIG_DVB_B2C2_FLEXCOP_PCI=m
> CONFIG_DVB_B2C2_FLEXCOP_USB=m
> # CONFIG_DVB_B2C2_FLEXCOP_DEBUG is not set
>
> #
> # Supported BT878 Adapters
> #
> CONFIG_DVB_BT8XX=m
>
> #
> # Supported Pluto2 Adapters
> #
> CONFIG_DVB_PLUTO2=m
>
> #
> # Supported DVB Frontends
> #
>
> #
> # Customise DVB Frontends
> #
>
> #
> # DVB-S (satellite) frontends
> #
> CONFIG_DVB_STV0299=m
> CONFIG_DVB_CX24110=m
> CONFIG_DVB_CX24123=m
> CONFIG_DVB_TDA8083=m
> CONFIG_DVB_MT312=m
> CONFIG_DVB_VES1X93=m
> CONFIG_DVB_S5H1420=m
>
> #
> # DVB-T (terrestrial) frontends
> #
> CONFIG_DVB_SP8870=m
> CONFIG_DVB_SP887X=m
> CONFIG_DVB_CX22700=m
> CONFIG_DVB_CX22702=m
> CONFIG_DVB_L64781=m
> CONFIG_DVB_TDA1004X=m
> CONFIG_DVB_NXT6000=m
> CONFIG_DVB_MT352=m
> CONFIG_DVB_ZL10353=m
> CONFIG_DVB_DIB3000MB=m
> CONFIG_DVB_DIB3000MC=m
>
> #
> # DVB-C (cable) frontends
> #
> CONFIG_DVB_VES1820=m
> CONFIG_DVB_TDA10021=m
> CONFIG_DVB_STV0297=m
>
> #
> # ATSC (North American/Korean Terrestrial/Cable DTV) frontend
```

```

> #
> CONFIG_DVB_NXT200X=m
> CONFIG_DVB_OR51211=m
> CONFIG_DVB_OR51132=m
> CONFIG_DVB_BCM3510=m
> CONFIG_DVB_LGDT330X=m
>
> #
> # Miscellaneous devices
> #
> CONFIG_DVB_PLL=m
> CONFIG_DVB_LNBP21=m
> CONFIG_DVB_ISL6421=m
> CONFIG_VIDEO_SAA7146=m
> CONFIG_VIDEO_SAA7146_VV=m
> CONFIG_VIDEO_VIDEOBUF=m
CONFIG_VIDEO_TUNER=m          CONFIG_VIDEO_TUNER=m
CONFIG_VIDEO_BUF=m          CONFIG_VIDEO_BUF=m
> CONFIG_VIDEO_BUF_DVB=m
CONFIG_VIDEO_BTCX=m          CONFIG_VIDEO_BTCX=m
CONFIG_VIDEO_IR=m          CONFIG_VIDEO_IR=m
CONFIG_VIDEO_TVEEPROM=m     CONFIG_VIDEO_TVEEPROM=m
CONFIG_USB_DABUSB=m        CONFIG_USB_DABUSB=m

#           #
# Graphics support           # Graphics support
#           #
# CONFIG_FIRMWARE_EDID is not set # CONFIG_FIRMWARE_EDID is not set
CONFIG_FB=y          CONFIG_FB=y
CONFIG_FB_CFB_FILLRECT=m    CONFIG_FB_CFB_FILLRECT=m
CONFIG_FB_CFB_COPYAREA=m    CONFIG_FB_CFB_COPYAREA=m
CONFIG_FB_CFB_IMAGEBLIT=m   CONFIG_FB_CFB_IMAGEBLIT=m
# CONFIG_FB_MACMODES is not set # CONFIG_FB_MACMODES is not set
# CONFIG_FB_BACKLIGHT is not set # CONFIG_FB_BACKLIGHT is not set
CONFIG_FB_MODE_HELPERS=y    CONFIG_FB_MODE_HELPERS=y
CONFIG_FB_TILEBLITTING=y    CONFIG_FB_TILEBLITTING=y
CONFIG_FB_CIRRUS=m         CONFIG_FB_CIRRUS=m
# CONFIG_FB_PM2 is not set # CONFIG_FB_PM2 is not set
# CONFIG_FB_CYBER2000 is not set # CONFIG_FB_CYBER2000 is not set
# CONFIG_FB_ARC is not set # CONFIG_FB_ARC is not set
# CONFIG_FB_ASILANT is not set # CONFIG_FB_ASILANT is not set
# CONFIG_FB_IMSTT is not set # CONFIG_FB_IMSTT is not set
CONFIG_FB_VGA16=m          CONFIG_FB_VGA16=m
# CONFIG_FB_VESA is not set # CONFIG_FB_VESA is not set
# CONFIG_FB_IMAC is not set # CONFIG_FB_IMAC is not set
# CONFIG_FB_HGA is not set # CONFIG_FB_HGA is not set
# CONFIG_FB_S1D13XXX is not set # CONFIG_FB_S1D13XXX is not set
CONFIG_FB_NVIDIA=m         CONFIG_FB_NVIDIA=m
CONFIG_FB_NVIDIA_I2C=y     CONFIG_FB_NVIDIA_I2C=y
CONFIG_FB_RIVA=m           CONFIG_FB_RIVA=m
# CONFIG_FB_RIVA_I2C is not set # CONFIG_FB_RIVA_I2C is not set
# CONFIG_FB_RIVA_DEBUG is not set # CONFIG_FB_RIVA_DEBUG is not set
CONFIG_FB_I810=m           CONFIG_FB_I810=m
CONFIG_FB_I810_GTF=y       CONFIG_FB_I810_GTF=y
CONFIG_FB_I810_I2C=y       CONFIG_FB_I810_I2C=y
CONFIG_FB_INTEL=m          CONFIG_FB_INTEL=m
# CONFIG_FB_INTEL_DEBUG is not set # CONFIG_FB_INTEL_DEBUG is not set
# CONFIG_FB_MATROX is not set # CONFIG_FB_MATROX is not set
# CONFIG_FB_RADEON is not set # CONFIG_FB_RADEON is not set
# CONFIG_FB_ATY128 is not set # CONFIG_FB_ATY128 is not set
# CONFIG_FB_ATY is not set # CONFIG_FB_ATY is not set
CONFIG_FB_SAVAGE=m         CONFIG_FB_SAVAGE=m
CONFIG_FB_SAVAGE_I2C=y     CONFIG_FB_SAVAGE_I2C=y
CONFIG_FB_SAVAGE_ACCEL=y   CONFIG_FB_SAVAGE_ACCEL=y
# CONFIG_FB_SIS is not set # CONFIG_FB_SIS is not set
# CONFIG_FB_NEOMAGIC is not set # CONFIG_FB_NEOMAGIC is not set
CONFIG_FB_KYRO=m           CONFIG_FB_KYRO=m
# CONFIG_FB_3DFX is not set # CONFIG_FB_3DFX is not set
# CONFIG_FB_VOODOO1 is not set # CONFIG_FB_VOODOO1 is not set
CONFIG_FB_CYBLA=m          CONFIG_FB_CYBLA=m
# CONFIG_FB_TRIDENT is not set # CONFIG_FB_TRIDENT is not set
# CONFIG_FB_GEODE is not set # CONFIG_FB_GEODE is not set
# CONFIG_FB_VIRTUAL is not set # CONFIG_FB_VIRTUAL is not set

#           #
# Console display driver support # Console display driver support
#           #
CONFIG_VGA_CONSOLE=y       CONFIG_VGA_CONSOLE=y
CONFIG_VGACON_SOFT_SCROLLBACK=y CONFIG_VGACON_SOFT_SCROLLBACK=y

```

```

CONFIG_VGACON_SOFT_SCROLLBACK_SIZE=64      CONFIG_VGACON_SOFT_SCROLLBACK_SIZE=64
CONFIG_VIDEO_SELECT=y                       CONFIG_VIDEO_SELECT=y
CONFIG_DUMMY_CONSOLE=y                      CONFIG_DUMMY_CONSOLE=y
CONFIG_FRAMEBUFFER_CONSOLE=y               CONFIG_FRAMEBUFFER_CONSOLE=y
CONFIG_FRAMEBUFFER_CONSOLE_ROTATION=y      CONFIG_FRAMEBUFFER_CONSOLE_ROTATION=y
# CONFIG_FONTS is not set                   # CONFIG_FONTS is not set
CONFIG_FONT_8x8=y                           CONFIG_FONT_8x8=y
CONFIG_FONT_8x16=y                          CONFIG_FONT_8x16=y

# #
# Logo configuration                        # Logo configuration
# #
CONFIG_LOGO=y                               CONFIG_LOGO=y
# CONFIG_LOGO_LINUX_MONO is not set        # CONFIG_LOGO_LINUX_MONO is not set
# CONFIG_LOGO_LINUX_VGA16 is not set       # CONFIG_LOGO_LINUX_VGA16 is not set
CONFIG_LOGO_LINUX_CLUT224=y                CONFIG_LOGO_LINUX_CLUT224=y
CONFIG_BACKLIGHT_LCD_SUPPORT=y              CONFIG_BACKLIGHT_LCD_SUPPORT=y
CONFIG_BACKLIGHT_CLASS_DEVICE=m            CONFIG_BACKLIGHT_CLASS_DEVICE=m
CONFIG_BACKLIGHT_DEVICE=y                  CONFIG_BACKLIGHT_DEVICE=y
CONFIG_LCD_CLASS_DEVICE=m                  CONFIG_LCD_CLASS_DEVICE=m
CONFIG_LCD_DEVICE=y                         CONFIG_LCD_DEVICE=y

# #
# Sound                                    # Sound
# #
CONFIG_SOUND=m                              CONFIG_SOUND=m

# #
# Advanced Linux Sound Architecture        # Advanced Linux Sound Architecture
# #
CONFIG_SND=m                                CONFIG_SND=m
CONFIG_SND_TIMER=m                          CONFIG_SND_TIMER=m
CONFIG_SND_PCM=m                            CONFIG_SND_PCM=m
CONFIG_SND_HWDEP=m                          CONFIG_SND_HWDEP=m
CONFIG_SND_RAWMIDI=m                        CONFIG_SND_RAWMIDI=m
CONFIG_SND_SEQUENCER=m                      CONFIG_SND_SEQUENCER=m
CONFIG_SND_SEQ_DUMMY=m                      CONFIG_SND_SEQ_DUMMY=m
CONFIG_SND_OSSEMUL=y                        CONFIG_SND_OSSEMUL=y
CONFIG_SND_MIXER_OSS=m                      CONFIG_SND_MIXER_OSS=m
CONFIG_SND_PCM_OSS=m                        CONFIG_SND_PCM_OSS=m
CONFIG_SND_PCM_OSS_PLUGINS=y                CONFIG_SND_PCM_OSS_PLUGINS=y
CONFIG_SND_SEQUENCER_OSS=y                  CONFIG_SND_SEQUENCER_OSS=y
CONFIG_SND_RTCTIMER=m                       CONFIG_SND_RTCTIMER=m
CONFIG_SND_SEQ_RTCTIMER_DEFAULT=y           CONFIG_SND_SEQ_RTCTIMER_DEFAULT=y
CONFIG_SND_DYNAMIC_MINORS=y                 CONFIG_SND_DYNAMIC_MINORS=y
# CONFIG_SND_SUPPORT_OLD_API is not set    # CONFIG_SND_SUPPORT_OLD_API is not set
CONFIG_SND_VERBOSE_PROCFS=y                 CONFIG_SND_VERBOSE_PROCFS=y
# CONFIG_SND_VERBOSE_PRINTK is not set     # CONFIG_SND_VERBOSE_PRINTK is not set
# CONFIG_SND_DEBUG is not set              # CONFIG_SND_DEBUG is not set

# #
# Generic devices                          # Generic devices
# #
CONFIG_SND_MPU401_UART=m                    CONFIG_SND_MPU401_UART=m
CONFIG_SND_OPL3_LIB=m                       CONFIG_SND_OPL3_LIB=m
CONFIG_SND_VX_LIB=m                          CONFIG_SND_VX_LIB=m
CONFIG_SND_AC97_CODEC=m                     CONFIG_SND_AC97_CODEC=m
CONFIG_SND_AC97_BUS=m                       CONFIG_SND_AC97_BUS=m
CONFIG_SND_DUMMY=m                           CONFIG_SND_DUMMY=m
CONFIG_SND_VIRMIDI=m                         CONFIG_SND_VIRMIDI=m
CONFIG_SND_MTPAV=m                           CONFIG_SND_MTPAV=m
# CONFIG_SND_SERIAL_U16550 is not set      # CONFIG_SND_SERIAL_U16550 is not set
CONFIG_SND_MPU401=m                          CONFIG_SND_MPU401=m

# #
# PCI devices                              # PCI devices
# #
CONFIG_SND_AD1889=m                          CONFIG_SND_AD1889=m
CONFIG_SND_ALS300=m                          CONFIG_SND_ALS300=m
CONFIG_SND_ALS4000=m                         CONFIG_SND_ALS4000=m
CONFIG_SND_ALI5451=m                         CONFIG_SND_ALI5451=m
CONFIG_SND_ATIIXP=m                          CONFIG_SND_ATIIXP=m
CONFIG_SND_ATIIXP_MODEM=m                    CONFIG_SND_ATIIXP_MODEM=m
CONFIG_SND_AU8810=m                          CONFIG_SND_AU8810=m
CONFIG_SND_AU8820=m                          CONFIG_SND_AU8820=m
CONFIG_SND_AU8830=m                          CONFIG_SND_AU8830=m
CONFIG_SND_AZT3328=m                         CONFIG_SND_AZT3328=m
CONFIG_SND_BT87X=m                           CONFIG_SND_BT87X=m
# CONFIG_SND_BT87X_OVERCLOCK is not set    # CONFIG_SND_BT87X_OVERCLOCK is not set

```

```

CONFIG_SND_CA0106=m          CONFIG_SND_CA0106=m
CONFIG_SND_CMIPCI=m         CONFIG_SND_CMIPCI=m
CONFIG_SND_CS4281=m        CONFIG_SND_CS4281=m
CONFIG_SND_CS46XX=m        CONFIG_SND_CS46XX=m
CONFIG_SND_CS46XX_NEW_DSP=y  CONFIG_SND_CS46XX_NEW_DSP=y
CONFIG_SND_CS5535AUDIO=m    CONFIG_SND_CS5535AUDIO=m
CONFIG_SND_DARLA20=m       CONFIG_SND_DARLA20=m
CONFIG_SND_GINA20=m        CONFIG_SND_GINA20=m
CONFIG_SND_LAYLA20=m       CONFIG_SND_LAYLA20=m
CONFIG_SND_DARLA24=m       CONFIG_SND_DARLA24=m
CONFIG_SND_GINA24=m        CONFIG_SND_GINA24=m
CONFIG_SND_LAYLA24=m       CONFIG_SND_LAYLA24=m
CONFIG_SND_MONA=m          CONFIG_SND_MONA=m
CONFIG_SND_MIA=m           CONFIG_SND_MIA=m
CONFIG_SND_ECHO3G=m        CONFIG_SND_ECHO3G=m
CONFIG_SND_INDIGO=m        CONFIG_SND_INDIGO=m
CONFIG_SND_INDIGOIO=m      CONFIG_SND_INDIGOIO=m
CONFIG_SND_INDIGODJ=m      CONFIG_SND_INDIGODJ=m
CONFIG_SND_EMU10K1=m       CONFIG_SND_EMU10K1=m
CONFIG_SND_EMU10K1X=m      CONFIG_SND_EMU10K1X=m
CONFIG_SND_ENS1370=m       CONFIG_SND_ENS1370=m
CONFIG_SND_ENS1371=m       CONFIG_SND_ENS1371=m
CONFIG_SND_ES1938=m        CONFIG_SND_ES1938=m
CONFIG_SND_ES1968=m        CONFIG_SND_ES1968=m
CONFIG_SND_FM801=m         CONFIG_SND_FM801=m
CONFIG_SND_FM801_TEA575X_BOOL=y  CONFIG_SND_FM801_TEA575X_BOOL=y
CONFIG_SND_FM801_TEA575X=m  CONFIG_SND_FM801_TEA575X=m
CONFIG_SND_HDA_INTEL=m     CONFIG_SND_HDA_INTEL=m
CONFIG_SND_HDSP=m          CONFIG_SND_HDSP=m
CONFIG_SND_HDSPM=m         CONFIG_SND_HDSPM=m
CONFIG_SND_ICE1712=m       CONFIG_SND_ICE1712=m
CONFIG_SND_ICE1724=m       CONFIG_SND_ICE1724=m
CONFIG_SND_INTEL8X0=m      CONFIG_SND_INTEL8X0=m
CONFIG_SND_INTEL8X0M=m     CONFIG_SND_INTEL8X0M=m
CONFIG_SND_KORG1212=m      CONFIG_SND_KORG1212=m
CONFIG_SND_MAESTRO3=m     CONFIG_SND_MAESTRO3=m
CONFIG_SND_MIXART=m        CONFIG_SND_MIXART=m
CONFIG_SND_NM256=m         CONFIG_SND_NM256=m
CONFIG_SND_PCXHR=m         CONFIG_SND_PCXHR=m
CONFIG_SND_RIPTIDE=m       CONFIG_SND_RIPTIDE=m
CONFIG_SND_RME32=m         CONFIG_SND_RME32=m
CONFIG_SND_RME96=m         CONFIG_SND_RME96=m
CONFIG_SND_RME9652=m       CONFIG_SND_RME9652=m
CONFIG_SND_SONICVIBES=m    CONFIG_SND_SONICVIBES=m
CONFIG_SND_TRIDENT=m       CONFIG_SND_TRIDENT=m
CONFIG_SND_VIA82XX=m       CONFIG_SND_VIA82XX=m
CONFIG_SND_VIA82XX_MODEM=m  CONFIG_SND_VIA82XX_MODEM=m
CONFIG_SND_VX222=m         CONFIG_SND_VX222=m
CONFIG_SND_YMFPCI=m        CONFIG_SND_YMFPCI=m

# #
# USB devices # USB devices
# #
CONFIG_SND_USB_AUDIO=m      CONFIG_SND_USB_AUDIO=m
CONFIG_SND_USB_USX2Y=m      CONFIG_SND_USB_USX2Y=m

# #
# PCMCIA devices # PCMCIA devices
# #
# CONFIG_SND_VXPOCKET is not set # CONFIG_SND_VXPOCKET is not set
# CONFIG_SND_PDAUDIOCF is not set # CONFIG_SND_PDAUDIOCF is not set

# #
# Open Sound System # Open Sound System
# #
# CONFIG_SOUND_PRIME is not set # CONFIG_SOUND_PRIME is not set

# #
# USB support # USB support
# #
CONFIG_USB_ARCH_HAS_HCD=y   CONFIG_USB_ARCH_HAS_HCD=y
CONFIG_USB_ARCH_HAS_OHCI=y  CONFIG_USB_ARCH_HAS_OHCI=y
CONFIG_USB_ARCH_HAS_EHCI=y  CONFIG_USB_ARCH_HAS_EHCI=y
CONFIG_USB=y                 CONFIG_USB=y
# CONFIG_USB_DEBUG is not set # CONFIG_USB_DEBUG is not set

# #
# Miscellaneous USB options # Miscellaneous USB options
# #

```

```

CONFIG_USB_DEVICEFS=y          CONFIG_USB_DEVICEFS=y
# CONFIG_USB_BANDWIDTH is not set # CONFIG_USB_BANDWIDTH is not set
# CONFIG_USB_DYNAMIC_MINORS is not set # CONFIG_USB_DYNAMIC_MINORS is not set
# CONFIG_USB_SUSPEND is not set # CONFIG_USB_SUSPEND is not set
# CONFIG_USB_OTG is not set # CONFIG_USB_OTG is not set

# #
# USB Host Controller Drivers # USB Host Controller Drivers
# #
CONFIG_USB_EHCI_HCD=m          CONFIG_USB_EHCI_HCD=m
CONFIG_USB_EHCI_SPLIT_ISO=y    CONFIG_USB_EHCI_SPLIT_ISO=y
CONFIG_USB_EHCI_ROOT_HUB_TT=y  CONFIG_USB_EHCI_ROOT_HUB_TT=y
CONFIG_USB_EHCI_TT_NEWSCHED=y  CONFIG_USB_EHCI_TT_NEWSCHED=y
CONFIG_USB_ISP116X_HCD=m       CONFIG_USB_ISP116X_HCD=m
CONFIG_USB_OHCI_HCD=m          CONFIG_USB_OHCI_HCD=m
# CONFIG_USB_OHCI_BIG_ENDIAN is not set # CONFIG_USB_OHCI_BIG_ENDIAN is not set
CONFIG_USB_OHCI_LITTLE_ENDIAN=y CONFIG_USB_OHCI_LITTLE_ENDIAN=y
CONFIG_USB_UHCI_HCD=m          CONFIG_USB_UHCI_HCD=m
CONFIG_USB_SL811_HCD=m         CONFIG_USB_SL811_HCD=m
CONFIG_USB_SL811_CS=m          CONFIG_USB_SL811_CS=m

# #
# USB Device Class drivers # USB Device Class drivers
# #
CONFIG_USB_ACM=m              CONFIG_USB_ACM=m
CONFIG_USB_PRINTER=m          CONFIG_USB_PRINTER=m

# #
# NOTE: USB_STORAGE enables SCSI, and 'SCSI disk support' # NOTE: USB_STORAGE enables SCSI, and
# #

# #
# may also be needed; see USB_STORAGE Help for more informati # may also be needed; see USB_STOR
# #
CONFIG_USB_STORAGE=m          CONFIG_USB_STORAGE=m
# CONFIG_USB_STORAGE_DEBUG is not set # CONFIG_USB_STORAGE_DEBUG is not set
CONFIG_USB_STORAGE_DATAFAB=y   CONFIG_USB_STORAGE_DATAFAB=y
CONFIG_USB_STORAGE_FREECOM=y   CONFIG_USB_STORAGE_FREECOM=y
CONFIG_USB_STORAGE_ISD200=y    CONFIG_USB_STORAGE_ISD200=y
CONFIG_USB_STORAGE_DPCM=y      CONFIG_USB_STORAGE_DPCM=y
CONFIG_USB_STORAGE_USBAT=y     CONFIG_USB_STORAGE_USBAT=y
CONFIG_USB_STORAGE_SDDR09=y    CONFIG_USB_STORAGE_SDDR09=y
CONFIG_USB_STORAGE_SDDR55=y    CONFIG_USB_STORAGE_SDDR55=y
CONFIG_USB_STORAGE_JUMPSHOT=y  CONFIG_USB_STORAGE_JUMPSHOT=y
CONFIG_USB_STORAGE_ALAUDA=y    CONFIG_USB_STORAGE_ALAUDA=y
# CONFIG_USB_LIBUSUAL is not set # CONFIG_USB_LIBUSUAL is not set

# #
# USB Input Devices # USB Input Devices
# #
CONFIG_USB_HID=y              CONFIG_USB_HID=y
CONFIG_USB_HIDINPUT=y          CONFIG_USB_HIDINPUT=y
CONFIG_USB_HIDINPUT_POWERBOOK=y CONFIG_USB_HIDINPUT_POWERBOOK=y
CONFIG_HID_FF=y                CONFIG_HID_FF=y
CONFIG_HID_PID=y               CONFIG_HID_PID=y
CONFIG_LOGITECH_FF=y           CONFIG_LOGITECH_FF=y
CONFIG_THRUSTMASTER_FF=y      CONFIG_THRUSTMASTER_FF=y
CONFIG_USB_HIDDEV=y            CONFIG_USB_HIDDEV=y
CONFIG_USB_AIPTEK=m            CONFIG_USB_AIPTEK=m
CONFIG_USB_WACOM=m              CONFIG_USB_WACOM=m
CONFIG_USB_ACECAD=m            CONFIG_USB_ACECAD=m
CONFIG_USB_KBTAB=m             CONFIG_USB_KBTAB=m
CONFIG_USB_POWERMATE=m         CONFIG_USB_POWERMATE=m
CONFIG_USB_TOUCHSCREEN=m        CONFIG_USB_TOUCHSCREEN=m
CONFIG_USB_TOUCHSCREEN_EGALAX=y CONFIG_USB_TOUCHSCREEN_EGALAX=y
CONFIG_USB_TOUCHSCREEN_PANJIT=y CONFIG_USB_TOUCHSCREEN_PANJIT=y
CONFIG_USB_TOUCHSCREEN_3M=y     CONFIG_USB_TOUCHSCREEN_3M=y
CONFIG_USB_TOUCHSCREEN_ITM=y    CONFIG_USB_TOUCHSCREEN_ITM=y
# CONFIG_USB_YEALINK is not set # CONFIG_USB_YEALINK is not set
CONFIG_USB_XPAD=m              CONFIG_USB_XPAD=m
CONFIG_USB_ATI_REMOTE=m         CONFIG_USB_ATI_REMOTE=m
CONFIG_USB_ATI_REMOTE2=m        CONFIG_USB_ATI_REMOTE2=m
CONFIG_USB_KEYSPAN_REMOTE=m     CONFIG_USB_KEYSPAN_REMOTE=m
CONFIG_USB_APPLETOUCH=m         CONFIG_USB_APPLETOUCH=m

# #
# USB Imaging devices # USB Imaging devices
# #
CONFIG_USB_MDC800=m            CONFIG_USB_MDC800=m

```

```

CONFIG_USB_MICROTEK=m          CONFIG_USB_MICROTEK=m

#          #
# USB Network Adapters        # USB Network Adapters
#          #
CONFIG_USB_CATC=m             CONFIG_USB_CATC=m
CONFIG_USB_KAWETH=m           CONFIG_USB_KAWETH=m
CONFIG_USB_PEGASUS=m          CONFIG_USB_PEGASUS=m
CONFIG_USB_RTL8150=m          CONFIG_USB_RTL8150=m
CONFIG_USB_USBNET=m           CONFIG_USB_USBNET=m
CONFIG_USB_NET_AX8817X=m      CONFIG_USB_NET_AX8817X=m
CONFIG_USB_NET_CDCETHER=m     CONFIG_USB_NET_CDCETHER=m
CONFIG_USB_NET_GL620A=m       CONFIG_USB_NET_GL620A=m
CONFIG_USB_NET_NET1080=m      CONFIG_USB_NET_NET1080=m
CONFIG_USB_NET_PLUSB=m        CONFIG_USB_NET_PLUSB=m
CONFIG_USB_NET_RNDIS_HOST=m    CONFIG_USB_NET_RNDIS_HOST=m
CONFIG_USB_NET_CDC_SUBSET=m    CONFIG_USB_NET_CDC_SUBSET=m
CONFIG_USB_ALI_M5632=y        CONFIG_USB_ALI_M5632=y
CONFIG_USB_AN2720=y           CONFIG_USB_AN2720=y
CONFIG_USB_BELKIN=y           CONFIG_USB_BELKIN=y
CONFIG_USB_ARMLINUX=y         CONFIG_USB_ARMLINUX=y
CONFIG_USB_EPSON2888=y        CONFIG_USB_EPSON2888=y
CONFIG_USB_NET_ZAURUS=m       CONFIG_USB_NET_ZAURUS=m
CONFIG_USB_MON=y              CONFIG_USB_MON=y

#          #
# USB port drivers            # USB port drivers
#          #
CONFIG_USB_USS720=m           CONFIG_USB_USS720=m

#          #
# USB Serial Converter support # USB Serial Converter support
#          #
CONFIG_USB_SERIAL=m           CONFIG_USB_SERIAL=m
CONFIG_USB_SERIAL_GENERIC=y    CONFIG_USB_SERIAL_GENERIC=y
CONFIG_USB_SERIAL_AIRPRIME=m   CONFIG_USB_SERIAL_AIRPRIME=m
CONFIG_USB_SERIAL_ARK3116=m    CONFIG_USB_SERIAL_ARK3116=m
CONFIG_USB_SERIAL_BELKIN=m     CONFIG_USB_SERIAL_BELKIN=m
CONFIG_USB_SERIAL_WHITEHEAT=m  CONFIG_USB_SERIAL_WHITEHEAT=m
CONFIG_USB_SERIAL_DIGI_ACCELEPORT=m CONFIG_USB_SERIAL_DIGI_ACCELEPORT=m
CONFIG_USB_SERIAL_CP2101=m     CONFIG_USB_SERIAL_CP2101=m
CONFIG_USB_SERIAL_CYPRESS_M8=m CONFIG_USB_SERIAL_CYPRESS_M8=m
CONFIG_USB_SERIAL_EMPEG=m      CONFIG_USB_SERIAL_EMPEG=m
CONFIG_USB_SERIAL_FTDI_SIO=m   CONFIG_USB_SERIAL_FTDI_SIO=m
CONFIG_USB_SERIAL_FUNSOFT=m    CONFIG_USB_SERIAL_FUNSOFT=m
CONFIG_USB_SERIAL_VISOR=m      CONFIG_USB_SERIAL_VISOR=m
CONFIG_USB_SERIAL_IPAQ=m       CONFIG_USB_SERIAL_IPAQ=m
CONFIG_USB_SERIAL_IR=m         CONFIG_USB_SERIAL_IR=m
CONFIG_USB_SERIAL_EDGEPORT=m   CONFIG_USB_SERIAL_EDGEPORT=m
CONFIG_USB_SERIAL_EDGEPORT_TI=m CONFIG_USB_SERIAL_EDGEPORT_TI=m
CONFIG_USB_SERIAL_GARMIN=m     CONFIG_USB_SERIAL_GARMIN=m
CONFIG_USB_SERIAL_IPW=m        CONFIG_USB_SERIAL_IPW=m
CONFIG_USB_SERIAL_KEYSPAN_PDA=m CONFIG_USB_SERIAL_KEYSPAN_PDA=m
CONFIG_USB_SERIAL_KEYSPAN=m    CONFIG_USB_SERIAL_KEYSPAN=m
CONFIG_USB_SERIAL_KEYSPAN_MPR=y CONFIG_USB_SERIAL_KEYSPAN_MPR=y
CONFIG_USB_SERIAL_KEYSPAN_USA28=y CONFIG_USB_SERIAL_KEYSPAN_USA28=y
CONFIG_USB_SERIAL_KEYSPAN_USA28X=y CONFIG_USB_SERIAL_KEYSPAN_USA28X=y
CONFIG_USB_SERIAL_KEYSPAN_USA28XA=y CONFIG_USB_SERIAL_KEYSPAN_USA28XA=y
CONFIG_USB_SERIAL_KEYSPAN_USA28XB=y CONFIG_USB_SERIAL_KEYSPAN_USA28XB=y
CONFIG_USB_SERIAL_KEYSPAN_USA19=y CONFIG_USB_SERIAL_KEYSPAN_USA19=y
CONFIG_USB_SERIAL_KEYSPAN_USA18X=y CONFIG_USB_SERIAL_KEYSPAN_USA18X=y
CONFIG_USB_SERIAL_KEYSPAN_USA19W=y CONFIG_USB_SERIAL_KEYSPAN_USA19W=y
CONFIG_USB_SERIAL_KEYSPAN_USA19QW=y CONFIG_USB_SERIAL_KEYSPAN_USA19QW=y
CONFIG_USB_SERIAL_KEYSPAN_USA19QI=y CONFIG_USB_SERIAL_KEYSPAN_USA19QI=y
CONFIG_USB_SERIAL_KEYSPAN_USA49W=y CONFIG_USB_SERIAL_KEYSPAN_USA49W=y
CONFIG_USB_SERIAL_KEYSPAN_USA49WLC=y CONFIG_USB_SERIAL_KEYSPAN_USA49WLC=y
CONFIG_USB_SERIAL_KLSI=m       CONFIG_USB_SERIAL_KLSI=m
CONFIG_USB_SERIAL_KOBIL_SCT=m   CONFIG_USB_SERIAL_KOBIL_SCT=m
CONFIG_USB_SERIAL_MCT_U232=m    CONFIG_USB_SERIAL_MCT_U232=m
CONFIG_USB_SERIAL_NAVMAN=m      CONFIG_USB_SERIAL_NAVMAN=m
CONFIG_USB_SERIAL_PL2303=m      CONFIG_USB_SERIAL_PL2303=m
CONFIG_USB_SERIAL_HP4X=m        CONFIG_USB_SERIAL_HP4X=m
CONFIG_USB_SERIAL_SAFE=m        CONFIG_USB_SERIAL_SAFE=m
CONFIG_USB_SERIAL_SAFE_PADDED=y CONFIG_USB_SERIAL_SAFE_PADDED=y
CONFIG_USB_SERIAL_SIERRAWIRELESS=m CONFIG_USB_SERIAL_SIERRAWIRELESS=m
CONFIG_USB_SERIAL_TI=m         CONFIG_USB_SERIAL_TI=m
CONFIG_USB_SERIAL_CYBERJACK=m   CONFIG_USB_SERIAL_CYBERJACK=m
CONFIG_USB_SERIAL_XIRCOM=m      CONFIG_USB_SERIAL_XIRCOM=m
CONFIG_USB_SERIAL_OPTION=m      CONFIG_USB_SERIAL_OPTION=m

```

```

CONFIG_USB_SERIAL_OMNINET=m      CONFIG_USB_SERIAL_OMNINET=m
CONFIG_USB_EZUSB=y              CONFIG_USB_EZUSB=y

#
#
# USB Miscellaneous drivers      # USB Miscellaneous drivers
#
#
CONFIG_USB_EMI62=m              CONFIG_USB_EMI62=m
CONFIG_USB_EMI26=m              CONFIG_USB_EMI26=m
CONFIG_USB_AUERSWALD=m          CONFIG_USB_AUERSWALD=m
CONFIG_USB_RIO500=m             CONFIG_USB_RIO500=m
CONFIG_USB_LEGOTOWER=m          CONFIG_USB_LEGOTOWER=m
CONFIG_USB_LCD=m                 CONFIG_USB_LCD=m
CONFIG_USB_LED=m                 CONFIG_USB_LED=m
# CONFIG_USB_CYPRESS_CY7C63 is not set # CONFIG_USB_CYPRESS_CY7C63 is not set
# CONFIG_USB_CYTHERM is not set # CONFIG_USB_CYTHERM is not set
CONFIG_USB_PHIDGETKIT=m          CONFIG_USB_PHIDGETKIT=m
CONFIG_USB_PHIDGETSERVO=m        CONFIG_USB_PHIDGETSERVO=m
CONFIG_USB_IDMOUSE=m            CONFIG_USB_IDMOUSE=m
CONFIG_USB_APPLEDISPLAY=m        CONFIG_USB_APPLEDISPLAY=m
CONFIG_USB_SISUSBVGA=m           CONFIG_USB_SISUSBVGA=m
CONFIG_USB_SISUSBVGA_CON=y       CONFIG_USB_SISUSBVGA_CON=y
CONFIG_USB_LD=m                  CONFIG_USB_LD=m
CONFIG_USB_TEST=m                CONFIG_USB_TEST=m

#
#
# USB DSL modem support          # USB DSL modem support
#
#
CONFIG_USB_ATM=m                 CONFIG_USB_ATM=m
CONFIG_USB_SPEEDTOUCH=m          CONFIG_USB_SPEEDTOUCH=m
CONFIG_USB_CXACRU=m              CONFIG_USB_CXACRU=m
CONFIG_USB_UEAGLEATM=m           CONFIG_USB_UEAGLEATM=m
CONFIG_USB_XUSBATM=m             CONFIG_USB_XUSBATM=m

#
#
# USB Gadget Support            # USB Gadget Support
#
#
# CONFIG_USB_GADGET is not set # CONFIG_USB_GADGET is not set

#
#
# MMC/SD Card support           # MMC/SD Card support
#
#
CONFIG_MMC=m                     CONFIG_MMC=m
# CONFIG_MMC_DEBUG is not set # CONFIG_MMC_DEBUG is not set
CONFIG_MMC_BLOCK=m               CONFIG_MMC_BLOCK=m
CONFIG_MMC_SDHCI=m               CONFIG_MMC_SDHCI=m
CONFIG_MMC_WBSD=m                CONFIG_MMC_WBSD=m

#
#
# LED devices                    # LED devices
#
#
CONFIG_NEW_LEDS=y                 CONFIG_NEW_LEDS=y
CONFIG_LEDS_CLASS=y               CONFIG_LEDS_CLASS=y

#
#
# LED drivers                    # LED drivers
#
#

#
#
# LED Triggers                   # LED Triggers
#
#
CONFIG_LEDS_TRIGGERS=y            CONFIG_LEDS_TRIGGERS=y
CONFIG_LEDS_TRIGGER_TIMER=m        CONFIG_LEDS_TRIGGER_TIMER=m
CONFIG_LEDS_TRIGGER_IDE_DISK=y     CONFIG_LEDS_TRIGGER_IDE_DISK=y
CONFIG_LEDS_TRIGGER_HEARTBEAT=m    CONFIG_LEDS_TRIGGER_HEARTBEAT=m

#
#
# InfiniBand support            # InfiniBand support
#
#
CONFIG_INFINIBAND=m               CONFIG_INFINIBAND=m
CONFIG_INFINIBAND_USER_MAD=m       CONFIG_INFINIBAND_USER_MAD=m
CONFIG_INFINIBAND_USER_ACCESS=m     CONFIG_INFINIBAND_USER_ACCESS=m
CONFIG_INFINIBAND_ADDR_TRANS=y      CONFIG_INFINIBAND_ADDR_TRANS=y
CONFIG_INFINIBAND_MTHCA=m           CONFIG_INFINIBAND_MTHCA=m
CONFIG_INFINIBAND_MTHCA_DEBUG=y     CONFIG_INFINIBAND_MTHCA_DEBUG=y
CONFIG_INFINIBAND_IPOIB=m           CONFIG_INFINIBAND_IPOIB=m
CONFIG_INFINIBAND_IPOIB_DEBUG=y     CONFIG_INFINIBAND_IPOIB_DEBUG=y
# CONFIG_INFINIBAND_IPOIB_DEBUG_DATA is not set # CONFIG_INFINIBAND_IPOIB_DEBUG_DATA is not set
CONFIG_INFINIBAND_SRP=m             CONFIG_INFINIBAND_SRP=m
CONFIG_INFINIBAND_ISER=m            CONFIG_INFINIBAND_ISER=m

```

```

CONFIG_INFINIBAND_SDP=m          CONFIG_INFINIBAND_SDP=m
# CONFIG_INFINIBAND_SDP_DEBUG is not set # CONFIG_INFINIBAND_SDP_DEBUG is not set
CONFIG_INFINIBAND_MADEYE=m      CONFIG_INFINIBAND_MADEYE=m

# #
# EDAC - error detection and reporting (RAS) (EXPERIMENTAL) # EDAC - error detection and reporti
# #
CONFIG_EDAC=y                  CONFIG_EDAC=y

# #
# Reporting subsystems # Reporting subsystems
# #
# CONFIG_EDAC_DEBUG is not set # CONFIG_EDAC_DEBUG is not set
CONFIG_EDAC_MM_EDAC=m          CONFIG_EDAC_MM_EDAC=m
CONFIG_EDAC_AMD76X=m           CONFIG_EDAC_AMD76X=m
CONFIG_EDAC_E7XXX=m            CONFIG_EDAC_E7XXX=m
CONFIG_EDAC_E752X=m            CONFIG_EDAC_E752X=m
CONFIG_EDAC_I82875P=m          CONFIG_EDAC_I82875P=m
CONFIG_EDAC_I82860=m           CONFIG_EDAC_I82860=m
CONFIG_EDAC_K8=m                CONFIG_EDAC_K8=m
CONFIG_EDAC_R82600=m           CONFIG_EDAC_R82600=m
CONFIG_EDAC_POLL=y             CONFIG_EDAC_POLL=y

# #
# Real Time Clock # Real Time Clock
# #
CONFIG_RTC_LIB=m                CONFIG_RTC_LIB=m
CONFIG_RTC_CLASS=m              CONFIG_RTC_CLASS=m

# #
# RTC interfaces # RTC interfaces
# #
CONFIG_RTC_INTF_SYSFS=m         CONFIG_RTC_INTF_SYSFS=m
CONFIG_RTC_INTF_PROC=m         CONFIG_RTC_INTF_PROC=m
CONFIG_RTC_INTF_DEV=m          CONFIG_RTC_INTF_DEV=m
# CONFIG_RTC_INTF_DEV_UIE_EMUL is not set # CONFIG_RTC_INTF_DEV_UIE_EMUL is not set

# #
# RTC drivers # RTC drivers
# #
CONFIG_RTC_DRV_X1205=m          CONFIG_RTC_DRV_X1205=m
CONFIG_RTC_DRV_DS1307=m        CONFIG_RTC_DRV_DS1307=m
CONFIG_RTC_DRV_DS1553=m        CONFIG_RTC_DRV_DS1553=m
CONFIG_RTC_DRV_ISL1208=m       CONFIG_RTC_DRV_ISL1208=m
CONFIG_RTC_DRV_DS1672=m        CONFIG_RTC_DRV_DS1672=m
CONFIG_RTC_DRV_DS1742=m        CONFIG_RTC_DRV_DS1742=m
CONFIG_RTC_DRV_PCF8563=m       CONFIG_RTC_DRV_PCF8563=m
CONFIG_RTC_DRV_PCF8583=m       CONFIG_RTC_DRV_PCF8583=m
CONFIG_RTC_DRV_RS5C372=m       CONFIG_RTC_DRV_RS5C372=m
# CONFIG_RTC_DRV_M48T86 is not set # CONFIG_RTC_DRV_M48T86 is not set
# CONFIG_RTC_DRV_TEST is not set # CONFIG_RTC_DRV_TEST is not set
CONFIG_RTC_DRV_V3020=m         CONFIG_RTC_DRV_V3020=m

# #
# DMA Engine support # DMA Engine support
# #
CONFIG_DMA_ENGINE=y            CONFIG_DMA_ENGINE=y

# #
# DMA Clients # DMA Clients
# #
CONFIG_NET_DMA=y               CONFIG_NET_DMA=y

# #
# DMA Devices # DMA Devices
# #
CONFIG_INTEL_IOATDMA=m         CONFIG_INTEL_IOATDMA=m

# #
# File systems # File systems
# #
CONFIG_EXT2_FS=y                CONFIG_EXT2_FS=y
CONFIG_EXT2_FS_XATTR=y         CONFIG_EXT2_FS_XATTR=y
CONFIG_EXT2_FS_POSIX_ACL=y     CONFIG_EXT2_FS_POSIX_ACL=y
CONFIG_EXT2_FS_SECURITY=y      CONFIG_EXT2_FS_SECURITY=y
CONFIG_EXT2_FS_XIP=y           CONFIG_EXT2_FS_XIP=y
CONFIG_FS_XIP=y                 CONFIG_FS_XIP=y
CONFIG_EXT3_FS=m                CONFIG_EXT3_FS=m
CONFIG_EXT3_FS_XATTR=y         CONFIG_EXT3_FS_XATTR=y

```

```

CONFIG_EXT3_FS_POSIX_ACL=y      CONFIG_EXT3_FS_POSIX_ACL=y
CONFIG_EXT3_FS_SECURITY=y      CONFIG_EXT3_FS_SECURITY=y
CONFIG_JBD=m                    CONFIG_JBD=m
# CONFIG_JBD_DEBUG is not set   # CONFIG_JBD_DEBUG is not set
CONFIG_FS_MBCACHE=y           CONFIG_FS_MBCACHE=y
# CONFIG_REISERFS_FS is not set | CONFIG_REISERFS_FS=m
# CONFIG_JFS_FS is not set     | # CONFIG_REISERFS_CHECK is not set
    > # CONFIG_REISERFS_PROC_INFO is not set
    > CONFIG_REISERFS_FS_XATTR=y
    > CONFIG_REISERFS_FS_POSIX_ACL=y
    > CONFIG_REISERFS_FS_SECURITY=y
    > CONFIG_JFS_FS=m
    > CONFIG_JFS_POSIX_ACL=y
    > CONFIG_JFS_SECURITY=y
    > # CONFIG_JFS_DEBUG is not set
    > # CONFIG_JFS_STATISTICS is not set
CONFIG_FS_POSIX_ACL=y         CONFIG_FS_POSIX_ACL=y
# CONFIG_XFS_FS is not set     # CONFIG_XFS_FS is not set
CONFIG_GFS2_FS=m             CONFIG_GFS2_FS=m
CONFIG_GFS2_FS_LOCKING_NOLOCK=m CONFIG_GFS2_FS_LOCKING_NOLOCK=m
CONFIG_GFS2_FS_LOCKING_DLM=m  CONFIG_GFS2_FS_LOCKING_DLM=m
# CONFIG_OCFS2_FS is not set   # CONFIG_OCFS2_FS is not set
# CONFIG_MINIX_FS is not set   # CONFIG_MINIX_FS is not set
# CONFIG_ROMFS_FS is not set   # CONFIG_ROMFS_FS is not set
CONFIG_INOTIFY=y             CONFIG_INOTIFY=y
CONFIG_INOTIFY_USER=y        CONFIG_INOTIFY_USER=y
CONFIG_QUOTA=y               CONFIG_QUOTA=y
# CONFIG_QFMT_V1 is not set    # CONFIG_QFMT_V1 is not set
CONFIG_QFMT_V2=y            CONFIG_QFMT_V2=y
CONFIG_QUOTACTL=y           CONFIG_QUOTACTL=y
CONFIG_DNOTIFY=y            CONFIG_DNOTIFY=y
# CONFIG_AUTOFS_FS is not set  # CONFIG_AUTOFS_FS is not set
CONFIG_AUTOFS4_FS=m         CONFIG_AUTOFS4_FS=m
# CONFIG_FUSE_FS is not set    | CONFIG_FUSE_FS=m

#                               #
# Caches                        # Caches
#                               #
CONFIG_FSCACHE=m            CONFIG_FSCACHE=m

#                               #
# CD-ROM/DVD Filesystems       # CD-ROM/DVD Filesystems
#                               #
CONFIG_ISO9660_FS=y         CONFIG_ISO9660_FS=y
CONFIG_JOLIET=y             CONFIG_JOLIET=y
CONFIG_ZISOFS=y             CONFIG_ZISOFS=y
CONFIG_ZISOFS_FS=y         CONFIG_ZISOFS_FS=y
CONFIG_UDF_FS=m             CONFIG_UDF_FS=m
CONFIG_UDF_NLS=y           CONFIG_UDF_NLS=y
CONFIG_CACHEFILES=m        CONFIG_CACHEFILES=m
CONFIG_CACHEFILES_DEBUG=y   CONFIG_CACHEFILES_DEBUG=y

#                               #
# DOS/FAT/NT Filesystems       # DOS/FAT/NT Filesystems
#                               #
CONFIG_FAT_FS=m             CONFIG_FAT_FS=m
CONFIG_MSDFS_FS=m          CONFIG_MSDFS_FS=m
CONFIG_VFAT_FS=m           CONFIG_VFAT_FS=m
CONFIG_FAT_DEFAULT_CODEPAGE=437 CONFIG_FAT_DEFAULT_CODEPAGE=437
CONFIG_FAT_DEFAULT_IOCHARSET="ascii" CONFIG_FAT_DEFAULT_IOCHARSET="ascii"
# CONFIG_NTFS_FS is not set    | CONFIG_NTFS_FS=m
    > # CONFIG_NTFS_DEBUG is not set
    > CONFIG_NTFS_RW=y

#                               #
# Pseudo filesystems          # Pseudo filesystems
#                               #
CONFIG_PROC_FS=y           CONFIG_PROC_FS=y
CONFIG_PROC_KCORE=y        CONFIG_PROC_KCORE=y
CONFIG_PROC_VMCORE=y       CONFIG_PROC_VMCORE=y
CONFIG_SYSFS=y             CONFIG_SYSFS=y
CONFIG_TMPFS=y             CONFIG_TMPFS=y
CONFIG_HUGETLBFS=y         CONFIG_HUGETLBFS=y
CONFIG_HUGETLB_PAGE=y      CONFIG_HUGETLB_PAGE=y
CONFIG_RAMFS=y             CONFIG_RAMFS=y
CONFIG_CONFIGFS_FS=m       CONFIG_CONFIGFS_FS=m

#                               #
# Miscellaneous filesystems    # Miscellaneous filesystems

```

```

# #
# CONFIG_ADFS_FS is not set # CONFIG_ADFS_FS is not set
# CONFIG_AFFS_FS is not set # CONFIG_AFFS_FS is not set
CONFIG_HFS_FS=m CONFIG_HFS_FS=m
CONFIG_HFSPLUS_FS=m CONFIG_HFSPLUS_FS=m
# CONFIG_BEFS_FS is not set # CONFIG_BEFS_FS is not set
# CONFIG_BFS_FS is not set # CONFIG_BFS_FS is not set
# CONFIG_EFS_FS is not set # CONFIG_EFS_FS is not set
# CONFIG_JFFS_FS is not set # CONFIG_JFFS_FS is not set
CONFIG_JFFS2_FS=m CONFIG_JFFS2_FS=m
CONFIG_JFFS2_FS_DEBUG=0 CONFIG_JFFS2_FS_DEBUG=0
CONFIG_JFFS2_FS_WRITEBUFFER=y CONFIG_JFFS2_FS_WRITEBUFFER=y
CONFIG_JFFS2_SUMMARY=y CONFIG_JFFS2_SUMMARY=y
# CONFIG_JFFS2_FS_XATTR is not set # CONFIG_JFFS2_FS_XATTR is not set
# CONFIG_JFFS2_COMPRESSION_OPTIONS is not set # CONFIG_JFFS2_COMPRESSION_OPTIONS is not set
CONFIG_JFFS2_ZLIB=y CONFIG_JFFS2_ZLIB=y
CONFIG_JFFS2_RTTIME=y CONFIG_JFFS2_RTTIME=y
# CONFIG_JFFS2_RUBIN is not set # CONFIG_JFFS2_RUBIN is not set
CONFIG_CRAMFS=m CONFIG_CRAMFS=m
CONFIG_SQUASHFS=m CONFIG_SQUASHFS=m
# CONFIG_SQUASHFS_EMBEDDED is not set # CONFIG_SQUASHFS_EMBEDDED is not set
CONFIG_SQUASHFS_FRAGMENT_CACHE_SIZE=3 CONFIG_SQUASHFS_FRAGMENT_CACHE_SIZE=3
# CONFIG_SQUASHFS_VMALLOC is not set # CONFIG_SQUASHFS_VMALLOC is not set
CONFIG_VXFS_FS=m CONFIG_VXFS_FS=m
# CONFIG_HPFS_FS is not set # CONFIG_HPFS_FS is not set
# CONFIG_QNX4FS_FS is not set # CONFIG_QNX4FS_FS is not set
# CONFIG_SYSV_FS is not set # CONFIG_SYSV_FS is not set
# CONFIG_UFS_FS is not set # CONFIG_UFS_FS is not set

# #
# Network File Systems # Network File Systems
# #
CONFIG_NFS_FS=m CONFIG_NFS_FS=m
CONFIG_NFS_V3=y CONFIG_NFS_V3=y
CONFIG_NFS_V3_ACL=y CONFIG_NFS_V3_ACL=y
CONFIG_NFS_V4=y CONFIG_NFS_V4=y
CONFIG_NFS_FSCACHE=y CONFIG_NFS_FSCACHE=y
CONFIG_NFS_DIRECTIO=y CONFIG_NFS_DIRECTIO=y
CONFIG_NFSD=m CONFIG_NFSD=m
CONFIG_NFSD_V3=y CONFIG_NFSD_V3=y
CONFIG_NFSD_V3_ACL=y CONFIG_NFSD_V3_ACL=y
CONFIG_NFSD_V4=y CONFIG_NFSD_V4=y
CONFIG_NFSD_TCP=y CONFIG_NFSD_TCP=y
CONFIG_LOCKD=m CONFIG_LOCKD=m
CONFIG_LOCKD_V4=y CONFIG_LOCKD_V4=y
CONFIG_EXPORTFS=m CONFIG_EXPORTFS=m
CONFIG_NFS_ACL_SUPPORT=m CONFIG_NFS_ACL_SUPPORT=m
CONFIG_NFS_COMMON=y CONFIG_NFS_COMMON=y
CONFIG_SUNRPC=m CONFIG_SUNRPC=m
CONFIG_SUNRPC_GSS=m CONFIG_SUNRPC_GSS=m
CONFIG_RPCSEC_GSS_KRB5=m CONFIG_RPCSEC_GSS_KRB5=m
CONFIG_RPCSEC_GSS_SPKM3=m CONFIG_RPCSEC_GSS_SPKM3=m
# CONFIG_SMB_FS is not set # CONFIG_SMB_FS is not set
CONFIG_CIFS=m CONFIG_CIFS=m
# CONFIG_CIFS_STATS is not set # CONFIG_CIFS_STATS is not set
CONFIG_CIFS_WEAK_PW_HASH=y CONFIG_CIFS_WEAK_PW_HASH=y
CONFIG_CIFS_XATTR=y CONFIG_CIFS_XATTR=y
CONFIG_CIFS_POSIX=y CONFIG_CIFS_POSIX=y
# CONFIG_CIFS_DEBUG2 is not set # CONFIG_CIFS_DEBUG2 is not set
# CONFIG_CIFS_EXPERIMENTAL is not set # CONFIG_CIFS_EXPERIMENTAL is not set
# CONFIG_NCP_FS is not set | CONFIG_NCP_FS=m
> CONFIG_NCPFS_PACKET_SIGNING=y
> CONFIG_NCPFS_IOCTL_LOCKING=y
> CONFIG_NCPFS_STRONG=y
> CONFIG_NCPFS_NFS_NS=y
> CONFIG_NCPFS_OS2_NS=y
> CONFIG_NCPFS_SMALLDOS=y
> CONFIG_NCPFS_NLS=y
> CONFIG_NCPFS_EXTRAS=y
# CONFIG_CODA_FS is not set # CONFIG_CODA_FS is not set
# CONFIG_AFS_FS is not set # CONFIG_AFS_FS is not set
# CONFIG_9P_FS is not set # CONFIG_9P_FS is not set

# #
# Partition Types # Partition Types
# #
CONFIG_PARTITION_ADVANCED=y CONFIG_PARTITION_ADVANCED=y
# CONFIG_ACORN_PARTITION is not set # CONFIG_ACORN_PARTITION is not set
CONFIG_OSF_PARTITION=y CONFIG_OSF_PARTITION=y

```

```

CONFIG_AMIGA_PARTITION=y      CONFIG_AMIGA_PARTITION=y
# CONFIG_ATARI_PARTITION is not set # CONFIG_ATARI_PARTITION is not set
CONFIG_MAC_PARTITION=y       CONFIG_MAC_PARTITION=y
CONFIG_MSDOS_PARTITION=y     CONFIG_MSDOS_PARTITION=y
CONFIG_BSD_DISKLABEL=y      CONFIG_BSD_DISKLABEL=y
CONFIG_MINIX_SUBPARTITION=y  CONFIG_MINIX_SUBPARTITION=y
CONFIG_SOLARIS_X86_PARTITION=y CONFIG_SOLARIS_X86_PARTITION=y
CONFIG_UNIXWARE_DISKLABEL=y  CONFIG_UNIXWARE_DISKLABEL=y
# CONFIG_LDM_PARTITION is not set | CONFIG_LDM_PARTITION=y
> # CONFIG_LDM_DEBUG is not set
CONFIG_SGI_PARTITION=y       CONFIG_SGI_PARTITION=y
# CONFIG_ULTRIX_PARTITION is not set # CONFIG_ULTRIX_PARTITION is not set
CONFIG_SUN_PARTITION=y      CONFIG_SUN_PARTITION=y
CONFIG_KARMA_PARTITION=y     CONFIG_KARMA_PARTITION=y
CONFIG_EFI_PARTITION=y       CONFIG_EFI_PARTITION=y

# #
# Native Language Support # Native Language Support
# #
CONFIG_NLS=y                 CONFIG_NLS=y
CONFIG_NLS_DEFAULT="utf8"   CONFIG_NLS_DEFAULT="utf8"
CONFIG_NLS_CODEPAGE_437=y   CONFIG_NLS_CODEPAGE_437=y
CONFIG_NLS_CODEPAGE_737=m   CONFIG_NLS_CODEPAGE_737=m
CONFIG_NLS_CODEPAGE_775=m   CONFIG_NLS_CODEPAGE_775=m
CONFIG_NLS_CODEPAGE_850=m   CONFIG_NLS_CODEPAGE_850=m
CONFIG_NLS_CODEPAGE_852=m   CONFIG_NLS_CODEPAGE_852=m
CONFIG_NLS_CODEPAGE_855=m   CONFIG_NLS_CODEPAGE_855=m
CONFIG_NLS_CODEPAGE_857=m   CONFIG_NLS_CODEPAGE_857=m
CONFIG_NLS_CODEPAGE_860=m   CONFIG_NLS_CODEPAGE_860=m
CONFIG_NLS_CODEPAGE_861=m   CONFIG_NLS_CODEPAGE_861=m
CONFIG_NLS_CODEPAGE_862=m   CONFIG_NLS_CODEPAGE_862=m
CONFIG_NLS_CODEPAGE_863=m   CONFIG_NLS_CODEPAGE_863=m
CONFIG_NLS_CODEPAGE_864=m   CONFIG_NLS_CODEPAGE_864=m
CONFIG_NLS_CODEPAGE_865=m   CONFIG_NLS_CODEPAGE_865=m
CONFIG_NLS_CODEPAGE_866=m   CONFIG_NLS_CODEPAGE_866=m
CONFIG_NLS_CODEPAGE_869=m   CONFIG_NLS_CODEPAGE_869=m
CONFIG_NLS_CODEPAGE_936=m   CONFIG_NLS_CODEPAGE_936=m
CONFIG_NLS_CODEPAGE_950=m   CONFIG_NLS_CODEPAGE_950=m
CONFIG_NLS_CODEPAGE_932=m   CONFIG_NLS_CODEPAGE_932=m
CONFIG_NLS_CODEPAGE_949=m   CONFIG_NLS_CODEPAGE_949=m
CONFIG_NLS_CODEPAGE_874=m   CONFIG_NLS_CODEPAGE_874=m
CONFIG_NLS_ISO8859_8=m      CONFIG_NLS_ISO8859_8=m
CONFIG_NLS_CODEPAGE_1250=m  CONFIG_NLS_CODEPAGE_1250=m
CONFIG_NLS_CODEPAGE_1251=m  CONFIG_NLS_CODEPAGE_1251=m
CONFIG_NLS_ASCII=y         CONFIG_NLS_ASCII=y
CONFIG_NLS_ISO8859_1=m     CONFIG_NLS_ISO8859_1=m
CONFIG_NLS_ISO8859_2=m     CONFIG_NLS_ISO8859_2=m
CONFIG_NLS_ISO8859_3=m     CONFIG_NLS_ISO8859_3=m
CONFIG_NLS_ISO8859_4=m     CONFIG_NLS_ISO8859_4=m
CONFIG_NLS_ISO8859_5=m     CONFIG_NLS_ISO8859_5=m
CONFIG_NLS_ISO8859_6=m     CONFIG_NLS_ISO8859_6=m
CONFIG_NLS_ISO8859_7=m     CONFIG_NLS_ISO8859_7=m
CONFIG_NLS_ISO8859_9=m     CONFIG_NLS_ISO8859_9=m
CONFIG_NLS_ISO8859_13=m    CONFIG_NLS_ISO8859_13=m
CONFIG_NLS_ISO8859_14=m    CONFIG_NLS_ISO8859_14=m
CONFIG_NLS_ISO8859_15=m    CONFIG_NLS_ISO8859_15=m
CONFIG_NLS_KOI8_R=m        CONFIG_NLS_KOI8_R=m
CONFIG_NLS_KOI8_U=m        CONFIG_NLS_KOI8_U=m
CONFIG_NLS_UTF8=m          CONFIG_NLS_UTF8=m

# #
# Distributed Lock Manager # Distributed Lock Manager
# #
CONFIG_DLM=m                CONFIG_DLM=m
CONFIG_DLM_TCP=y           CONFIG_DLM_TCP=y
# CONFIG_DLM_SCTP is not set # CONFIG_DLM_SCTP is not set
CONFIG_DLM_DEBUG=y         CONFIG_DLM_DEBUG=y

# #
# Instrumentation Support # Instrumentation Support
# #
CONFIG_PROFILING=y         CONFIG_PROFILING=y
CONFIG_OPROFILE=m          CONFIG_OPROFILE=m
CONFIG_KPROBES=y           CONFIG_KPROBES=y

# #
# Kernel hacking # Kernel hacking
# #
CONFIG_TRACE_IRQFLAGS_SUPPORT=y CONFIG_TRACE_IRQFLAGS_SUPPORT=y

```

```

# CONFIG_PRINTK_TIME is not set      # CONFIG_PRINTK_TIME is not set
CONFIG_MAGIC_SYSRQ=y      CONFIG_MAGIC_SYSRQ=y
# CONFIG_UNUSED_SYMBOLS is not set  # CONFIG_UNUSED_SYMBOLS is not set
CONFIG_DEBUG_KERNEL=y      CONFIG_DEBUG_KERNEL=y
CONFIG_LOG_BUF_SHIFT=17    CONFIG_LOG_BUF_SHIFT=17
CONFIG_DETECT_SOFTLOCKUP=y  CONFIG_DETECT_SOFTLOCKUP=y
CONFIG_SCHEDSTATS=y      CONFIG_SCHEDSTATS=y
# CONFIG_DEBUG_SLAB is not set      # CONFIG_DEBUG_SLAB is not set
# CONFIG_DEBUG_RT_MUTEXES is not set # CONFIG_DEBUG_RT_MUTEXES is not set
# CONFIG_RT_MUTEX_TESTER is not set # CONFIG_RT_MUTEX_TESTER is not set
# CONFIG_DEBUG_SPINLOCK is not set  # CONFIG_DEBUG_SPINLOCK is not set
# CONFIG_DEBUG_MUTEXES is not set   # CONFIG_DEBUG_MUTEXES is not set
# CONFIG_DEBUG_RWSEMS is not set    # CONFIG_DEBUG_RWSEMS is not set
# CONFIG_DEBUG_LOCK_ALLOC is not set # CONFIG_DEBUG_LOCK_ALLOC is not set
# CONFIG_PROVE_LOCKING is not set   # CONFIG_PROVE_LOCKING is not set
# CONFIG_DEBUG_SPINLOCK_SLEEP is not set # CONFIG_DEBUG_SPINLOCK_SLEEP is not set
# CONFIG_DEBUG_LOCKING_API_SELFTESTS is not set # CONFIG_DEBUG_LOCKING_API_SELFTESTS is not set
# CONFIG_DEBUG_KOBJECT is not set   # CONFIG_DEBUG_KOBJECT is not set
CONFIG_DEBUG_HIGHMEM=y    CONFIG_DEBUG_HIGHMEM=y
CONFIG_DEBUG_BUGVERBOSE=y  CONFIG_DEBUG_BUGVERBOSE=y
CONFIG_DEBUG_INFO=y      CONFIG_DEBUG_INFO=y
CONFIG_DEBUG_FS=y        CONFIG_DEBUG_FS=y
# CONFIG_DEBUG_VM is not set      # CONFIG_DEBUG_VM is not set
CONFIG_DEBUG_LIST=y      CONFIG_DEBUG_LIST=y
# CONFIG_FRAME_POINTER is not set   # CONFIG_FRAME_POINTER is not set
# CONFIG_FORCED_INLINING is not set # CONFIG_FORCED_INLINING is not set
CONFIG_BOOT_DELAY=y      CONFIG_BOOT_DELAY=y
# CONFIG_RCU_TORTURE_TEST is not set # CONFIG_RCU_TORTURE_TEST is not set
CONFIG_EARLY_PRINTK=y    CONFIG_EARLY_PRINTK=y
CONFIG_DEBUG_STACKOVERFLOW=y  CONFIG_DEBUG_STACKOVERFLOW=y
CONFIG_DEBUG_STACK_USAGE=y  CONFIG_DEBUG_STACK_USAGE=y

# #
# Page alloc debug is incompatible with Software Suspend on i # Page alloc debug is incompatible
# #
CONFIG_DEBUG_RODATA=y    CONFIG_DEBUG_RODATA=y
CONFIG_4KSTACKS=y      CONFIG_4KSTACKS=y
CONFIG_X86_FIND_SMP_CONFIG=y  CONFIG_X86_FIND_SMP_CONFIG=y
CONFIG_X86_MPPARSE=y    CONFIG_X86_MPPARSE=y
CONFIG_DOUBLEFAULT=y    CONFIG_DOUBLEFAULT=y

# #
# Security options      # Security options
# #
CONFIG_KEYS=y          CONFIG_KEYS=y
CONFIG_KEYS_DEBUG_PROC_KEYS=y  CONFIG_KEYS_DEBUG_PROC_KEYS=y
CONFIG_SECURITY=y      CONFIG_SECURITY=y
CONFIG_SECURITY_NETWORK=y  CONFIG_SECURITY_NETWORK=y
CONFIG_SECURITY_NETWORK_XFRM=y  CONFIG_SECURITY_NETWORK_XFRM=y
CONFIG_SECURITY_CAPABILITIES=y  CONFIG_SECURITY_CAPABILITIES=y
# CONFIG_SECURITY_ROOTPLUG is not set # CONFIG_SECURITY_ROOTPLUG is not set
# CONFIG_SECURITY_SECLVL is not set   # CONFIG_SECURITY_SECLVL is not set
CONFIG_SECURITY_SELINUX=y  CONFIG_SECURITY_SELINUX=y
CONFIG_SECURITY_SELINUX_BOOTPARAM=y  CONFIG_SECURITY_SELINUX_BOOTPARAM=y
CONFIG_SECURITY_SELINUX_BOOTPARAM_VALUE=1  CONFIG_SECURITY_SELINUX_BOOTPARAM_VALUE=1
CONFIG_SECURITY_SELINUX_DISABLE=y  CONFIG_SECURITY_SELINUX_DISABLE=y
CONFIG_SECURITY_SELINUX_DEVELOP=y  CONFIG_SECURITY_SELINUX_DEVELOP=y
CONFIG_SECURITY_SELINUX_AVC_STATS=y  CONFIG_SECURITY_SELINUX_AVC_STATS=y
CONFIG_SECURITY_SELINUX_CHECKREQPROT_VALUE=1  CONFIG_SECURITY_SELINUX_CHECKREQPROT_VALUE=1
CONFIG_SECURITY_SELINUX_ENABLE_SECMARK_DEFAULT=y  CONFIG_SECURITY_SELINUX_ENABLE_SECMARK_DEFAULT
# CONFIG_SECURITY_SELINUX_POLICYDB_VERSION_MAX is not set # CONFIG_SECURITY_SELINUX_POLICYDB_VER

# #
# Cryptographic options  # Cryptographic options
# #
CONFIG_CRYPT=y        CONFIG_CRYPT=y
CONFIG_CRYPT_HMAC=y   CONFIG_CRYPT_HMAC=y
CONFIG_CRYPT_NULL=m   CONFIG_CRYPT_NULL=m
CONFIG_CRYPT_MD4=m    CONFIG_CRYPT_MD4=m
CONFIG_CRYPT_MD5=m    CONFIG_CRYPT_MD5=m
CONFIG_CRYPT_SHA1=y   CONFIG_CRYPT_SHA1=y
CONFIG_CRYPT_SHA256=m  CONFIG_CRYPT_SHA256=m
CONFIG_CRYPT_SHA512=m  CONFIG_CRYPT_SHA512=m
CONFIG_CRYPT_WP512=m   CONFIG_CRYPT_WP512=m
CONFIG_CRYPT_TGR192=m  CONFIG_CRYPT_TGR192=m
CONFIG_CRYPT_DES=m     CONFIG_CRYPT_DES=m
CONFIG_CRYPT_BLOWFISH=m  CONFIG_CRYPT_BLOWFISH=m
CONFIG_CRYPT_TWOFISH=m  CONFIG_CRYPT_TWOFISH=m
CONFIG_CRYPT_SERPENT=m  CONFIG_CRYPT_SERPENT=m

```

```

CONFIG_CRYPT0_AES=m          CONFIG_CRYPT0_AES=m
CONFIG_CRYPT0_AES_586=m     CONFIG_CRYPT0_AES_586=m
CONFIG_CRYPT0_CAST5=m       CONFIG_CRYPT0_CAST5=m
CONFIG_CRYPT0_CAST6=m       CONFIG_CRYPT0_CAST6=m
CONFIG_CRYPT0_TEA=m         CONFIG_CRYPT0_TEA=m
CONFIG_CRYPT0_ARC4=m        CONFIG_CRYPT0_ARC4=m
CONFIG_CRYPT0_KHAZAD=m      CONFIG_CRYPT0_KHAZAD=m
CONFIG_CRYPT0_ANUBIS=m      CONFIG_CRYPT0_ANUBIS=m
CONFIG_CRYPT0_DEFLATE=m     CONFIG_CRYPT0_DEFLATE=m
CONFIG_CRYPT0_MICHAEL_MIC=m CONFIG_CRYPT0_MICHAEL_MIC=m
CONFIG_CRYPT0_CRC32C=y      CONFIG_CRYPT0_CRC32C=y
# CONFIG_CRYPT0_TEST is not set # CONFIG_CRYPT0_TEST is not set
CONFIG_CRYPT0_SIGNATURE=y   CONFIG_CRYPT0_SIGNATURE=y
CONFIG_CRYPT0_SIGNATURE_DSA=y CONFIG_CRYPT0_SIGNATURE_DSA=y
CONFIG_CRYPT0_MPILIB=y      CONFIG_CRYPT0_MPILIB=y

# #
# Hardware crypto devices # Hardware crypto devices
# #
CONFIG_CRYPT0_DEV_PADLOCK=m CONFIG_CRYPT0_DEV_PADLOCK=m
CONFIG_CRYPT0_DEV_PADLOCK_AES=y CONFIG_CRYPT0_DEV_PADLOCK_AES=y

# #
# Library routines # Library routines
# #
CONFIG_CRC_CCITT=m          CONFIG_CRC_CCITT=m
CONFIG_CRC16=m              CONFIG_CRC16=m
CONFIG_CRC32=y              CONFIG_CRC32=y
CONFIG_LIBCRC32C=y          CONFIG_LIBCRC32C=y
CONFIG_AUDIT_GENERIC=y      CONFIG_AUDIT_GENERIC=y
CONFIG_ZLIB_INFLATE=y       CONFIG_ZLIB_INFLATE=y
CONFIG_ZLIB_DEFLATE=m       CONFIG_ZLIB_DEFLATE=m
CONFIG_REED_SOLOMON=m       CONFIG_REED_SOLOMON=m
CONFIG_REED_SOLOMON_DEC16=y CONFIG_REED_SOLOMON_DEC16=y
CONFIG_TEXTSEARCH=y         CONFIG_TEXTSEARCH=y
CONFIG_TEXTSEARCH_KMP=m     CONFIG_TEXTSEARCH_KMP=m
CONFIG_TEXTSEARCH_BM=m      CONFIG_TEXTSEARCH_BM=m
CONFIG_TEXTSEARCH_FSM=m     CONFIG_TEXTSEARCH_FSM=m
CONFIG_PLIST=y              CONFIG_PLIST=y
CONFIG_GENERIC_HARDIRQS=y   CONFIG_GENERIC_HARDIRQS=y
CONFIG_GENERIC_IRQ_PROBE=y  CONFIG_GENERIC_IRQ_PROBE=y
CONFIG_GENERIC_PENDING_IRQ=y CONFIG_GENERIC_PENDING_IRQ=y
CONFIG_X86_SMP=y            CONFIG_X86_SMP=y
CONFIG_X86_HT=y             CONFIG_X86_HT=y
CONFIG_X86_BIOS_REBOOT=y    CONFIG_X86_BIOS_REBOOT=y
CONFIG_X86_TRAMPOLINE=y     CONFIG_X86_TRAMPOLINE=y
CONFIG_KTIME_SCALAR=y       CONFIG_KTIME_SCALAR=y

```

Revision #1

Created 2021-04-29 11:21:21 UTC by magenbrot

Updated 2021-04-29 11:21:57 UTC by magenbrot